

SECTION 6 ELECTRICAL PARTS LIST

B

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

When indicating parts by reference number, please include the board name.

- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS

- All resistors are in ohms
- F : nonflammable

CAPACITORS

- PF : μ MF

- The components identified by \boxtimes in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
Should replacement be required, replace only with the value originally used.
- There are some cases the reference number on one board overlaps on the other board. Therefore, when ordering parts by the reference number, please include the board name.

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
	* A-1135-897-A	B COMPLETE PC BOARD *****		C133	1-135-091-00	TANTAL. CHIP 1MF 20% 16V	
	1-562-579-21	RECEPTACLE, CONNECTOR 2P (CN35, 36, 37, 38, 39, 40)		C134	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
	* 4-056-085-01	HOLDER (BB), TR (IC606, 608, 609, 611)		C135	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
	* 4-057-871-01	HOLDER, HEAT SINK (BB)(IC601, 604)		C136	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
	4-057-872-01	HEAT SINK (BB)(IC601, 604)		C137	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
	7-682-648-09	SCREW +PS 3X8		C138	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
		< CAPACITOR >		C139	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
C101	1-109-982-11	CERAMIC CHIP 1MF 10% 10V		C140	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C102	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C141	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C103	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C142	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C104	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C143	1-135-091-00	TANTAL. CHIP 1MF 20% 16V	
C105	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C144	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
C106	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C145	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C107	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C146	1-135-091-00	TANTAL. CHIP 1MF 20% 16V	
C108	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C147	1-128-004-11	ELECT CHIP 10MF 20% 16V	
C109	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C148	1-128-004-11	ELECT CHIP 10MF 20% 16V	
C110	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C149	1-128-004-11	ELECT CHIP 10MF 20% 16V	
C111	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C150	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C112	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C151	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C113	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C152	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C114	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C153	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C115	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C154	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C116	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C155	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C117	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C156	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C118	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C157	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C119	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C158	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C120	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C159	1-128-004-11	ELECT CHIP 10MF 20% 16V	
C121	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C160	1-109-982-11	CERAMIC CHIP 1MF 10% 10V	
C122	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C161	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C123	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C162	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C124	1-109-982-11	CERAMIC CHIP 1MF 10% 10V		C163	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C125	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C164	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C126	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C165	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
C127	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C166	1-163-809-11	CERAMIC CHIP 0.047MF 10% 25V	
C128	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C167	1-109-982-11	CERAMIC CHIP 1MF 10% 10V	
C129	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C168	1-126-204-11	ELECT 47MF 20% 16V	
C131	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C169	1-110-666-11	ELECT CHIP 22MF 20% 6.3V	
C132	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		C170	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
				C500	1-135-157-21	TANTAL. CHIP 10MF 20% 6.3V	
				C501	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V	
				C502	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
C503	1-128-453-21	ELECT CHIP	47MF	20%	6.3V	C573	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C504	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C574	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C505	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C575	1-163-245-11	CERAMIC CHIP	56PF	5%	50V
C506	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C576	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C507	1-128-004-11	ELECT CHIP	10MF	20%	16V	C577	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C508	1-128-453-21	ELECT CHIP	47MF	20%	6.3V	C578	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C509	1-110-666-11	ELECT CHIP	22MF	20%	6.3V	C579	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C510	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C580	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C513	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C581	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C515	1-128-453-21	ELECT CHIP	47MF	20%	6.3V	C582	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C516	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C583	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C517	1-109-982-11	CERAMIC CHIP	1MF	10%	10V	C584	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C520	1-128-453-21	ELECT CHIP	47MF	20%	6.3V	C585	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C523	1-135-157-21	TANTAL. CHIP	10MF	20%	6.3V	C586	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C524	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C587	1-135-092-21	TANTAL. CHIP	3.3MF	20%	16V
C525	1-128-453-21	ELECT CHIP	47MF	20%	6.3V	C588	1-128-004-11	ELECT CHIP	10MF	20%	16V
C526	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C589	1-128-004-11	ELECT CHIP	10MF	20%	16V
C527	1-135-157-21	TANTAL. CHIP	10MF	20%	6.3V	C590	1-128-004-11	ELECT CHIP	10MF	20%	16V
C530	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C591	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C531	1-128-453-21	ELECT CHIP	47MF	20%	6.3V	C592	1-128-004-11	ELECT CHIP	10MF	20%	16V
C533	1-110-666-11	ELECT CHIP	22MF	20%	6.3V	C593	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C534	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C594	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C535	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C595	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C536	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C596	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C538	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C597	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C539	1-109-982-11	CERAMIC CHIP	1MF	10%	10V	C598	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C540	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C599	1-128-004-11	ELECT CHIP	10MF	20%	16V
C541	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C600	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C542	1-128-004-11	ELECT CHIP	10MF	20%	16V	C601	1-126-935-11	ELECT	470MF	20%	16V
C543	1-135-157-21	TANTAL. CHIP	10MF	20%	6.3V	C602	1-128-004-11	ELECT CHIP	10MF	20%	16V
C544	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C604	1-128-004-11	ELECT CHIP	10MF	20%	16V
C545	1-135-157-21	TANTAL. CHIP	10MF	20%	6.3V	C605	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C546	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C606	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C547	1-110-666-11	ELECT CHIP	22MF	20%	6.3V	C607	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C548	1-126-200-11	ELECT	10MF	20%	35V	C608	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C549	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C609	1-128-004-11	ELECT CHIP	10MF	20%	16V
C550	1-136-177-00	FILM	1MF	5%	50V	C610	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C551	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C611	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C552	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C613	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C554	1-128-004-11	ELECT CHIP	10MF	20%	16V	C614	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C555	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C615	1-128-004-11	ELECT CHIP	10MF	20%	16V
C556	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C616	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C557	1-109-982-11	CERAMIC CHIP	1MF	10%	10V	C617	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C558	1-128-004-11	ELECT CHIP	10MF	20%	16V	C618	1-128-004-11	ELECT CHIP	10MF	20%	16V
C559	1-128-004-11	ELECT CHIP	10MF	20%	16V	C619	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C560	1-135-157-21	TANTAL. CHIP	10MF	20%	6.3V	C620	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C561	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C621	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C562	1-107-417-11	ELECT CHIP	33MF	20%	25V	C622	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C563	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C623	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C564	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C625	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C565	1-128-004-11	ELECT CHIP	10MF	20%	16V	C626	1-128-004-11	ELECT CHIP	10MF	20%	16V
C566	1-126-200-11	ELECT	10MF	20%	35V	C627	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C567	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C628	1-128-004-11	ELECT CHIP	10MF	20%	16V
C568	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C629	1-128-004-11	ELECT CHIP	10MF	20%	16V
C569	1-126-200-11	ELECT	10MF	20%	35V	C630	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C570	1-136-177-00	FILM	1MF	5%	50V	C631	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C571	1-107-417-11	ELECT CHIP	33MF	20%	25V	C632	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C572	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C633	1-126-200-11	ELECT	10MF	20%	35V
						C634	1-128-004-11	ELECT CHIP	10MF	20%	16V

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
C635	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C753	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C636	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C754	1-128-004-11	ELECT CHIP	10MF	20%	16V
C637	1-126-200-11	ELECT	10MF	20%	35V	C755	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C638	1-128-004-11	ELECT CHIP	10MF	20%	16V	C756	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C639	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C757	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C640	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C758	1-128-004-11	ELECT CHIP	10MF	20%	16V
C641	1-126-200-11	ELECT	10MF	20%	35V	C759	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C642	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C760	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C643	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C761	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C644	1-128-004-11	ELECT CHIP	10MF	20%	16V	C762	1-128-004-11	ELECT CHIP	10MF	20%	16V
C645	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	C763	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C646	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C764	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C647	1-128-004-11	ELECT CHIP	10MF	20%	16V	C765	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C648	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C766	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C649	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C767	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C650	1-128-004-11	ELECT CHIP	10MF	20%	16V	C801	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C651	1-128-004-11	ELECT CHIP	10MF	20%	16V	C802	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C652	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C803	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C653	1-126-941-11	ELECT	470MF	20%	25V	C804	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C654	1-128-004-11	ELECT CHIP	10MF	20%	16V	C805	1-128-004-11	ELECT CHIP	10MF	20%	16V
C655	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C806	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C656	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C808	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C657	1-128-004-11	ELECT CHIP	10MF	20%	16V	C810	1-128-004-11	ELECT CHIP	10MF	20%	16V
C658	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C811	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C659	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C813	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C660	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C850	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C661	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C851	1-163-085-00	CERAMIC CHIP	2PF	0.25PF	50V
C662	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C852	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C663	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C853	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C664	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C854	1-128-004-11	ELECT CHIP	10MF	20%	16V
C665	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C856	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C666	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C857	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C667	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C858	1-128-004-11	ELECT CHIP	10MF	20%	16V
C668	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C859	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C669	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C860	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C670	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C861	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C672	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C862	1-128-004-11	ELECT CHIP	10MF	20%	16V
C674	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C863	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C675	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C864	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C677	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C865	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C678	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C866	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C679	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C867	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C680	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	C868	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C682	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C901	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C683	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C902	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C701	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C903	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C702	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C904	1-128-004-11	ELECT CHIP	10MF	20%	16V
C703	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C905	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C704	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C906	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C705	1-128-004-11	ELECT CHIP	10MF	20%	16V	C908	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C706	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C910	1-128-004-11	ELECT CHIP	10MF	20%	16V
C708	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C911	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C710	1-128-004-11	ELECT CHIP	10MF	20%	16V	C913	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C711	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C950	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C713	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C951	1-163-085-00	CERAMIC CHIP	2PF	0.25PF	50V
C750	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C952	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C751	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C953	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C752	1-163-085-00	CERAMIC CHIP	2PF	0.25PF	50V	C954	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
						C955	1-128-004-11	ELECT CHIP	10MF	20%	16V

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C956	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D855	8-719-800-76	DIODE 1SS226	
C957	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D856	8-719-801-78	DIODE 1SS184	
C958	1-128-004-11	ELECT CHIP	10MF 20% 16V	D857	8-719-801-78	DIODE 1SS184	
C959	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D858	8-719-801-78	DIODE 1SS184	
C960	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D859	8-719-800-76	DIODE 1SS226	
C961	1-128-004-11	ELECT CHIP	10MF 20% 16V	D860	8-719-801-78	DIODE 1SS184	
C962	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D900	8-719-800-76	DIODE 1SS226	
C963	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D903	8-719-801-78	DIODE 1SS184	
C964	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D950	8-719-801-78	DIODE 1SS184	
C965	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D951	8-719-801-78	DIODE 1SS184	
C966	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	D952	8-719-801-78	DIODE 1SS184	
< CONNECTOR >				D953	8-719-801-78	DIODE 1SS184	
CN35	* 1-564-948-21	PIN, CONNECTOR 3P		D954	8-719-801-78	DIODE 1SS184	
CN36	* 1-564-948-21	PIN, CONNECTOR 3P		D955	8-719-801-78	DIODE 1SS184	
CN37	* 1-564-948-21	PIN, CONNECTOR 3P		D956	8-719-801-78	DIODE 1SS184	
CN38	* 1-564-948-21	PIN, CONNECTOR 3P		D957	8-719-800-76	DIODE 1SS226	
CN39	* 1-564-948-21	PIN, CONNECTOR 3P		D958	8-719-801-78	DIODE 1SS184	
CN40	* 1-564-948-21	PIN, CONNECTOR 3P		D959	8-719-800-76	DIODE 1SS226	
CN431	* 1-766-305-11	PIN, PC CONNECTOR 96P		D960	8-719-801-78	DIODE 1SS184	
CN432	* 1-764-790-11	SOCKET, CONNECTOR 80P		< IC >			
< DIODE >				IC100	8-759-251-32	IC NJM4200M	
D100	8-719-801-78	DIODE 1SS184		IC101	8-759-251-32	IC NJM4200M	
D101	8-719-801-78	DIODE 1SS184		IC102	8-759-251-32	IC NJM4200M	
D102	8-719-801-78	DIODE 1SS184		IC103	8-759-925-72	IC SN74HC02ANS	
D103	8-719-801-78	DIODE 1SS184		IC104	8-759-285-80	IC PC74HC164D-T	
D104	8-719-105-82	DIODE RD5.1M-B2		IC105	8-759-981-48	IC TL082M	
D105	8-719-801-78	DIODE 1SS184		IC106	8-759-981-48	IC TL082M	
D500	8-719-800-76	DIODE 1SS226		IC107	8-759-981-48	IC TL082M	
D501	8-719-800-76	DIODE 1SS226		IC108	8-759-981-48	IC TL082M	
D502	8-719-800-76	DIODE 1SS226		IC109	8-759-981-48	IC TL082M	
D503	8-719-800-76	DIODE 1SS226		IC110	8-759-981-48	IC TL082M	
D504	8-719-801-78	DIODE 1SS184		IC111	8-759-100-71	IC MAX4050HBP	
D505	8-719-800-76	DIODE 1SS226		IC112	8-752-072-94	IC CXA1875AM-T4	
D506	8-719-801-78	DIODE 1SS184		IC113	8-759-981-48	IC TL082M	
D507	8-719-801-78	DIODE 1SS184		IC114	8-759-981-48	IC TL082M	
D602	8-719-800-76	DIODE 1SS226		IC115	8-759-981-48	IC TL082M	
D700	8-719-800-76	DIODE 1SS226		IC116	8-752-072-94	IC CXA1875AM-T4	
D703	8-719-801-78	DIODE 1SS184		IC117	8-752-072-94	IC CXA1875AM-T4	
D750	8-719-801-78	DIODE 1SS184		IC118	8-759-100-93	IC μPC393G2	
D751	8-719-801-78	DIODE 1SS184		IC119	8-759-981-48	IC TL082M	
D752	8-719-801-78	DIODE 1SS184		IC120	8-759-981-48	IC TL082M	
D753	8-719-801-78	DIODE 1SS184		IC121	8-759-062-66	IC TC7S66F	
D754	8-719-801-78	DIODE 1SS184		IC501	8-752-052-77	IC CXA1450M	
D755	8-719-800-76	DIODE 1SS226		IC502	8-759-431-38	IC MAX4121CSA-TE2	
D756	8-719-801-78	DIODE 1SS184		IC503	8-759-100-96	IC μPC4558G2	
D757	8-719-801-78	DIODE 1SS184		IC504	8-759-457-54	IC AD835AR-REE	
D758	8-719-801-78	DIODE 1SS184		IC506	8-752-052-77	IC CXA1450M	
D759	8-719-800-76	DIODE 1SS226		IC507	8-759-431-38	IC MAX4121CSA-TE2	
D760	8-719-801-78	DIODE 1SS184		IC508	8-759-100-96	IC μPC4558G2	
D800	8-719-800-76	DIODE 1SS226		IC509	8-759-457-54	IC AD835AR-REE	
D803	8-719-801-78	DIODE 1SS184		IC510	8-752-052-77	IC CXA1450M	
D850	8-719-801-78	DIODE 1SS184		IC511	8-759-431-38	IC MAX4121CSA-TE2	
D851	8-719-801-78	DIODE 1SS184		IC512	8-759-981-48	IC TL082M	
D852	8-719-801-78	DIODE 1SS184		IC513	8-759-457-54	IC AD835AR-REE	
D853	8-719-801-78	DIODE 1SS184		IC514	8-759-457-53	IC GS1881-CTA	
D854	8-719-801-78	DIODE 1SS184		IC515	8-759-092-82	IC SN75157PS-ELL2000	
				IC516	8-759-431-38	IC MAX4121CSA-TE2	
				IC517	8-759-431-38	IC MAX4121CSA-TE2	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
IC518	8-759-431-38	IC MAX4121CSA-TE2		Q104	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC519	8-759-981-48	IC TL082M		Q105	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC520	8-759-062-66	IC TC7S66F		Q106	8-729-216-22	TRANSISTOR 2SA1162-G	
IC521	8-759-242-64	IC TC4W53F		Q107	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC522	8-759-035-93	IC SC7S32F		Q108	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC600	8-759-431-38	IC MAX4121CSA-TE2		Q109	8-729-216-22	TRANSISTOR 2SA1162-G	
IC601	8-759-445-85	IC LM1283		Q110	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC602	8-759-431-38	IC MAX4121CSA-TE2		Q111	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC603	8-759-431-38	IC MAX4121CSA-TE2		Q112	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC604	8-752-075-54	IC CXA3069S		Q113	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC605	8-759-031-84	IC SC7S04F		Q114	8-729-216-22	TRANSISTOR 2SA1162-G	
IC606	8-759-144-82	IC μ PC2405HF		Q115	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC607	8-759-431-39	IC MAX8213BCSE-TE2		Q116	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC608	8-759-231-58	IC TA7812S		Q500	8-729-302-77	TRANSISTOR 2SC1906	
IC609	8-759-231-58	IC TA7812S		Q501	8-729-116-04	TRANSISTOR 2SK160-K4	
IC610	8-759-929-65	IC LM7912CT		Q502	8-729-302-77	TRANSISTOR 2SC1906	
IC611	8-759-701-59	IC NJM78M09FA		Q503	8-729-116-04	TRANSISTOR 2SK160-K4	
IC612	8-759-247-67	IC LM2990T-5.0		Q504	8-729-302-77	TRANSISTOR 2SC1906	
IC613	8-759-448-65	IC EL2186CS-TE2		Q505	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC614	8-759-448-65	IC EL2186CS-TE2		Q506	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC615	8-759-448-65	IC EL2186CS-TE2		Q507	8-729-216-22	TRANSISTOR 2SA1162-G	
IC616	8-759-234-20	IC TC7S08F		Q508	8-729-116-04	TRANSISTOR 2SK160-K4	
IC617	8-759-031-84	IC SC7S04F		Q511	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC618	8-759-031-84	IC SC7S04F		Q512	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC619	8-759-035-93	IC SC7S32F		Q513	8-729-216-22	TRANSISTOR 2SA1162-G	
IC700	8-759-448-64	IC EL2160CS-TE2		Q514	8-729-112-65	TRANSISTOR 2SA1462-Y33	
IC750	8-759-448-64	IC EL2160CS-TE2		Q515	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC800	8-759-448-64	IC EL2160CS-TE2		Q516	8-729-216-22	TRANSISTOR 2SA1162-G	
IC850	8-759-448-64	IC EL2160CS-TE2		Q517	8-729-027-59	TRANSISTOR DTC144EKA-T146	
IC900	8-759-448-64	IC EL2160CS-TE2		Q518	8-729-101-07	TRANSISTOR 2SB798-DL	
IC950	8-759-448-64	IC EL2160CS-TE2		Q519	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
< JACK >				Q520	8-729-027-59	TRANSISTOR DTC144EKA-T146	
J700	1-568-547-11	JACK, MINIATURE PIN		Q604	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
J750	1-568-547-11	JACK, MINIATURE PIN		Q605	8-729-027-59	TRANSISTOR DTC144EKA-T146	
J800	1-568-547-11	JACK, MINIATURE PIN		Q606	8-729-107-31	TRANSISTOR 2SC3545-T1T44	
J850	1-568-547-11	JACK, MINIATURE PIN		Q607	8-729-107-31	TRANSISTOR 2SC3545-T1T44	
J900	1-568-547-11	JACK, MINIATURE PIN		Q608	8-729-107-31	TRANSISTOR 2SC3545-T1T44	
J950	1-568-547-11	JACK, MINIATURE PIN		Q609	8-729-107-31	TRANSISTOR 2SC3545-T1T44	
< COIL >				Q651	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
L500	1-412-028-11	INDUCTOR CHIP 4.7 μ H		Q702	8-729-112-65	TRANSISTOR 2SA1462-Y33	
L501	1-412-028-11	INDUCTOR CHIP 4.7 μ H		Q703	8-729-015-06	TRANSISTOR 2SC2498	
L502	1-412-028-11	INDUCTOR CHIP 4.7 μ H		Q704	8-729-031-16	TRANSISTOR 2SC4504E-TD	
L503	1-412-028-11	INDUCTOR CHIP 4.7 μ H		Q705	8-729-041-08	TRANSISTOR 2SA1575E-TD	
L504	1-412-028-11	INDUCTOR CHIP 4.7 μ H		Q706	8-729-112-65	TRANSISTOR 2SA1462-Y33	
L505	1-412-028-11	INDUCTOR CHIP 4.7 μ H		Q707	8-729-112-65	TRANSISTOR 2SA1462-Y33	
L600	1-412-533-21	INDUCTOR 47 μ H		Q750	8-729-129-54	TRANSISTOR 2SC2954	
L601	1-412-533-21	INDUCTOR 47 μ H		Q751	8-729-129-54	TRANSISTOR 2SC2954	
L602	1-412-029-11	INDUCTOR CHIP 10 μ H		Q752	8-729-112-65	TRANSISTOR 2SA1462-Y33	
L603	1-412-029-11	INDUCTOR CHIP 10 μ H		Q753	8-729-107-31	TRANSISTOR 2SC3545-T1T44	
L604	1-412-537-31	INDUCTOR 100 μ H		Q754	8-729-112-65	TRANSISTOR 2SA1462-Y33	
< TRANSISTOR >				Q755	8-729-015-06	TRANSISTOR 2SC2498	
Q100	8-729-027-59	TRANSISTOR DTC144EKA-T146		Q756	8-729-112-65	TRANSISTOR 2SA1462-Y33	
Q101	8-729-027-59	TRANSISTOR DTC144EKA-T146		Q757	8-729-145-13	TRANSISTOR 2SC3356-(R25)	
Q102	8-729-027-59	TRANSISTOR DTC144EKA-T146		Q758	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q103	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		Q759	8-729-031-16	TRANSISTOR 2SC4504E-TD	
				Q760	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
				Q761	8-729-107-31	TRANSISTOR 2SC3545-T1T44	
				Q762	8-729-112-65	TRANSISTOR 2SA1462-Y33	

REF NO	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
Q763	8-729-041-08	TRANSISTOR 2SA1575E-TD		R106	1-216-693-11	METAL CHIP 56K	0.5% 1/10W
Q764	8-729-112-65	TRANSISTOR 2SA1462-Y33		R107	1-216-663-11	METAL CHIP 3.3K	0.5% 1/10W
Q765	8-729-216-22	TRANSISTOR 2SA1162-G		R108	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
Q766	8-729-112-65	TRANSISTOR 2SA1462-Y33		R109	1-216-693-11	METAL CHIP 56K	0.5% 1/10W
Q802	8-729-112-65	TRANSISTOR 2SA1462-Y33		R110	1-216-663-11	METAL CHIP 3.3K	0.5% 1/10W
Q803	8-729-015-06	TRANSISTOR 2SC2498		R111	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
Q804	8-729-031-16	TRANSISTOR 2SC4504E-TD		R112	1-216-693-11	METAL CHIP 56K	0.5% 1/10W
Q805	8-729-041-08	TRANSISTOR 2SA1575E-TD		R113	1-216-663-11	METAL CHIP 3.3K	0.5% 1/10W
Q806	8-729-112-65	TRANSISTOR 2SA1462-Y33		R114	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
Q807	8-729-112-65	TRANSISTOR 2SA1462-Y33		R116	1-216-679-11	METAL CHIP 15K	0.5% 1/10W
Q850	8-729-129-54	TRANSISTOR 2SC2954		R118	1-216-679-11	METAL CHIP 15K	0.5% 1/10W
Q851	8-729-129-54	TRANSISTOR 2SC2954		R120	1-216-679-11	METAL CHIP 15K	0.5% 1/10W
Q852	8-729-112-65	TRANSISTOR 2SA1462-Y33		R128	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
Q853	8-729-107-31	TRANSISTOR 2SC3545-T1T44		R130	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
Q854	8-729-112-65	TRANSISTOR 2SA1462-Y33		R132	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
Q855	8-729-015-06	TRANSISTOR 2SC2498		R133	1-216-695-11	METAL CHIP 68K	0.5% 1/10W
Q856	8-729-112-65	TRANSISTOR 2SA1462-Y33		R134	1-216-683-11	METAL CHIP 22K	0.5% 1/10W
Q857	8-729-145-13	TRANSISTOR 2SC3356-(R25)		R135	1-216-679-11	METAL CHIP 15K	0.5% 1/10W
Q858	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R136	1-216-695-11	METAL CHIP 68K	0.5% 1/10W
Q859	8-729-031-16	TRANSISTOR 2SC4504E-TD		R137	1-216-683-11	METAL CHIP 22K	0.5% 1/10W
Q860	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R138	1-216-679-11	METAL CHIP 15K	0.5% 1/10W
Q861	8-729-107-31	TRANSISTOR 2SC3545-T1T44		R139	1-216-695-11	METAL CHIP 68K	0.5% 1/10W
Q862	8-729-112-65	TRANSISTOR 2SA1462-Y33		R140	1-216-683-11	METAL CHIP 22K	0.5% 1/10W
Q863	8-729-041-08	TRANSISTOR 2SA1575E-TD		R141	1-216-679-11	METAL CHIP 15K	0.5% 1/10W
Q864	8-729-112-65	TRANSISTOR 2SA1462-Y33		R142	1-218-754-11	METAL CHIP 120K	0.5% 1/10W
Q865	8-729-216-22	TRANSISTOR 2SA1162-G		R143	1-218-754-11	METAL CHIP 120K	0.5% 1/10W
Q866	8-729-112-65	TRANSISTOR 2SA1462-Y33		R144	1-218-754-11	METAL CHIP 120K	0.5% 1/10W
Q902	8-729-112-65	TRANSISTOR 2SA1462-Y33		R145	1-216-675-11	METAL CHIP 10K	0.5% 1/10W
Q903	8-729-015-06	TRANSISTOR 2SC2498		R146	1-216-675-11	METAL CHIP 10K	0.5% 1/10W
Q904	8-729-031-16	TRANSISTOR 2SC4504E-TD		R147	1-216-675-11	METAL CHIP 10K	0.5% 1/10W
Q905	8-729-041-08	TRANSISTOR 2SA1575E-TD		R148	1-216-025-91	METAL GLAZE 100	5% 1/10W
Q906	8-729-112-65	TRANSISTOR 2SA1462-Y33		R149	1-216-025-91	METAL GLAZE 100	5% 1/10W
Q907	8-729-112-65	TRANSISTOR 2SA1462-Y33		R150	1-216-665-11	METAL CHIP 3.9K	0.5% 1/10W
Q950	8-729-129-54	TRANSISTOR 2SC2954		R151	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
Q951	8-729-129-54	TRANSISTOR 2SC2954		R152	1-216-025-91	METAL GLAZE 100	5% 1/10W
Q952	8-729-112-65	TRANSISTOR 2SA1462-Y33		R153	1-216-665-11	METAL CHIP 3.9K	0.5% 1/10W
Q953	8-729-112-65	TRANSISTOR 2SA1462-Y33		R154	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
Q954	8-729-145-13	TRANSISTOR 2SC3356-(R25)		R155	1-216-025-91	METAL GLAZE 100	5% 1/10W
Q955	8-729-107-31	TRANSISTOR 2SC3545-T1T44		R156	1-216-665-11	METAL CHIP 3.9K	0.5% 1/10W
Q956	8-729-112-65	TRANSISTOR 2SA1462-Y33		R157	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
Q957	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R158	1-216-665-11	METAL CHIP 3.9K	0.5% 1/10W
Q958	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R159	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
Q959	8-729-015-06	TRANSISTOR 2SC2498		R160	1-216-665-11	METAL CHIP 3.9K	0.5% 1/10W
Q960	8-729-031-16	TRANSISTOR 2SC4504E-TD		R161	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
Q961	8-729-107-31	TRANSISTOR 2SC3545-T1T44		R162	1-216-665-11	METAL CHIP 3.9K	0.5% 1/10W
Q962	8-729-112-65	TRANSISTOR 2SA1462-Y33		R163	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
Q963	8-729-041-08	TRANSISTOR 2SA1575E-TD		R164	1-216-675-11	METAL CHIP 10K	0.5% 1/10W
Q964	8-729-112-65	TRANSISTOR 2SA1462-Y33		R165	1-216-675-11	METAL CHIP 10K	0.5% 1/10W
Q965	8-729-216-22	TRANSISTOR 2SA1162-G		R166	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
Q966	8-729-112-65	TRANSISTOR 2SA1462-Y33		R167	1-216-675-11	METAL CHIP 10K	0.5% 1/10W
< RESISTOR >				R168	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
R100	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R169	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
R101	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R170	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
R102	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R171	1-216-651-11	METAL CHIP 1K	0.5% 1/10W
R103	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R173	1-216-671-11	METAL CHIP 6.8K	0.5% 1/10W
R104	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R174	1-216-651-11	METAL CHIP 1K	0.5% 1/10W
R105	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R176	1-216-673-11	METAL CHIP 4.7K	0.5% 1/10W
				R177	1-216-667-11	METAL CHIP 3.6K	0.5% 1/10W
				R178	1-216-675-11	METAL CHIP 10K	0.5% 1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R179	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W	R240	1-216-001-00	METAL GLAZE	10	5%	1/10W
R180	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R242	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R182	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R243	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R183	1-216-664-11	METAL CHIP	3.6K	0.5%	1/10W	R244	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R185	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R245	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R186	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R246	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R187	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	R247	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R188	1-216-025-91	METAL GLAZE	100	5%	1/10W	R248	1-216-013-00	METAL GLAZE	33	5%	1/10W
R189	1-216-025-91	METAL GLAZE	100	5%	1/10W	R249	1-216-013-00	METAL GLAZE	33	5%	1/10W
R190	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	R250	1-216-013-00	METAL GLAZE	33	5%	1/10W
R191	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R251	1-216-001-00	METAL GLAZE	10	5%	1/10W
R192	1-216-025-91	METAL GLAZE	100	5%	1/10W	R252	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W
R193	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R253	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R194	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	R254	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R195	1-216-025-91	METAL GLAZE	100	5%	1/10W	R255	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R196	1-216-013-00	METAL GLAZE	33	5%	1/10W	R256	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R197	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R257	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R198	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	R258	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R200	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R259	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R201	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W	R260	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R202	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W	R261	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R203	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R262	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R204	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R263	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R205	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R264	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R206	1-216-647-11	METAL CHIP	680	0.5%	1/10W	R265	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R207	1-216-001-00	METAL GLAZE	10	5%	1/10W	R266	1-216-699-11	METAL CHIP	100K	0.5%	1/10W
R208	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R267	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R209	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R269	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R210	1-216-679-11	METAL CHIP	15K	0.5%	1/10W	R270	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R211	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R271	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R212	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R272	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R213	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R273	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W
R214	1-216-025-91	METAL GLAZE	100	5%	1/10W	R274	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W
R215	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R275	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R216	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R276	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R217	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	R277	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R218	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R278	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R219	1-216-077-00	METAL GLAZE	15K	5%	1/10W	R279	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R220	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R280	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R221	1-216-025-91	METAL GLAZE	100	5%	1/10W	R281	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R222	1-218-760-11	METAL CHIP	220K	0.5%	1/10W	R282	1-216-025-91	METAL GLAZE	100	5%	1/10W
R223	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R283	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R224	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W	R284	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R225	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R285	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R226	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W	R287	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R227	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R500	1-216-013-00	METAL GLAZE	33	5%	1/10W
R228	1-216-035-00	METAL GLAZE	270	5%	1/10W	R501	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R229	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R502	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R230	1-216-025-91	METAL GLAZE	100	5%	1/10W	R503	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R231	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R504	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R232	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R505	1-216-121-91	METAL GLAZE	1M	5%	1/10W
R233	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R506	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R234	1-216-025-91	METAL GLAZE	100	5%	1/10W	R507	1-216-025-91	METAL GLAZE	100	5%	1/10W
R235	1-216-679-11	METAL CHIP	15K	0.5%	1/10W	R508	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R236	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R509	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R237	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R510	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R238	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	R511	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R239	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	R512	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W
						R513	1-216-615-11	METAL CHIP	33	0.5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R514	1-216-013-00	METAL GLAZE	33	5%	1/10W	R577	1-216-089-91	METAL GLAZE	47K	5%	1/10W
R515	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R578	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R516	1-216-001-00	METAL GLAZE	10	5%	1/10W	R579	1-216-089-91	METAL GLAZE	47K	5%	1/10W
R517	1-216-631-11	METAL CHIP	150	0.5%	1/10W	R580	1-216-095-00	METAL GLAZE	82K	5%	1/10W
R518	1-216-631-11	METAL CHIP	150	0.5%	1/10W	R581	1-216-025-91	METAL GLAZE	100	5%	1/10W
R519	1-216-603-11	METAL CHIP	10	0.5%	1/10W	R582	1-220-259-11	METAL GLAZE	150	5%	1/4W
R520	1-216-025-91	METAL GLAZE	100	5%	1/10W	R583	1-220-259-11	METAL GLAZE	150	5%	1/4W
R521	1-216-013-00	METAL GLAZE	33	5%	1/10W	R584	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R522	1-216-025-91	METAL GLAZE	100	5%	1/10W	R585	1-216-097-91	METAL GLAZE	100K	5%	1/10W
R523	1-216-001-00	METAL GLAZE	10	5%	1/10W	R586	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R524	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R587	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R525	1-216-063-91	METAL GLAZE	3.9K	5%	1/10W	R588	1-216-089-91	METAL GLAZE	47K	5%	1/10W
R526	1-216-001-00	METAL GLAZE	10	5%	1/10W	R589	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R527	1-216-039-00	METAL GLAZE	390	5%	1/10W	R590	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R528	1-216-025-91	METAL GLAZE	100	5%	1/10W	R591	1-216-025-91	METAL GLAZE	100	5%	1/10W
R529	1-216-025-91	METAL GLAZE	100	5%	1/10W	R592	1-216-013-00	METAL GLAZE	33	5%	1/10W
R530	1-216-001-00	METAL GLAZE	10	5%	1/10W	R593	1-216-013-00	METAL GLAZE	33	5%	1/10W
R531	1-216-001-00	METAL GLAZE	10	5%	1/10W	R594	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R532	1-216-025-91	METAL GLAZE	100	5%	1/10W	R595	1-216-025-91	METAL GLAZE	100	5%	1/10W
R533	1-216-001-00	METAL GLAZE	10	5%	1/10W	R596	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R534	1-216-025-91	METAL GLAZE	100	5%	1/10W	R597	1-216-001-00	METAL GLAZE	10	5%	1/10W
R535	1-216-025-91	METAL GLAZE	100	5%	1/10W	R598	1-216-001-00	METAL GLAZE	10	5%	1/10W
R536	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W	R599	1-216-001-00	METAL GLAZE	10	5%	1/10W
R537	1-216-615-11	METAL CHIP	33	0.5%	1/10W	R600	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R538	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R601	1-216-013-00	METAL GLAZE	33	5%	1/10W
R539	1-216-121-91	METAL GLAZE	1M	5%	1/10W	R602	1-216-063-91	METAL GLAZE	3.9K	5%	1/10W
R540	1-216-013-00	METAL GLAZE	33	5%	1/10W	R603	1-216-001-00	METAL GLAZE	10	5%	1/10W
R541	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R604	1-216-001-00	METAL GLAZE	10	5%	1/10W
R543	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	R606	1-216-041-00	METAL CHIP	470	5%	1/10W
R544	1-216-013-00	METAL GLAZE	33	5%	1/10W	R607	1-216-041-00	METAL CHIP	470	5%	1/10W
R545	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R608	1-216-001-00	METAL GLAZE	10	5%	1/10W
R546	1-216-013-00	METAL GLAZE	33	5%	1/10W	R609	1-220-259-11	METAL GLAZE	150	5%	1/4W
R548	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R610	1-220-259-11	METAL GLAZE	150	5%	1/4W
R549	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R611	1-216-001-00	METAL GLAZE	10	5%	1/10W
R550	1-216-097-91	METAL GLAZE	100K	5%	1/10W	R613	1-216-013-00	METAL GLAZE	33	5%	1/10W
R551	1-216-025-91	METAL GLAZE	100	5%	1/10W	R614	1-216-041-00	METAL CHIP	470	5%	1/10W
R552	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W	R615	1-220-259-11	METAL GLAZE	150	5%	1/4W
R553	1-216-615-11	METAL CHIP	33	0.5%	1/10W	R616	1-220-259-11	METAL GLAZE	150	5%	1/4W
R554	1-216-013-00	METAL GLAZE	33	5%	1/10W	R617	1-216-001-00	METAL GLAZE	10	5%	1/10W
R555	1-220-259-11	METAL GLAZE	150	5%	1/4W	R620	1-216-001-00	METAL GLAZE	10	5%	1/10W
R556	1-220-259-11	METAL GLAZE	150	5%	1/4W	R622	1-216-013-00	METAL GLAZE	33	5%	1/10W
R557	1-216-025-91	METAL GLAZE	100	5%	1/10W	R623	1-216-013-00	METAL GLAZE	33	5%	1/10W
R558	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R624	1-216-013-00	METAL GLAZE	33	5%	1/10W
R559	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R625	1-216-089-91	METAL GLAZE	47K	5%	1/10W
R560	1-216-097-91	METAL GLAZE	100K	5%	1/10W	R626	1-216-013-00	METAL GLAZE	33	5%	1/10W
R561	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R627	1-216-063-91	METAL GLAZE	6.8K	5%	1/10W
R562	1-216-121-91	METAL GLAZE	1M	5%	1/10W	R628	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R563	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R629	1-216-641-11	METAL CHIP	470	0.5%	1/10W
R564	1-216-041-00	METAL GLAZE	470	5%	1/10W	R630	1-216-013-00	METAL GLAZE	33	5%	1/10W
R565	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	R631	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R566	1-216-013-00	METAL GLAZE	33	5%	1/10W	R632	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R568	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R634	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R569	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R635	1-216-699-11	METAL CHIP	100K	0.5%	1/10W
R570	1-216-013-00	METAL GLAZE	33	5%	1/10W	R636	1-216-699-11	METAL CHIP	100K	0.5%	1/10W
R571	1-218-767-11	METAL CHIP	430K	0.5%	1/10W	R637	1-216-687-11	METAL CHIP	11K	0.5%	1/10W
R572	1-216-013-00	METAL GLAZE	33	5%	1/10W	R638	1-216-699-11	METAL CHIP	100K	0.5%	1/10W
R573	1-216-013-00	METAL GLAZE	33	5%	1/10W	R639	1-216-678-11	METAL CHIP	11K	0.5%	1/10W
R574	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R640	1-216-689-11	METAL CHIP	39K	0.5%	1/10W
R576	1-216-089-91	METAL GLAZE	47K	5%	1/10W						

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R641	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R705	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R642	1-216-681-11	METAL CHIP	18K	0.5%	1/10W	R706	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R643	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R707	1-216-045-00	METAL GLAZE	680	5%	1/10W
R644	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R708	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R645	1-216-295-91	CONDUCTOR, CHIP (2012)				R709	1-216-641-11	METAL CHIP	390	5%	1/10W
R646	1-216-013-00	METAL GLAZE	33	5%	1/10W	R710	1-216-001-00	METAL GLAZE	10	5%	1/10W
R647	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	R711	1-216-025-91	METAL GLAZE	100	5%	1/10W
R648	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R713	1-216-639-11	METAL CHIP	330	0.5%	1/10W
R649	1-216-035-00	METAL GLAZE	270	5%	1/10W	R714	1-217-671-11	METAL GLAZE	1	5%	1/10W
R650	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	R716	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R651	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R718	1-217-671-11	METAL GLAZE	1	5%	1/10W
R652	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R720	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R653	1-216-027-00	METAL GLAZE	120	5%	1/10W	R721	1-216-025-91	METAL GLAZE	100	5%	1/10W
R654	1-216-039-00	METAL GLAZE	390	5%	1/10W	R722	1-216-013-00	METAL GLAZE	33	5%	1/10W
R656	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R723	1-216-025-91	METAL GLAZE	100	5%	1/10W
R657	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R725	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R658	1-220-256-11	METAL GLAZE	75	5%	1/4W	R728	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R660	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R729	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R661	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R730	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R662	1-220-256-11	METAL GLAZE	75	5%	1/4W	R731	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R664	1-216-013-00	METAL GLAZE	33	5%	1/10W	R732	1-216-027-00	METAL GLAZE	120	5%	1/10W
R665	1-216-001-00	METAL GLAZE	10	5%	1/10W	R733	1-216-017-91	METAL GLAZE	47	5%	1/10W
R666	1-216-001-00	METAL GLAZE	10	5%	1/10W	R734	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R667	1-216-001-00	METAL GLAZE	10	5%	1/10W	R735	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R668	1-220-259-11	METAL GLAZE	150	5%	1/4W	R736	1-216-017-91	METAL GLAZE	47	5%	1/10W
R669	1-220-259-11	METAL GLAZE	150	5%	1/4W	R748	1-216-017-91	METAL GLAZE	47	5%	1/10W
R670	1-220-259-11	METAL GLAZE	150	5%	1/4W	R749	1-216-017-91	METAL GLAZE	47	5%	1/10W
R671	1-220-259-11	METAL GLAZE	150	5%	1/4W	R750	1-216-045-00	METAL GLAZE	680	5%	1/10W
R672	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R751	1-216-045-00	METAL GLAZE	680	5%	1/10W
R673	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R752	1-216-045-00	METAL GLAZE	680	5%	1/10W
R674	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R753	1-216-045-00	METAL GLAZE	680	5%	1/10W
R675	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R754	1-216-045-00	METAL GLAZE	680	5%	1/10W
R676	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R755	1-216-045-00	METAL GLAZE	680	5%	1/10W
R677	1-220-256-11	METAL GLAZE	75	5%	1/4W	R756	1-216-045-00	METAL GLAZE	680	5%	1/10W
R678	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R757	1-216-045-00	METAL GLAZE	680	5%	1/10W
R679	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R758	1-216-687-11	METAL CHIP	33K	0.5%	1/10W
R680	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R759	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R681	1-216-045-00	METAL GLAZE	680	5%	1/10W	R760	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R684	1-216-025-91	METAL GLAZE	100	5%	1/10W	R761	1-216-644-11	METAL CHIP	510	0.5%	1/10W
R685	1-216-025-91	METAL GLAZE	100	5%	1/10W	R762	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W
R686	1-216-025-91	METAL GLAZE	100	5%	1/10W	R764	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R687	1-216-624-11	METAL CHIP	75	0.5%	1/10W	R765	1-216-646-11	METAL CHIP	620	0.5%	1/10W
R688	1-216-624-11	METAL CHIP	75	0.5%	1/10W	R766	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R689	1-216-624-11	METAL CHIP	75	0.5%	1/10W	R767	1-216-025-91	METAL GLAZE	100	5%	1/10W
R690	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R768	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R691	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R769	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W
R692	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R770	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R693	1-216-025-91	METAL GLAZE	100	5%	1/10W	R771	1-216-025-91	METAL GLAZE	100	5%	1/10W
R694	1-216-013-00	METAL GLAZE	33	5%	1/10W	R772	1-216-063-91	METAL GLAZE	3.9K	5%	1/10W
R695	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R773	1-216-021-00	METAL GLAZE	68	5%	1/10W
R696	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	R774	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W
R697	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	R775	1-216-075-00	METAL GLAZE	12K	5%	1/10W
R698	1-216-013-00	METAL GLAZE	33	5%	1/10W	R776	1-217-671-11	METAL GLAZE	1	5%	1/10W
R699	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R777	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R701	1-216-631-11	METAL CHIP	150	0.5%	1/10W	R780	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R702	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W	R781	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R703	1-216-045-00	METAL GLAZE	680	5%	1/10W	R782	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W
R704	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R783	1-217-671-11	METAL GLAZE	1	5%	1/10W
						R784	1-216-025-91	METAL GLAZE	100	5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK		
R785	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R786	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R787	1-216-021-00	METAL GLAZE	68	5%	1/10W
R788	1-216-013-00	METAL GLAZE	33	5%	1/10W
R789	1-216-025-91	METAL GLAZE	100	5%	1/10W
R790	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R791	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R792	1-216-079-00	METAL GLAZE	18K	5%	1/10W
R793	1-216-025-91	METAL GLAZE	100	5%	1/10W
R795	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W
R796	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R798	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R799	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R801	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R802	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R803	1-216-045-00	METAL GLAZE	680	5%	1/10W
R804	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R805	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R806	1-216-045-00	METAL GLAZE	680	5%	1/10W
R807	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R808	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R809	1-216-001-00	METAL GLAZE	10	5%	1/10W
R811	1-216-641-11	METAL CHIP	390	5%	1/10W
R812	1-216-025-91	METAL GLAZE	100	5%	1/10W
R813	1-216-639-11	METAL CHIP	330	0.5%	1/10W
R814	1-217-671-11	METAL GLAZE	1	5%	1/10W
R816	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R818	1-217-671-11	METAL GLAZE	1	5%	1/10W
R820	1-216-013-00	METAL GLAZE	33	5%	1/10W
R821	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R822	1-216-025-91	METAL GLAZE	100	5%	1/10W
R823	1-216-025-91	METAL GLAZE	100	5%	1/10W
R825	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R827	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R828	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R829	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R830	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R831	1-216-027-00	METAL GLAZE	120	5%	1/10W
R832	1-216-017-91	METAL GLAZE	47	5%	1/10W
R833	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R834	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R835	1-216-017-91	METAL GLAZE	47	5%	1/10W
R848	1-216-017-91	METAL GLAZE	47	5%	1/10W
R849	1-216-017-91	METAL GLAZE	47	5%	1/10W
R850	1-216-045-00	METAL GLAZE	680	5%	1/10W
R851	1-216-045-00	METAL GLAZE	680	5%	1/10W
R852	1-216-045-00	METAL GLAZE	680	5%	1/10W
R853	1-216-045-00	METAL GLAZE	680	5%	1/10W
R854	1-216-045-00	METAL GLAZE	680	5%	1/10W
R855	1-216-045-00	METAL GLAZE	680	5%	1/10W
R856	1-216-045-00	METAL GLAZE	680	5%	1/10W
R857	1-216-045-00	METAL GLAZE	680	5%	1/10W
R858	1-216-687-11	METAL CHIP	3.3K	0.5%	1/10W
R859	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R860	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R861	1-216-644-11	METAL CHIP	510	0.5%	1/10W
R863	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W
R864	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK		
R865	1-216-646-11	METAL CHIP	620	0.5%	1/10W
R866	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R867	1-216-025-91	METAL GLAZE	100	5%	1/10W
R868	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R869	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W
R870	1-216-021-00	METAL GLAZE	68	5%	1/10W
R871	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R872	1-216-025-91	METAL GLAZE	100	5%	1/10W
R873	1-216-063-91	METAL GLAZE	3.9K	5%	1/10W
R874	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W
R875	1-216-075-00	METAL GLAZE	12K	5%	1/10W
R877	1-217-671-11	METAL GLAZE	1	5%	1/10W
R878	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R880	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R881	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R882	1-216-021-00	METAL GLAZE	68	5%	1/10W
R883	1-217-671-11	METAL GLAZE	1	5%	1/10W
R884	1-216-025-91	METAL GLAZE	100	5%	1/10W
R885	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R886	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W
R887	1-216-013-00	METAL GLAZE	33	5%	1/10W
R888	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R889	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R890	1-216-025-91	METAL GLAZE	100	5%	1/10W
R891	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R892	1-216-079-00	METAL GLAZE	18K	5%	1/10W
R893	1-216-025-91	METAL GLAZE	100	5%	1/10W
R895	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W
R896	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R898	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R899	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R901	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R902	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R903	1-216-045-00	METAL GLAZE	680	5%	1/10W
R904	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R905	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R906	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R907	1-216-045-00	METAL GLAZE	680	5%	1/10W
R908	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R909	1-216-001-00	METAL GLAZE	10	5%	1/10W
R910	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R911	1-216-025-91	METAL GLAZE	100	5%	1/10W
R913	1-216-639-11	METAL CHIP	330	0.5%	1/10W
R914	1-217-671-11	METAL GLAZE	1	5%	1/10W
R916	1-216-631-11	METAL CHIP	150	0.5%	1/10W
R918	1-217-671-11	METAL GLAZE	1	5%	1/10W
R920	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R921	1-216-025-91	METAL GLAZE	100	5%	1/10W
R922	1-216-013-00	METAL GLAZE	33	5%	1/10W
R923	1-216-025-91	METAL GLAZE	100	5%	1/10W
R925	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R927	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R928	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R929	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R930	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W
R931	1-216-027-00	METAL GLAZE	120	5%	1/10W
R932	1-216-017-91	METAL GLAZE	47	5%	1/10W
R933	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R934	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	RV602	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K			
R935	1-216-017-91	METAL GLAZE	47	5%	1/10W						
R948	1-216-017-91	METAL GLAZE	47	5%	1/10W	RV603	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K			
R949	1-216-017-91	METAL GLAZE	47	5%	1/10W	RV750	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K			
R950	1-216-045-00	METAL GLAZE	680	5%	1/10W	RV850	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K			
						RV950	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K			
R951	1-216-045-00	METAL GLAZE	680	5%	1/10W			< TERMINAL BOARD >			
R952	1-216-045-00	METAL GLAZE	680	5%	1/10W						
R953	1-216-045-00	METAL GLAZE	680	5%	1/10W						
R954	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	TB500	* 1-694-206-11	TERMINAL BOARD ASSY, I/O			
R955	1-216-045-00	METAL GLAZE	680	5%	1/10W			< TEST PIN >			
R956	1-216-045-00	METAL GLAZE	680	5%	1/10W						
R957	1-216-045-00	METAL GLAZE	680	5%	1/10W	TP100	* 1-535-877-22	CHIP, CHECKER			
R958	1-216-045-00	METAL GLAZE	680	5%	1/10W	TP101	* 1-535-877-22	CHIP, CHECKER			
R959	1-216-687-11	METAL CHIP	33K	0.5%	1/10W	TP102	* 1-535-877-22	CHIP, CHECKER			
R960	1-216-631-11	METAL CHIP	150	0.5%	1/10W	TP103	* 1-535-877-22	CHIP, CHECKER			
R961	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W						
R962	1-216-644-11	METAL CHIP	510	0.5%	1/10W						
R963	1-216-053-00	METAL GLAZE	1.5K	5%	1/10W						
R964	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R965	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W						
R966	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W						
R967	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W						
R969	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W						
R970	1-216-063-91	METAL GLAZE	3.9K	5%	1/10W						
R971	1-216-646-11	METAL CHIP	620	0.5%	1/10W						
R972	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W						
R973	1-216-075-00	METAL GLAZE	12K	5%	1/10W						
R974	1-216-627-11	METAL CHIP	100	0.5%	1/10W						
R975	1-216-021-00	METAL GLAZE	68	5%	1/10W						
R977	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R978	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W						
R980	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W						
R981	1-217-671-11	METAL GLAZE	1	5%	1/10W						
R982	1-216-631-11	METAL CHIP	150	0.5%	1/10W						
R983	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W						
R984	1-216-049-91	METAL GLAZE	1K	5%	1/10W						
R985	1-216-021-00	METAL GLAZE	68	5%	1/10W						
R986	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W						
R987	1-216-079-00	METAL GLAZE	18K	5%	1/10W						
R988	1-216-013-00	METAL GLAZE	33	5%	1/10W						
R989	1-217-671-11	METAL GLAZE	1	5%	1/10W						
R990	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R991	1-216-631-11	METAL CHIP	150	0.5%	1/10W						
R992	1-220-277-11	METAL GLAZE	2.2K	5%	1/4W						
R993	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R995	1-216-071-00	METAL GLAZE	8.2K	5%	1/10W						
R996	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W						
R997	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R999	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W						
		< NETWORK >									
RB101	1-236-908-11	RES, CHIP NETWORK 10K (3216)									
RB102	1-236-908-11	RES, CHIP NETWORK 10K (3216)									
RB103	1-236-908-11	RES, CHIP NETWORK 10K (3216)									
		< VARIABLE RESISTOR >									
RV101	1-241-396-11	RES, ADJ, METAL GLAZE 22K									
RV501	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K									
RV600	1-241-395-11	RES, ADJ, METAL GLAZE 10K									
RV601	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K									

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
C132	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C310	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C133	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C311	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C134	1-128-004-11	ELECT CHIP	10MF	20%	16V	C312	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C135	1-128-004-11	ELECT CHIP	10MF	20%	16V	C313	1-109-982-11	CERAMIC CHIP	1MF	10%	10V
C136	1-128-004-11	ELECT CHIP	10MF	20%	16V	C314	1-124-465-00	ELECT	0.47MF	20%	50V
C137	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C315	1-124-465-00	ELECT	0.47MF	20%	50V
C138	1-128-416-11	ELECT CHIP	100MF	20%	16V	C316	1-124-465-00	ELECT	0.47MF	20%	50V
C139	1-126-204-11	ELECT	47MF	20%	16V	C317	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V
C140	1-128-004-11	ELECT CHIP	10MF	20%	16V	C318	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V
C141	1-128-004-11	ELECT CHIP	10MF	20%	16V	C319	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V
C142	1-128-004-11	ELECT CHIP	10MF	20%	16V	C321	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V
C143	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C322	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V
C144	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C323	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V
C150	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	C324	1-128-004-11	ELECT CHIP	10MF	20%	16V
C200	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C325	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C201	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	C326	1-126-204-11	ELECT	47MF	20%	16V
C202	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	C327	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C203	1-126-204-11	ELECT	47MF	20%	16V	C400	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C204	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C401	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C205	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C402	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C206	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V	C403	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C207	1-163-133-00	CERAMIC CHIP	470PF	5%	50V	C404	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C208	1-109-982-11	CERAMIC CHIP	1MF	10%	10V	C405	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C209	1-164-489-11	CERAMIC CHIP	0.22MF	10%	16V	C406	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C210	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C407	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C211	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	C408	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C212	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V	C409	1-126-204-11	ELECT	47MF	20%	16V
C213	1-163-235-11	CERAMIC CHIP	22PF	5%	50V	C410	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C218	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C411	1-128-004-11	ELECT CHIP	10MF	20%	16V
C219	1-126-935-11	ELECT	470MF	20%	16V	C412	1-128-416-11	ELECT CHIP	100MF	20%	16V
C222	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C413	1-128-416-11	ELECT CHIP	100MF	20%	16V
C223	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C414	1-128-416-11	ELECT CHIP	100MF	20%	16V
C224	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C500	1-126-603-11	ELECT CHIP	4.7MF	20%	16V
C225	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C501	1-164-489-11	CERAMIC CHIP	0.22MF	10%	16V
C226	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C502	1-164-489-11	CERAMIC CHIP	0.22MF	10%	16V
C227	1-126-204-11	ELECT	47MF	20%	16V	C503	1-109-982-11	CERAMIC CHIP	1MF	10%	10V
C228	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C504	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C230	1-128-006-11	ELECT CHIP	4.7MF	20%	25V	C505	1-164-489-11	CERAMIC CHIP	0.22MF	10%	16V
C234	1-128-006-11	ELECT CHIP	4.7MF	20%	25V	C506	1-109-982-11	CERAMIC CHIP	1MF	10%	10V
C235	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C507	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C240	1-126-204-11	ELECT	47MF	20%	16V	C508	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C241	1-128-006-11	ELECT CHIP	4.7MF	20%	25V	C509	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C247	1-128-006-11	ELECT CHIP	4.7MF	20%	25V	C510	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C248	1-126-204-11	ELECT	47MF	20%	16V	C511	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C249	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C512	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C251	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C513	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V
C252	1-126-204-11	ELECT	47MF	20%	16V	C515	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C253	1-109-982-11	CERAMIC CHIP	1MF	10%	10V	C516	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C260	1-128-004-11	ELECT CHIP	10MF	20%	16V	C517	1-128-004-11	ELECT CHIP	10MF	20%	16V
C261	1-128-004-11	ELECT CHIP	10MF	20%	16V	C518	1-128-004-11	ELECT CHIP	10MF	20%	16V
C300	1-128-004-11	ELECT CHIP	10MF	20%	16V	C519	1-128-004-11	ELECT CHIP	10MF	20%	16V
C301	1-128-004-11	ELECT CHIP	10MF	20%	16V	C520	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C302	1-128-004-11	ELECT CHIP	10MF	20%	16V	C521	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C303	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V	C522	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C304	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V	C523	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C305	1-107-823-11	CERAMIC CHIP	0.47MF	10%	16V	C524	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C306	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C525	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C308	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C529	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C309	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V						

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C530	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	L400	1-412-058-11	INDUCTOR CHIP	10μH
C531	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	L401	1-412-533-21	INDUCTOR	47μH
< CONNECTOR >				L402	1-412-533-21	INDUCTOR	47μH
CN434	* 1-764-795-11	SOCKET, CONNECTOR 80P		L403	1-412-533-21	INDUCTOR	47μH
CN435	* 1-564-522-11	PLUG, CONNECTOR 7P		< TRANSISTOR >			
CN438	1-564-729-11	PIN, CONNECTOR (SMALL TYPE)13P		Q101	8-729-216-22	TRANSISTOR	2SA1162-G
CN439	1-564-731-11	PIN, CONNECTOR (SMALL TYPE)15P		Q102	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
< DIODE >				Q103	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
D100	8-719-801-78	DIODE 1SS184		Q104	8-729-216-22	TRANSISTOR	2SA1162-G
D200	8-719-801-78	DIODE 1SS184		Q105	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
D201	8-719-801-78	DIODE 1SS184		Q106	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
< FILTER >				Q107	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
FL100	1-239-397-11	FILTER, LOW PASS		Q108	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
FL101	1-239-397-11	FILTER, LOW PASS		Q109	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
FL102	1-239-397-11	FILTER, LOW PASS		Q110	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
< IC >				Q111	8-729-216-22	TRANSISTOR	2SA1162-G
IC2	8-759-008-45	IC MC74HC4538F		Q112	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC3	8-759-927-72	IC TL1591CP		Q113	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC4	8-759-926-18	IC SN74HC157ANS		Q114	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC5	8-759-926-18	IC SN74HC157ANS		Q115	8-729-216-22	TRANSISTOR	2SA1162-G
IC6	8-759-175-04	IC PCF8574T-T		Q116	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC7	8-759-175-04	IC PCF8574T-T		Q117	8-729-216-22	TRANSISTOR	2SA1162-G
IC100	8-759-711-62	IC NJM2240M		Q118	8-729-216-22	TRANSISTOR	2SA1162-G
IC101	8-759-710-29	IC NJM2235M		Q119	8-729-216-22	TRANSISTOR	2SA1162-G
IC102	8-752-372-78	IC CXD2024AQ		Q200	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC103	8-752-068-45	IC CXA1855Q		Q201	8-729-027-59	TRANSISTOR	DTC144EKA-T146
IC104	8-759-011-65	IC MC74HC4053F		Q202	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC200	8-759-295-47	IC TDA9141-N2C		Q203	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC201	8-759-288-85	IC TDA4665T-T		Q205	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC202	8-759-335-58	IC MM1112XFF		Q206	8-729-107-31	TRANSISTOR	2SC3545-T1T44
IC204	8-759-335-58	IC MM1112XFF		Q211	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC300	8-752-072-88	IC CXA2011Q		Q212	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC301	8-759-925-74	IC SN74HC04ANS		Q300	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC400	8-752-070-54	IC CXA1839Q-T6		Q301	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC500	8-752-071-52	IC CXA2016S		Q302	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC501	8-759-926-18	IC SN74HC157ANS		Q400	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC502	8-759-035-93	IC SC7812F		Q401	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC503	8-759-011-65	IC MC74HC4053F		Q402	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
IC504	8-752-052-77	IC CXA1450M		Q403	8-729-026-57	TRANSISTOR	FMS1A-T148
IC505	8-752-052-77	IC CXA1450M		Q404	8-729-026-57	TRANSISTOR	FMS1A-T148
IC506	8-752-052-77	IC CXA1450M		Q405	8-729-026-57	TRANSISTOR	FMS1A-T148
< COIL >				Q406	8-729-027-59	TRANSISTOR	DTC144EKA-T146
L100	1-412-058-11	INDUCTOR CHIP	10μH	Q500	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
L101	1-412-058-11	INDUCTOR CHIP	10μH	Q501	8-729-216-22	TRANSISTOR	2SA1162-G
L102	1-412-058-11	INDUCTOR CHIP	10μH	Q502	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
L105	1-412-058-11	INDUCTOR CHIP	10μH	Q503	8-729-216-22	TRANSISTOR	2SA1162-G
L200	1-412-064-11	INDUCTOR CHIP	100μH	Q504	8-729-027-59	TRANSISTOR	DTC144EKA-T146
L201	1-412-058-11	INDUCTOR CHIP	10μH	Q505	8-729-216-22	TRANSISTOR	2SA1162-G
L202	1-412-064-11	INDUCTOR CHIP	100μH	Q506	8-729-027-59	TRANSISTOR	DTC144EKA-T146
L204	1-412-058-11	INDUCTOR CHIP	10μH	Q507	8-729-216-22	TRANSISTOR	2SA1162-G
L205	1-412-058-11	INDUCTOR CHIP	10μH	Q508	8-729-027-59	TRANSISTOR	DTC144EKA-T146
L206	1-412-064-11	INDUCTOR CHIP	100μH	Q509	8-729-216-22	TRANSISTOR	2SA1162-G
L207	1-412-796-41	INDUCTOR	47μH	Q510	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
L300	1-412-058-11	INDUCTOR CHIP	10μH	Q511	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
				Q512	8-729-230-49	TRANSISTOR	2SC2712-YG-TE85L
				Q515	8-729-216-22	TRANSISTOR	2SA1162-G

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
< RESISTOR >						R126	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R1	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W	R127	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R2	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R128	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R3	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R129	1-216-025-91	METAL GLAZE	100	5%	1/10W
R5	1-216-097-91	METAL GLAZE	100K	5%	1/10W	R130	1-216-025-91	METAL GLAZE	100	5%	1/10W
R6	1-216-097-91	METAL GLAZE	100K	5%	1/10W	R131	1-216-043-91	METAL GLAZE	560	5%	1/10W
R7	1-216-097-91	METAL GLAZE	100K	5%	1/10W	R132	1-216-025-91	METAL GLAZE	100	5%	1/10W
R8	1-216-097-91	METAL GLAZE	100K	5%	1/10W	R133	1-216-647-11	METAL CHIP	680	0.5%	1/10W
R9	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	R134	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R11	1-216-025-91	METAL GLAZE	100	5%	1/10W	R135	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R12	1-216-025-91	METAL GLAZE	100	5%	1/10W	R136	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R13	1-216-025-91	METAL GLAZE	100	5%	1/10W	R137	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R14	1-216-025-91	METAL GLAZE	100	5%	1/10W	R138	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R15	1-216-025-91	METAL GLAZE	100	5%	1/10W	R139	1-216-025-91	METAL GLAZE	100	5%	1/10W
R16	1-216-025-91	METAL GLAZE	100	5%	1/10W	R140	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R17	1-216-025-91	METAL GLAZE	100	5%	1/10W	R141	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R18	1-216-025-91	METAL GLAZE	100	5%	1/10W	R142	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R19	1-216-025-91	METAL GLAZE	100	5%	1/10W	R143	1-216-017-91	METAL GLAZE	47	5%	1/10W
R21	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R144	1-216-017-91	METAL GLAZE	47	5%	1/10W
R22	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R145	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R23	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R146	1-216-025-91	METAL GLAZE	100	5%	1/10W
R24	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R147	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R25	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R148	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R26	1-216-025-91	METAL GLAZE	100	5%	1/10W	R149	1-216-017-91	METAL GLAZE	47	5%	1/10W
R27	1-216-025-91	METAL GLAZE	100	5%	1/10W	R150	1-216-017-91	METAL GLAZE	47	5%	1/10W
R28	1-216-025-91	METAL GLAZE	100	5%	1/10W	R151	1-216-043-91	METAL GLAZE	560	5%	1/10W
R30	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R152	1-216-025-91	METAL GLAZE	100	5%	1/10W
R31	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R154	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R32	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R155	1-216-025-91	METAL GLAZE	100	5%	1/10W
R33	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R157	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R34	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R158	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R35	1-216-025-91	METAL GLAZE	100	5%	1/10W	R159	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R36	1-216-025-91	METAL GLAZE	100	5%	1/10W	R160	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R37	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R161	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R38	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R162	1-216-017-91	METAL GLAZE	47	5%	1/10W
R101	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R163	1-216-017-91	METAL GLAZE	47	5%	1/10W
R102	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R164	1-216-025-91	METAL GLAZE	100	5%	1/10W
R103	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	R165	1-216-025-91	METAL GLAZE	100	5%	1/10W
R104	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R166	1-216-025-91	METAL GLAZE	100	5%	1/10W
R105	1-216-059-00	METAL GLAZE	2.7K	5%	1/10W	R167	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W
R106	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R168	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R107	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R169	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R108	1-216-017-91	METAL GLAZE	47	5%	1/10W	R170	1-216-017-91	METAL GLAZE	47	5%	1/10W
R109	1-216-025-91	METAL GLAZE	100	5%	1/10W	R171	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R110	1-216-017-91	METAL GLAZE	47	5%	1/10W	R172	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R112	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R173	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R113	1-216-017-91	METAL GLAZE	47	5%	1/10W	R174	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R114	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	R175	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R116	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R176	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R117	1-216-033-00	METAL GLAZE	220	5%	1/10W	R177	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R118	1-216-017-91	METAL GLAZE	47	5%	1/10W	R178	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R119	1-216-017-91	METAL GLAZE	47	5%	1/10W	R179	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R120	1-216-025-91	METAL GLAZE	100	5%	1/10W	R180	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R121	1-216-017-91	METAL GLAZE	47	5%	1/10W	R181	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R122	1-216-025-91	METAL GLAZE	100	5%	1/10W	R182	1-216-017-91	METAL GLAZE	47	5%	1/10W
R123	1-216-041-00	METAL GLAZE	470	5%	1/10W	R183	1-216-017-91	METAL GLAZE	47	5%	1/10W
R124	1-216-025-91	METAL GLAZE	100	5%	1/10W	R184	1-216-617-11	METAL CHIP	39	0.5%	1/10W
R125	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R185	1-216-073-00	METAL GLAZE	10K	5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R186	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R319	1-216-025-91	METAL GLAZE	100	5%	1/10W
R187	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R321	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R188	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R322	1-216-017-91	METAL GLAZE	47	5%	1/10W
R189	1-216-017-91	METAL GLAZE	47	5%	1/10W	R323	1-216-017-91	METAL GLAZE	47	5%	1/10W
R190	1-216-025-91	METAL GLAZE	100	5%	1/10W	R324	1-216-017-91	METAL GLAZE	47	5%	1/10W
R191	1-216-025-91	METAL GLAZE	100	5%	1/10W	R325	1-216-039-00	METAL GLAZE	390	5%	1/10W
R192	1-216-025-91	METAL GLAZE	100	5%	1/10W	R326	1-216-017-91	METAL GLAZE	47	5%	1/10W
R193	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R327	1-216-017-91	METAL GLAZE	47	5%	1/10W
R194	1-216-017-91	METAL GLAZE	47	5%	1/10W	R328	1-216-017-91	METAL GLAZE	47	5%	1/10W
R195	1-216-633-11	METAL CHIP	180	0.5%	1/10W	R329	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R196	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R330	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R197	1-216-025-91	METAL GLAZE	100	5%	1/10W	R331	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R198	1-216-025-91	METAL GLAZE	100	5%	1/10W	R332	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R199	1-216-025-91	METAL GLAZE	100	5%	1/10W	R333	1-216-017-91	METAL GLAZE	47	5%	1/10W
R200	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R334	1-216-017-91	METAL GLAZE	47	5%	1/10W
R201	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R335	1-216-017-91	METAL GLAZE	47	5%	1/10W
R202	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R336	1-216-017-91	METAL GLAZE	47	5%	1/10W
R203	1-216-025-91	METAL GLAZE	100	5%	1/10W	R337	1-216-017-91	METAL GLAZE	47	5%	1/10W
R204	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R338	1-216-017-91	METAL GLAZE	47	5%	1/10W
R205	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R339	1-216-069-00	METAL GLAZE	6.8K	5%	1/10W
R206	1-216-033-00	METAL GLAZE	220	5%	1/10W	R340	1-216-077-00	METAL GLAZE	15K	5%	1/10W
R207	1-216-017-91	METAL GLAZE	47	5%	1/10W	R400	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R208	1-216-083-00	METAL GLAZE	27K	5%	1/10W	R401	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R209	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R402	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R210	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R405	1-216-685-11	METAL CHIP	27K	0.5%	1/10W
R211	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R407	1-216-067-00	METAL GLAZE	5.6K	5%	1/10W
R212	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R408	1-216-025-91	METAL GLAZE	100	5%	1/10W
R215	1-216-017-91	METAL GLAZE	47	5%	1/10W	R409	1-216-025-91	METAL GLAZE	100	5%	1/10W
R216	1-216-095-00	METAL GLAZE	82K	5%	1/10W	R411	1-216-025-91	METAL GLAZE	100	5%	1/10W
R217	1-216-047-91	METAL GLAZE	820	5%	1/10W	R413	1-216-025-91	METAL GLAZE	100	5%	1/10W
R218	1-216-017-91	METAL GLAZE	47	5%	1/10W	R414	1-216-025-91	METAL GLAZE	100	5%	1/10W
R219	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R415	1-216-025-91	METAL GLAZE	100	5%	1/10W
R220	1-216-295-91	CONDUCTOR, CHIP (2012)				R416	1-216-025-91	METAL GLAZE	100	5%	1/10W
R221	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R417	1-216-025-91	METAL GLAZE	100	5%	1/10W
R229	1-216-025-91	METAL GLAZE	100	5%	1/10W	R418	1-216-025-91	METAL GLAZE	100	5%	1/10W
R231	1-216-025-91	METAL GLAZE	100	5%	1/10W	R420	1-216-041-00	METAL GLAZE	470	5%	1/10W
R244	1-216-025-91	METAL GLAZE	100	5%	1/10W	R422	1-216-041-00	METAL GLAZE	470	5%	1/10W
R245	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R424	1-216-041-00	METAL GLAZE	470	5%	1/10W
R250	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R425	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R253	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R427	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W
R254	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R428	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R255	1-216-029-00	METAL GLAZE	150	5%	1/10W	R429	1-216-017-91	METAL GLAZE	47	5%	1/10W
R256	1-216-029-00	METAL GLAZE	150	5%	1/10W	R430	1-216-017-91	METAL GLAZE	47	5%	1/10W
R300	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R431	1-216-017-91	METAL GLAZE	47	5%	1/10W
R301	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R432	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R302	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R433	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R303	1-216-081-00	METAL GLAZE	22K	5%	1/10W	R434	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R304	1-216-081-00	METAL GLAZE	22K	5%	1/10W	R435	1-216-029-00	METAL GLAZE	150	5%	1/10W
R305	1-216-037-00	METAL GLAZE	330	5%	1/10W	R436	1-216-025-91	METAL GLAZE	100	5%	1/10W
R306	1-216-037-00	METAL GLAZE	330	5%	1/10W	R437	1-216-025-91	METAL GLAZE	100	5%	1/10W
R307	1-216-081-00	METAL GLAZE	22K	5%	1/10W	R438	1-216-025-91	METAL GLAZE	100	5%	1/10W
R308	1-216-037-00	METAL GLAZE	330	5%	1/10W	R500	1-216-085-00	METAL GLAZE	33K	5%	1/10W
R309	1-216-025-91	METAL GLAZE	100	5%	1/10W	R501	1-216-033-00	METAL GLAZE	220	5%	1/10W
R310	1-216-025-91	METAL GLAZE	100	5%	1/10W	R502	1-216-097-91	METAL GLAZE	100K	5%	1/10W
R311	1-216-025-91	METAL GLAZE	100	5%	1/10W	R503	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R312	1-216-025-91	METAL GLAZE	100	5%	1/10W	R504	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R313	1-216-025-91	METAL GLAZE	100	5%	1/10W	R505	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R314	1-216-025-91	METAL GLAZE	100	5%	1/10W	R506	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R318	1-216-025-91	METAL GLAZE	100	5%	1/10W						

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
	* 4-055-634-01	CASE (CA), SHIELD					C212	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
	* 4-056-039-01	HEAT SINK (CA)					C213	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
	* 4-056-040-01	HOLDER (A), PACK					C215	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
	* 4-056-061-01	HOLDER (B), PACK					C216	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	
	* 7-322-065-72	RUBBER, RTV (SE-9168) (130G)							< CONNECTOR >				
	7-682-552-04	SCREW +P 3X16					CN154	1-691-756-11	PIN, CONNECTOR (PC BOARD) 2P				
	7-682-654-09	SCREW +PS 3X25					CN155	* 1-691-961-11	PIN, CONNECTOR (PC BOARD) 2P				
	7-685-646-79	SCREW +BVTP 3X8 TYPE2 N-S					CN156	* 1-564-520-11	PLUG, CONNECTOR 5P				
		< CAPACITOR >					CN157	* 1-564-522-11	PLUG, CONNECTOR 7P				
C101	1-124-779-00	ELECT	10MF	20%	16V		CN158	* 1-564-521-11	PLUG, CONNECTOR 6P				
C102	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V				< DIODE >				
C104	1-163-251-11	CERAMIC CHIP	100PF	5%	50V		D101	8-719-901-83	DIODE 1SS83				
C106	1-163-255-11	CERAMIC CHIP	150PF	5%	50V		D103	8-719-901-83	DIODE 1SS83				
C108	1-102-050-00	CERAMIC	0.01MF	0.99	500V		D105	8-719-106-53	DIODE RD10M-B2				
C109	1-107-746-11	ELECT	10MF	20%	200V		D106	8-719-901-83	DIODE 1SS83				
C110	1-107-958-11	ELECT	2.2MF	20%	250V		D107	8-719-901-83	DIODE 1SS83				
C111	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		D108	8-719-901-83	DIODE 1SS83				
C112	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		D109	8-719-901-83	DIODE 1SS83				
C113	1-126-395-11	ELECT	22MF	20%	16V		D151	8-719-901-83	DIODE 1SS83				
C114	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		D153	8-719-901-83	DIODE 1SS83				
C115	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		D155	8-719-800-76	DIODE 1SS226				
C116	1-164-506-11	CERAMIC CHIP	4.7MF		16V		D156	8-719-800-76	DIODE 1SS226				
C117	1-164-506-11	CERAMIC CHIP	4.7MF		16V		D157	8-719-106-44	DIODE RD9.1M-B2				
C118	1-102-050-00	CERAMIC	0.01MF	0.99	500V		D158	8-719-800-76	DIODE 1SS226				
C119	1-107-961-91	ELECT	10MF	20%	250V		D159	8-719-105-82	DIODE RD5.1M-B2				
C151	1-124-779-00	ELECT	10MF	20%	16V		D161	8-719-911-19	DIODE 1SS119-25				
C152	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		D162	8-719-109-72	DIODE RD3.9ESB2				
C154	1-163-249-11	CERAMIC CHIP	82PF	5%	50V		D163	8-719-911-19	DIODE 1SS119-25				
C158	1-102-050-00	CERAMIC	0.01MF	0.99	500V		D164	8-719-106-53	DIODE RD10M-B2				
C159	1-107-943-11	ELECT	10MF	20%	160V		D165	8-719-107-24	DIODE RD20M-B2				
C160	1-163-275-11	CERAMIC CHIP	0.001MF	5%	50V				< FERRITE BEAD >				
C161	1-102-234-11	CERAMIC	270PF	10%	50V		FB102	1-410-396-41	FERRITE BEAD INDUCTOR 0.45μH				
C162	1-163-251-11	CERAMIC CHIP	100PF	5%	50V				< FILTER >				
C163	1-163-275-11	CERAMIC CHIP	0.001MF	5%	50V		FL101	1-233-830-11	FILTER, EMI				
C164	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL102	1-233-830-11	FILTER, EMI				
C165	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL103	1-233-830-11	FILTER, EMI				
C166	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL104	1-233-830-11	FILTER, EMI				
C167	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL105	1-233-830-11	FILTER, EMI				
C168	1-104-660-11	ELECT	47MF	20%	16V		FL106	1-233-831-11	FILTER, EMI				
C169	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL107	1-233-831-11	FILTER, EMI				
C170	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL108	1-233-831-11	FILTER, EMI				
C181	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL109	1-233-831-11	FILTER, EMI				
C182	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL110	1-233-831-11	FILTER, EMI				
C183	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		FL111	1-233-512-21	FILTER, EMI				
C186	1-163-251-11	CERAMIC CHIP	100PF	5%	50V		FL112	1-233-512-21	FILTER, EMI				
C191	1-162-114-00	CERAMIC	0.0047MF		2KV				< IC >				
C192	1-162-114-00	CERAMIC	0.0047MF		2KV		IC101	8-749-923-01	IC VPH06				
C193	1-124-779-00	ELECT	10MF	20%	16V		IC102	8-759-710-78	IC NJM082BM-T1				
C194	1-126-395-11	ELECT	22MF	20%	16V		IC151	8-749-011-19	IC VPA15H				
C195	1-126-395-11	ELECT	22MF	20%	16V		IC152	8-749-011-45	IC NJL5152MD				
C196	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		IC153	8-759-710-78	IC NJM082BM-T1				
C197	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		IC154	8-759-710-78	IC NJM082BM-T1				
C198	1-164-506-11	CERAMIC CHIP	4.7MF		16V		IC155	8-759-234-77	IC TC4S66F				
C199	1-164-506-11	CERAMIC CHIP	4.7MF		16V								
C200	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V								
C201	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V								
C202	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V								
C203	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V								



The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

REF NO.	PART NO	DESCRIPTION	REMARK
IC156	8-759-168-20	IC TA78L09S	
IC157	8-759-708-12	IC NJM78L12A	
IC158	8-759-700-69	IC NJM79L12A	
IC159	8-759-710-78	IC NJM082BM-T1	
IC161	8-759-448-64	IC EL2160CS-TE2	
IC162	8-759-448-64	IC EL2160CS-TE2	
< JACK >			
J101	1-568-548-11	JACK, MINIATURE PIN	
J102	Δ 1-251-493-11	SOCKET, CRT	
J151	1-568-548-11	JACK, MINIATURE PIN	
< COIL >			
L101	1-412-533-21	INDUCTOR 47 μ H	
L102	1-414-137-31	INDUCTOR 0.22 μ H	
L151	1-412-533-21	INDUCTOR 47 μ H	
L152	1-414-137-31	INDUCTOR 0.22 μ H	
L153	1-414-137-31	INDUCTOR 0.22 μ H	
< TRANSISTOR >			
Q101	8-729-116-05	TRANSISTOR 2SK160-K5	
Q102	8-729-801-88	TRANSISTOR 2SA1381-E	
Q103	8-729-821-02	TRANSISTOR 2SC3503-DE	
Q104	8-729-804-63	TRANSISTOR 2SA1406-E	
Q105	8-729-107-31	TRANSISTOR 2SC3545-T1T44	
Q106	8-729-027-59	TRANSISTOR DTC144EKA-T146	
< RESISTOR >			
R101	1-216-631-11	METAL CHIP 150 0.5% 1/10W	
R102	1-216-631-11	METAL CHIP 150 0.5% 1/10W	
R103	1-216-025-00	METAL GLAZE 100 5% 1/10W	
R104	1-216-615-11	METAL CHIP 33 0.5% 1/10W	
R106	1-216-607-11	METAL CHIP 15 0.5% 1/10W	
R107	1-249-405-11	CARBON 100 5% 1/4W	
R109	1-215-493-00	METAL 1M 1% 1/4W	
R110	1-215-471-00	METAL 120K 1% 1/4W	
R111	1-216-689-11	METAL CHIP 39K 0.5% 1/10W	
R112	1-216-121-91	METAL GLAZE 1M 5% 1/10W	
R113	1-216-013-00	METAL GLAZE 33 5% 1/10W	
R114	1-216-075-00	METAL GLAZE 12K 5% 1/10W	
R115	1-216-661-11	METAL CHIP 2.7K 0.5% 1/10W	
R116	1-216-675-11	METAL CHIP 10K 0.5% 1/10W	
R117	1-216-023-00	METAL GLAZE 82 5% 1/10W	
R118	1-216-667-11	METAL CHIP 4.7K 0.5% 1/10W	
R119	1-215-461-11	METAL 47K 1% 1/4W	
R120	1-247-887-00	CARBON 220K 5% 1/4W	
R121	1-202-535-00	SOLID 27 20% 1/2W	
R140	1-202-818-00	SOLID 1K 20% 1/2W	
R141	1-202-838-00	SOLID 100K 20% 1/2W	
R142	1-259-884-11	CARBON 4.7M 5% 1/4W	
R143	1-247-735-11	SOLID 47 20% 1/2W	
R151	1-216-631-11	METAL CHIP 150 0.5% 1/10W	
R152	1-216-631-11	METAL CHIP 150 0.5% 1/10W	
R153	1-216-025-11	METAL GLAZE 100 5% 1/10W	
R154	1-216-603-11	METAL CHIP 10 0.5% 1/10W	
R157	1-249-398-11	CARBON 27 5% 1/4W	
R161	1-247-903-00	CARBON 1M 5% 1/4W	
R162	1-216-025-91	METAL GLAZE 100 5% 1/10W	

REF NO.	PART NO.	DESCRIPTION	REMARK
R163	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
R164	1-216-049-91	METAL GLAZE 1K 5% 1/10W	
R166	1-216-649-11	METAL CHIP 820 0.5% 1/10W	
R167	1-218-760-11	METAL CHIP 220K 0.5% 1/10W	
R170	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R171	1-216-653-11	METAL CHIP 1.2K 0.5% 1/10W	
R172	1-216-653-11	METAL CHIP 1.2K 0.5% 1/10W	
R173	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R174	1-216-045-00	METAL GLAZE 680 5% 1/10W	
R175	1-216-621-11	METAL CHIP 56 0.5% 1/10W	
R176	1-216-673-11	METAL CHIP 8.2K 0.5% 1/10W	
R177	1-216-673-11	METAL CHIP 8.2K 0.5% 1/10W	
R178	1-216-049-91	METAL GLAZE 1K 5% 1/10W	
R179	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R180	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R181	1-216-675-11	METAL CHIP 10K 0.5% 1/10W	
R182	1-216-109-00	METAL GLAZE 330K 5% 1/10W	
R183	1-216-659-11	METAL CHIP 2.2K 0.5% 1/10W	
R184	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R190	1-202-549-00	SOLID 100 20% 1/2W	
R201	1-216-001-00	METAL GLAZE 10 5% 1/10W	
R203	1-216-645-11	METAL CHIP 560 0.5% 1/10W	
R204	1-216-659-11	METAL CHIP 2.2K 0.5% 1/10W	
R206	1-216-645-11	METAL CHIP 560 0.5% 1/10W	
R221	1-216-001-00	METAL GLAZE 10 5% 1/10W	
R223	1-216-645-11	METAL CHIP 560 0.5% 1/10W	
R224	1-216-649-11	METAL CHIP 820 0.5% 1/10W	
R226	1-216-651-11	METAL CHIP 1K 0.5% 1/10W	
R227	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R228	1-216-049-91	METAL GLAZE 1K 5% 1/10W	
< VARIABLE RESISTOR >			
RV101	1-237-516-21	RES, ADJ, CERMET 2K	
RV102	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K	
RV103	1-241-394-11	RES, ADJ, METAL GLAZE 4.7K	
< SPARK GAP >			
SG101	1-519-422-11	GAP, SPARK	
SG102	1-519-422-11	GAP, SPARK	
SG103	1-519-422-11	GAP, SPARK	

* A-1346-532-A D COMPLETE PC BOARD *****			
	1-923-510-48	WIRE UL1007 AWG24 110MM BRN	
	1-923-510-49	WIRE UL1007 AWG24 130MM YEL	
	1-923-510-50	WIRE UL1007 AWG24 130MM WHT	
	1-923-510-51	WIRE UL1007 AWG24 90MM BLU	
	1-923-510-52	WIRE UL1007 AWG24 80MM VIO	
	1-923-510-53	WIRE UL1007 AWG24 60MM WHT	
	1-923-510-54	WIRE UL1007 AWG24 60MM YEL	
	1-923-510-55	WIRE UL1007 AWG24 40MM VIO	
	1-923-510-56	WIRE UL1007 AWG24 120MM ORG	
	1-923-510-57	WIRE UL1007 AWG24 120MM RED	
	1-923-510-58	WIRE UL1007 AWG24 40MM BRN	
	4-382-854-11	SCREW (M3X10), P, SW (+)	
	* 4-395-527-01	HOLDER (B), TR	
	* 7-322-065-72	RUBBER, RTV (SE 9168) (100G)	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
< CAPACITOR >				C61	1-126-959-11	ELECT	0.47MF 20% 50V
C1	1-126-968-11	ELECT	100MF 20% 50V	C62	1-126-963-11	ELECT	4.7MF 20% 50V
C2	1-126-933-11	ELECT	100MF 20% 16V	C63	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C3	1-126-968-11	ELECT	100MF 20% 50V	C64	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C4	1-126-933-11	ELECT	100MF 20% 16V	C65	1-126-963-11	ELECT	4.7MF 20% 50V
C5	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	C66	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C6	1-163-125-00	CERAMIC CHIP	220PF 5% 50V	C67	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C7	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C68	1-137-194-11	FILM	0.47MF 5% 50V
C8	1-126-964-11	ELECT	10MF 20% 50V	C69	1-126-933-11	ELECT	100MF 20% 16V
C9	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	C70	1-126-960-11	ELECT	1MF 20% 50V
C10	1-126-960-11	ELECT	1MF 20% 50V	C71	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C11	1-136-153-00	FILM	0.01MF 5% 50V	C72	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C12	1-126-960-11	ELECT	1MF 20% 50V	C73	1-126-933-11	ELECT	100MF 20% 16V
C13	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C75	1-136-159-00	FILM	0.033MF 5% 50V
C14	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C76	1-136-155-00	FILM	0.015MF 5% 50V
C15	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	C77	1-136-165-00	FILM	0.1MF 5% 50V
C16	1-126-964-11	ELECT	10MF 20% 50V	C78	1-126-960-11	ELECT	1MF 20% 50V
C17	1-126-960-11	ELECT	1MF 20% 50V	C79	1-136-161-00	FILM	0.047MF 5% 50V
C18	1-136-153-00	FILM	0.01MF 5% 50V	C80	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C19	1-163-243-11	CERAMIC CHIP	47PF 5% 50V	C81	1-126-959-11	ELECT	0.47MF 20% 50V
C20	1-163-243-11	CERAMIC CHIP	47PF 5% 50V	C82	1-126-963-11	ELECT	4.7MF 20% 50V
C21	1-126-960-11	ELECT	1MF 20% 50V	C83	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C22	1-126-967-11	ELECT	47MF 20% 16V	C84	1-126-964-11	ELECT	10MF 20% 50V
C23	1-126-961-11	ELECT	2.2MF 20% 50V	C85	1-126-967-11	ELECT	47MF 20% 16V
C24	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	C86	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C25	1-126-960-11	ELECT	1MF 20% 50V	C87	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C26	1-136-153-00	FILM	0.01MF 5% 50V	C88	1-126-933-11	ELECT	100MF 20% 16V
C27	1-126-960-11	ELECT	1MF 20% 50V	C89	1-126-514-11	ELECT	22MF 20% 16V
C28	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	C90	1-126-964-11	ELECT	10MF 20% 50V
C29	1-126-964-11	ELECT	10MF 20% 50V	C91	1-126-964-11	ELECT	10MF 20% 50V
C30	1-126-960-11	ELECT	1MF 20% 50V	C92	1-136-153-00	FILM	0.01MF 5% 50V
C31	1-136-153-00	FILM	0.01MF 5% 50V	C93	1-126-964-11	ELECT	10MF 20% 50V
C32	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	C94	1-126-964-11	ELECT	10MF 20% 50V
C33	1-126-963-11	ELECT	4.7MF 20% 50V	C95	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C34	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	C96	1-126-964-11	ELECT	10MF 20% 50V
C35	1-137-366-11	FILM	0.0022MF 5% 50V	C97	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C37	1-126-967-11	ELECT	47MF 20% 16V	C98	1-126-964-11	ELECT	10MF 20% 50V
C38	1-136-165-00	FILM	0.1MF 5% 50V	C99	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C39	1-126-964-11	ELECT	10MF 20% 50V	C100	1-126-964-11	ELECT	10MF 20% 50V
C40	1-126-963-11	ELECT	4.7MF 20% 50V	C101	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C41	1-137-366-11	FILM	0.0022MF 5% 50V	C102	1-126-964-11	ELECT	10MF 20% 50V
C42	1-107-487-11	FILM	0.001MF 5% 50V	C103	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C43	1-107-487-11	FILM	0.001MF 5% 50V	C104	1-126-964-11	ELECT	10MF 20% 50V
C44	1-126-965-11	ELECT	22MF 20% 50V	C105	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C45	1-126-961-11	ELECT	2.2MF 20% 50V	C106	1-126-964-11	ELECT	10MF 20% 50V
C46	1-126-935-11	ELECT	470MF 20% 16V	C107	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C47	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C108	1-126-964-11	ELECT	10MF 20% 50V
C48	1-126-960-11	ELECT	1MF 20% 50V	C109	1-126-964-11	ELECT	10MF 20% 50V
C49	1-136-159-00	FILM	0.033MF 5% 50V	C110	1-126-964-11	ELECT	10MF 20% 50V
C50	1-126-961-11	ELECT	2.2MF 20% 50V	C111	1-126-964-11	ELECT	10MF 20% 50V
C51	1-126-961-11	ELECT	2.2MF 20% 50V	C112	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C54	1-136-165-00	FILM	0.1MF 5% 50V	C113	1-136-155-00	FILM	0.015MF 5% 50V
C55	1-126-960-11	ELECT	1MF 20% 50V	C114	1-136-159-00	FILM	0.033MF 5% 50V
C56	1-137-364-11	FILM	0.001MF 5% 50V	C115	1-136-165-00	FILM	0.1MF 5% 50V
C57	1-136-157-00	FILM	0.022MF 5% 50V	C116	1-126-960-11	ELECT	1MF 20% 50V
C58	1-126-934-11	ELECT	220MF 20% 16V	C117	1-136-161-00	FILM	0.047MF 5% 50V
C59	1-126-964-11	ELECT	10MF 20% 50V	C118	1-126-959-11	ELECT	0.47MF 20% 50V
C60	1-163-253-11	CERAMIC CHIP	120PF 5% 50V	C119	1-126-963-11	ELECT	4.7MF 20% 50V
				C120	1-163-031-11	CERAMIC CHIP	0.01MF 50V

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
C121	1-126-964-11	ELECT	10MF	20%	50V	C822	1-136-111-00	FILM	1MF	5%	200V
C122	1-126-963-11	ELECT	4.7MF	20%	50V	C823	1-126-963-11	ELECT	4.7MF	20%	50V
C123	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C824	1-136-165-00	FILM	0.1MF	5%	50V
C124	1-126-964-11	ELECT	10MF	20%	50V	C825	1-163-239-11	CERAMIC CHIP	33PF	5%	50V
C129	1-126-968-11	ELECT	100MF	20%	50V	C826	1-136-157-00	FILM	0.022MF	5%	50V
C130	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C827	1-163-239-11	CERAMIC CHIP	33PF	5%	50V
C131	1-126-968-11	ELECT	100MF	20%	50V	C828	1-126-968-11	ELECT	100MF	20%	50V
C132	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C829	1-136-111-00	FILM	1MF	5%	200V
C133	1-126-964-11	ELECT	10MF	20%	50V	C830	1-126-963-11	ELECT	4.7MF	20%	50V
C134	1-126-964-11	ELECT	10MF	20%	50V	C831	1-136-165-00	FILM	0.1MF	5%	50V
C135	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C832	1-163-239-11	CERAMIC CHIP	33PF	5%	50V
C136	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	C833	1-136-157-00	FILM	0.022MF	5%	50V
C137	1-126-960-11	ELECT	1MF	20%	50V	C834	1-163-239-11	CERAMIC CHIP	33PF	5%	50V
C138	1-126-964-11	ELECT	10MF	20%	50V	C835	1-126-968-11	ELECT	100MF	20%	50V
C139	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C836	1-136-111-00	FILM	1MF	5%	200V
C140	1-126-964-11	ELECT	10MF	20%	50V	C837	1-126-963-11	ELECT	4.7MF	20%	50V
C141	1-126-964-11	ELECT	10MF	20%	50V	C838	1-126-967-11	ELECT	47MF	20%	16V
C142	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C839	1-126-960-11	ELECT	1MF	20%	50V
C143	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C840	1-126-933-11	ELECT	100MF	20%	16V
C144	1-126-964-11	ELECT	10MF	20%	50V	C841	1-126-960-11	ELECT	1MF	20%	50V
C145	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C842	1-126-967-11	ELECT	47MF	20%	50V
C147	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C843	1-126-935-11	ELECT	470MF	20%	16V
C148	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C844	1-126-963-11	ELECT	4.7MF	20%	50V
C150	1-126-791-11	ELECT	10MF	20%	16V	C845	1-126-935-11	ELECT	470MF	20%	16V
C201	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C855	1-136-165-00	FILM	0.1MF	5%	50V
C242	1-137-368-11	FILM	0.0047MF	5%	50V	C856	1-136-165-00	FILM	0.1MF	5%	50V
C301	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	C857	1-136-165-00	FILM	0.1MF	5%	50V
C302	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	C858	1-136-165-00	FILM	0.1MF	5%	50V
C303	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	C859	1-136-165-00	FILM	0.1MF	5%	50V
C304	1-126-933-11	ELECT	100MF	20%	16V	C860	1-136-165-00	FILM	0.1MF	5%	50V
C305	1-126-934-11	ELECT	220MF	20%	16V	C861	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C306	1-126-964-11	ELECT	10MF	20%	50V	C862	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C307	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C864	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C308	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C865	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C309	1-126-964-11	ELECT	10MF	20%	50V	C1100	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C310	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C1101	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C314	1-126-964-11	ELECT	10MF	20%	50V	C1103	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C450	1-163-031-11	CERAMIC CHIP	0.01MF		50V	C1104	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C801	1-126-963-11	ELECT	4.7MF	20%	50V	C1107	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C802	1-126-967-11	ELECT	47MF	20%	16V	C1108	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C803	1-126-963-11	ELECT	4.7MF	20%	50V	C1200	1-136-153-00	FILM	0.01MF	5%	50V
C804	1-126-967-11	ELECT	47MF	20%	16V	C1201	1-126-791-11	ELECT	10MF	20%	16V
C805	1-126-964-11	ELECT	10MF	20%	50V	C1302	1-136-485-11	FILM	0.01MF	5%	50V
C806	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	< CONNECTOR >					
C807	1-136-159-00	FILM	0.033MF	5%	50V	CN361	1-695-989-11	SOCKET, CONNECTOR 40P			
C808	1-136-155-00	FILM	0.015MF	5%	50V	< DIODE >					
C809	1-136-165-00	FILM	0.1MF	5%	50V	D1	8-719-900-95	DIODE V09G			
C810	1-126-965-11	ELECT	22MF	20%	50V	D2	8-719-900-95	DIODE V09G			
C811	1-126-960-11	ELECT	1MF	20%	50V	D3	8-719-801-78	DIODE 1SS184			
C812	1-126-967-11	ELECT	47MF	20%	16V	D4	8-719-106-71	DIODE RD12M-B2			
C813	1-126-963-11	ELECT	4.7MF	20%	50V	D5	8-719-801-78	DIODE 1SS184			
C814	1-126-964-11	ELECT	10MF	20%	50V	D6	8-719-801-78	DIODE 1SS184			
C815	1-126-967-11	ELECT	47MF	20%	16V	D7	8-719-801-78	DIODE 1SS184			
C816	1-126-967-11	ELECT	47MF	20%	16V	D8	8-719-911-19	DIODE 1SS119-25			
C817	1-136-165-00	FILM	0.1MF	5%	50V	D9	8-719-801-78	DIODE 1SS184			
C818	1-163-239-11	CERAMIC CHIP	33PF	5%	50V	D10	8-719-801-78	DIODE 1SS184			
C819	1-136-157-00	FILM	0.022MF	5%	50V						
C820	1-163-239-11	CERAMIC CHIP	33PF	5%	50V						
C821	1-126-968-11	ELECT	100MF	20%	50V						

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
D11	8-719-800-76	DIODE 1SS226		IC24	8-752-068-37	IC CXA1726AM	
D12	8-719-801-78	DIODE 1SS184		IC25	8-752-068-37	IC CXA1726AM	
D13	8-719-800-76	DIODE 1SS226					
D14	8-719-801-78	DIODE 1SS184		IC26	8-752-068-37	IC CXA1726AM	
D15	8-719-800-76	DIODE 1SS226		IC27	8-759-381-53	IC μPC814G2-E2	
				IC28	8-752-068-37	IC CXA1726AM	
D16	8-719-900-95	DIODE V09G		IC29	8-759-381-53	IC μPC814G2-E2	
D17	8-719-900-95	DIODE V09G		IC30	8-752-065-69	IC CXA1470AS	
D18	8-719-801-78	DIODE 1SS184					
D101	8-719-921-19	DIODE 1SS119-25		IC31	8-759-457-55	IC AD835AR-REE	
D301	8-719-801-78	DIODE 1SS184		IC32	8-759-232-86	IC TC74HC238AF	
D302	8-719-801-78	DIODE 1SS184		IC33	8-759-925-76	IC SN74HC08ANS	
				IC34	8-759-925-76	IC SN74HC08ANS	
D303	8-719-801-78	DIODE 1SS184		IC35	8-759-144-82	IC μPC2405HF	
D304	8-719-801-78	DIODE 1SS184					
D801	8-719-900-95	DIODE V09G		IC36	8-759-247-67	IC LM2990T-5.0	
D802	8-719-900-95	DIODE V09G		IC37	8-759-457-55	IC AD835AR-REE	
D803	8-719-801-78	DIODE 1SS184		IC38	8-759-381-53	IC μPC814G2-E2	
				IC301	8-759-326-65	IC MP7670AS-TE2	
D804	8-719-900-95	DIODE V09G		IC302	8-759-326-65	IC MP7670AS-TE2	
D805	8-719-900-95	DIODE V09G					
D806	8-719-900-95	DIODE V09G		IC303	8-759-326-65	IC MP7670AS-TE2	
D807	8-719-900-95	DIODE V09G		IC304	8-759-326-65	IC MP7670AS-TE2	
D808	8-719-900-95	DIODE V09G		IC305	8-759-326-65	IC MP7670AS-TE2	
				IC306	8-759-326-65	IC MP7670AS-TE2	
D809	8-719-800-76	DIODE 1SS226		IC307	8-759-326-65	IC MP7670AS-TE2	
D810	8-719-801-78	DIODE 1SS184					
D811	8-719-801-78	DIODE 1SS184		IC308	8-759-326-65	IC MP7670AS-TE2	
D812	8-719-801-78	DIODE 1SS184		IC309	8-759-326-65	IC MP7670AS-TE2	
D813	8-719-801-78	DIODE 1SS184		IC310	8-759-326-65	IC MP7670AS-TE2	
				IC311	8-759-326-65	IC MP7670AS-TE2	
D814	8-719-801-78	DIODE 1SS184		IC312	8-759-326-65	IC MP7670AS-TE2	
D815	8-719-800-76	DIODE 1SS226					
D816	8-719-800-76	DIODE 1SS226		IC313	8-759-326-65	IC MP7670AS-TE2	
D817	8-719-800-76	DIODE 1SS226		IC314	8-759-326-65	IC MP7670AS-TE2	
D818	8-719-800-76	DIODE 1SS226		IC315	8-759-326-65	IC MP7670AS-TE2	
				IC316	8-759-326-65	IC MP7670AS-TE2	
D819	8-719-800-76	DIODE 1SS226		IC317	8-759-326-65	IC MP7670AS-TE2	
D820	8-719-110-08	DIODE RD8.2ESB2					
D821	8-719-911-19	DIODE 1SS119-25		IC318	8-759-326-65	IC MP7670AS-TE2	
		< IC >		IC319	8-759-326-65	IC MP7670AS-TE2	
IC1	8-759-231-58	IC TA7812S		IC320	8-759-326-65	IC MP7670AS-TE2	
IC2	8-759-700-69	IC NJM79L12A		IC321	8-759-326-65	IC MP7670AS-TE2	
IC3	8-759-300-78	IC HD14538BFP		IC322	8-759-326-65	IC MP7670AS-TE2	
IC4	8-759-100-96	IC μPC4558G2					
IC5	8-759-300-78	IC HD14538BFP		IC323	8-759-326-65	IC MP7670AS-TE2	
				IC324	8-759-326-65	IC MP7670AS-TE2	
IC6	8-759-100-96	IC μPC4558G2		IC325	8-759-326-65	IC MP7670AS-TE2	
IC7	8-759-300-78	IC HD14538BFP		IC326	8-759-326-65	IC MP7670AS-TE2	
IC8	8-759-381-53	IC μPC814G2-E2		IC327	8-759-326-65	IC MP7670AS-TE2	
IC9	8-759-100-93	IC μPC393G2					
IC10	8-749-010-15	IC MC-8639A		IC328	8-759-326-65	IC MP7670AS-TE2	
				IC329	8-759-326-65	IC MP7670AS-TE2	
IC11	8-759-100-60	IC μPC1377C		IC330	8-759-326-65	IC MP7670AS-TE2	
IC12	8-759-300-78	IC HD14538BFP		IC331	8-759-326-65	IC MP7670AS-TE2	
IC13	8-759-381-53	IC μPC814G2-E2		IC332	8-759-326-65	IC MP7670AS-TE2	
IC14	8-759-381-53	IC μPC814G2-E2					
IC15	8-759-381-53	IC μPC814G2-E2		IC333	8-759-326-65	IC MP7670AS-TE2	
				IC334	8-759-326-65	IC MP7670AS-TE2	
IC16	8-759-031-84	IC SC7S04F		IC335	8-759-326-65	IC MP7670AS-TE2	
IC17	8-752-065-69	IC CXA1470AS		IC336	8-759-326-65	IC MP7670AS-TE2	
IC18	8-759-381-53	IC μPC814G2-E2		IC337	8-759-381-53	IC μPC814G2-E2	
IC19	8-759-381-53	IC μPC814G2-E2					
IC20	8-759-100-96	IC μPC4558G2		IC338	8-759-443-72	IC RH5VL43AA-T1	
				IC339	8-759-443-72	IC RH5VL43AA-T1	
IC21	8-759-381-53	IC μPC814G2-E2		IC340	8-759-908-15	IC TL431CLP	
IC22	8-752-068-37	IC CXA1726AM		IC341	8-759-381-53	IC μPC814G2-E2	
IC23	8-759-381-53	IC μPC814G2-E2		IC342	8-752-068-37	IC CXA1726AM	
				IC343	8-752-068-37	IC CXA1726AM	
				IC344	8-759-926-05	IC SN74HC125ANS	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
IC345	8-759-381-53	IC μ PC814G2-E2		Q8	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC346	8-759-381-53	IC μ PC814G2-E2		Q9	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC347	8-759-381-53	IC μ PC814G2-E2		Q10	8-729-216-22	TRANSISTOR 2SA1162-G	
IC348	8-759-381-53	IC μ PC814G2-E2		Q11	8-729-105-74	TRANSISTOR 2SK523-M1	
IC349	8-759-381-53	IC μ PC814G2-E2		Q12	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC350	8-759-381-53	IC μ PC814G2-E2		Q13	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC351	8-759-381-53	IC μ PC814G2-E2		Q14	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC352	8-759-381-53	IC μ PC814G2-E2		Q15	8-729-216-22	TRANSISTOR 2SA1162-G	
IC353	8-759-381-53	IC μ PC814G2-E2		Q16	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC354	8-759-326-65	IC MP7670AS-TE2		Q17	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC355	8-759-326-65	IC MP7670AS-TE2		Q18	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC801	8-759-144-82	IC μ PC2405HF		Q19	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC802	8-759-247-67	IC LM2990T-5.0		Q20	8-729-027-59	TRANSISTOR DTC144EKA-T146	
IC803	8-752-065-69	IC CXA1470AS		Q21	8-729-027-59	TRANSISTOR DTC144EKA-T146	
IC804	8-759-100-96	IC μ PC4558G2		Q22	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC805	8-759-100-96	IC μ PC4558G2		Q23	8-729-904-04	TRANSISTOR FMS2	
IC806	8-759-908-15	IC TL431CLP		Q24	8-729-926-23	TRANSISTOR FMW5	
IC807	8-759-443-72	IC RH5VL43AA-T1		Q25	8-729-216-22	TRANSISTOR 2SA1162-G	
IC808	8-759-326-65	IC MP7670AS-TE2		Q26	8-729-027-59	TRANSISTOR DTC144EKA-T146	
IC809	8-759-326-65	IC MP7670AS-TE2		Q27	8-729-027-59	TRANSISTOR DTC144EKA-T146	
IC810	8-759-326-65	IC MP7670AS-TE2		Q28	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC811	8-759-100-96	IC μ PC4558G2		Q29	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC812	8-759-113-13	IC μ PC1498H		Q30	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC813	8-759-100-96	IC μ PC4558G2		Q31	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC814	8-759-113-13	IC μ PC1498H		Q32	8-729-216-22	TRANSISTOR 2SA1162-G	
IC815	8-759-100-96	IC μ PC4558G2		Q33	8-729-105-74	TRANSISTOR 2SK523-M1	
IC816	8-759-113-13	IC μ PC1498H		Q34	8-729-926-23	TRANSISTOR FMW5	
IC817	8-759-231-58	IC TA7812S		Q35	8-729-216-22	TRANSISTOR 2SA1162-G	
IC818	8-759-701-88	IC NJM7912FA		Q36	8-729-026-57	TRANSISTOR FMS1A-T148	
IC819	8-759-100-96	IC μ PC4558G2		Q37	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC820	8-759-100-93	IC μ PC393G2		Q38	8-729-926-23	TRANSISTOR FMW5	
IC821	8-759-326-65	IC MP7670AS-TE2		Q39	8-729-216-22	TRANSISTOR 2SA1162-G	
IC822	8-759-100-96	IC μ PC4558G2		Q40	8-729-026-57	TRANSISTOR FMS1A-T148	
IC823	8-759-100-96	IC μ PC4558G2		Q41	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC824	8-759-100-96	IC μ PC4558G2		Q42	8-729-026-57	TRANSISTOR FMS1A-T148	
IC1100	8-759-326-65	IC MP7670AS-TE2		Q43	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC1101	8-759-381-53	IC μ PC814G2-E2		Q44	8-729-026-57	TRANSISTOR FMS1A-T148	
IC1102	8-759-100-96	IC μ PC4558G2		Q45	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
IC1103	8-759-326-65	IC MP7670AS-TE2		Q46	8-729-926-23	TRANSISTOR FMW5	
IC1104	8-759-381-53	IC μ PC814G2-E2		Q47	8-729-216-22	TRANSISTOR 2SA1162-G	
IC1105	8-759-326-65	IC MP7670AS-TE2		Q48	8-729-926-23	TRANSISTOR FMW5	
IC1107	8-759-381-53	IC μ PC814G2-E2		Q49	8-729-216-22	TRANSISTOR 2SA1162-G	
IC1108	8-759-326-65	IC MP7670AS-TE2		Q50	8-729-926-23	TRANSISTOR FMW5	
< COIL >				Q51	8-729-216-22	TRANSISTOR 2SA1162-G	
L1	1-412-533-21	INDUCTOR 47 μ H		Q52	8-729-026-57	TRANSISTOR FMS1A-T148	
L2	1-412-533-21	INDUCTOR 47 μ H		Q53	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
L801	1-412-533-21	INDUCTOR 47 μ H		Q54	8-729-926-23	TRANSISTOR FMW5	
L804	1-412-533-21	INDUCTOR 47 μ H		Q55	8-729-216-22	TRANSISTOR 2SA1162-G	
L805	1-412-533-21	INDUCTOR 47 μ H		Q56	8-729-026-57	TRANSISTOR FMS1A-T148	
< TRANSISTOR >				Q57	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q1	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		Q58	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q2	8-729-216-22	TRANSISTOR 2SA1162-G		Q59	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q3	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		Q60	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q4	8-729-216-22	TRANSISTOR 2SA1162-G		Q201	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q5	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		Q801	8-729-216-22	TRANSISTOR 2SA1162-G	
Q6	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		Q802	8-729-026-57	TRANSISTOR FMS1A-T148	
Q7	8-729-904-04	TRANSISTOR FMS2		Q804	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
				Q805	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
Q806	8-729-038-82	TRANSISTOR 2SK2251-01		R38	1-216-651-11	METAL CHIP 1K	0.5% 1/10W
Q807	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R39	1-216-651-11	METAL CHIP 1K	0.5% 1/10W
Q808	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R40	1-216-049-91	METAL GLAZE 1K	5% 1/10W
Q809	8-729-038-82	TRANSISTOR 2SK2251-01		R41	1-216-667-11	METAL CHIP 4.7K	0.5% 1/10W
Q810	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R42	1-216-077-00	METAL GLAZE 15K	5% 1/10W
Q811	8-729-038-82	TRANSISTOR 2SK2251-01		R43	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q812	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R44	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q813	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R45	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q814	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R46	1-216-057-00	METAL GLAZE 2.2K	5% 1/10W
Q815	8-729-207-82	TRANSISTOR 2SC3421-Y		R47	1-216-059-00	METAL GLAZE 2.7K	5% 1/10W
Q816	8-729-207-89	TRANSISTOR 2SA1358-Y		R48	1-216-049-91	METAL GLAZE 1K	5% 1/10W
Q817	8-729-207-82	TRANSISTOR 2SC3421-Y		R49	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q818	8-729-207-89	TRANSISTOR 2SA1358-Y		R50	1-216-025-91	METAL GLAZE 100	5% 1/10W
Q819	8-729-207-82	TRANSISTOR 2SC3421-Y		R51	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q820	8-729-207-89	TRANSISTOR 2SA1358-Y		R52	1-216-065-00	METAL GLAZE 4.7K	5% 1/10W
Q821	8-729-207-82	TRANSISTOR 2SC3421-Y		R53	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q822	8-729-207-89	TRANSISTOR 2SA1358-Y		R54	1-216-077-00	METAL GLAZE 15K	5% 1/10W
Q823	8-729-207-82	TRANSISTOR 2SC3421-Y		R55	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q824	8-729-207-89	TRANSISTOR 2SA1358-Y		R56	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
Q825	8-729-207-82	TRANSISTOR 2SC3421-Y		R57	1-216-073-00	METAL GLAZE 10K	5% 1/10W
Q826	8-729-207-89	TRANSISTOR 2SA1358-Y		R58	1-216-065-00	METAL GLAZE 4.7K	5% 1/10W
Q827	8-729-926-23	TRANSISTOR FMW5		R59	1-216-101-00	METAL GLAZE 150K	5% 1/10W
		< RESISTOR >		R61	1-216-057-00	METAL GLAZE 2.2K	5% 1/10W
R1	1-216-049-91	METAL GLAZE 1K	5% 1/10W	R62	1-216-041-00	METAL GLAZE 470	5% 1/10W
R2	1-216-057-00	METAL GLAZE 2.2K	5% 1/10W	R66	1-216-049-91	METAL GLAZE 1K	5% 1/10W
R3	1-216-055-00	METAL GLAZE 1.8K	5% 1/10W	R67	1-216-049-91	METAL GLAZE 1K	5% 1/10W
R4	1-216-025-91	METAL GLAZE 100	5% 1/10W	R68	1-216-033-00	METAL GLAZE 220	5% 1/10W
R5	1-216-681-11	METAL CHIP 18K	0.5% 1/10W	R69	1-216-013-00	METAL GLAZE 33	5% 1/10W
R6	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R70	1-216-065-00	METAL GLAZE 4.7K	5% 1/10W
R8	1-216-077-00	METAL GLAZE 15K	5% 1/10W	R71	1-216-673-11	METAL CHIP 8.2K	0.5% 1/10W
R9	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R72	1-216-025-91	METAL GLAZE 100	5% 1/10W
R10	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R73	1-216-697-91	METAL CHIP 82K	0.5% 1/10W
R11	1-216-057-00	METAL GLAZE 2.2K	5% 1/10W	R74	1-216-697-91	METAL CHIP 82K	0.5% 1/10W
R12	1-216-059-00	METAL GLAZE 2.7K	5% 1/10W	R75	1-216-643-11	METAL CHIP 470	0.5% 1/10W
R13	1-216-049-91	METAL GLAZE 1K	5% 1/10W	R76	1-216-697-91	METAL CHIP 82K	0.5% 1/10W
R14	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R77	1-216-697-91	METAL CHIP 82K	0.5% 1/10W
R15	1-216-025-91	METAL GLAZE 100	5% 1/10W	R78	1-216-655-11	METAL CHIP 1.5K	0.5% 1/10W
R16	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R79	1-216-699-11	METAL CHIP 100K	0.5% 1/10W
R17	1-216-065-00	METAL GLAZE 4.7K	5% 1/10W	R80	1-216-073-00	METAL GLAZE 10K	5% 1/10W
R18	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R81	1-216-065-00	METAL GLAZE 4.7K	5% 1/10W
R19	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R82	1-216-065-00	METAL GLAZE 4.7K	5% 1/10W
R20	1-216-077-00	METAL GLAZE 15K	5% 1/10W	R83	1-216-085-00	METAL GLAZE 33K	5% 1/10W
R21	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R84	1-216-049-91	METAL GLAZE 1K	5% 1/10W
R22	1-216-109-00	METAL GLAZE 100K	5% 1/10W	R85	1-216-025-91	METAL GLAZE 100	5% 1/10W
R23	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R86	1-216-049-91	METAL GLAZE 1K	5% 1/10W
R24	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R87	1-216-049-91	METAL GLAZE 1K	5% 1/10W
R25	1-216-093-00	METAL GLAZE 68K	5% 1/10W	R88	1-216-089-91	METAL GLAZE 47K	5% 1/10W
R26	1-216-061-00	METAL GLAZE 3.3K	5% 1/10W	R89	1-216-089-91	METAL GLAZE 47K	5% 1/10W
R27	1-216-085-00	METAL GLAZE 33K	5% 1/10W	R90	1-216-097-91	METAL GLAZE 100K	5% 1/10W
R28	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R91	1-216-073-00	METAL GLAZE 10K	5% 1/10W
R29	1-216-089-91	METAL GLAZE 47K	5% 1/10W	R92	1-216-073-00	METAL GLAZE 10K	5% 1/10W
R30	1-216-073-00	METAL GLAZE 10K	5% 1/10W	R93	1-216-073-00	METAL GLAZE 10K	5% 1/10W
R31	1-216-075-00	METAL GLAZE 12K	5% 1/10W	R94	1-216-091-00	METAL GLAZE 56K	5% 1/10W
R32	1-216-089-91	METAL GLAZE 47K	5% 1/10W	R97	1-216-677-11	METAL CHIP 12K	0.5% 1/10W
R33	1-216-081-00	METAL GLAZE 22K	5% 1/10W	R98	1-216-673-11	METAL CHIP 8.2K	0.5% 1/10W
R34	1-216-687-11	METAL CHIP 33K	0.5% 1/10W	R99	1-216-071-00	METAL GLAZE 8.2K	5% 1/10W
R35	1-216-699-11	METAL CHIP 100K	0.5% 1/10W	R100	1-216-069-00	METAL GLAZE 6.8K	5% 1/10W
R37	1-216-025-91	METAL GLAZE 100	5% 1/10W	R101	1-216-043-91	METAL GLAZE 56K	5% 1/10W
				R102	1-216-031-00	METAL GLAZE 180	5% 1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R101	1-216-043-91	METAL GLAZE	560	5%	1/10W	R162	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R104	1-216-081-00	METAL GLAZE	22K	5%	1/10W	R163	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R106	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R164	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R107	1-216-077-00	METAL GLAZE	15K	5%	1/10W	R165	1-216-025-91	METAL GLAZE	100	5%	1/10W
R108	1-216-083-00	METAL GLAZE	27K	5%	1/10W	R166	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R109	1-216-095-00	METAL GLAZE	82K	5%	1/10W	R167	1-216-025-91	METAL GLAZE	100	5%	1/10W
R110	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	R168	1-216-025-91	METAL GLAZE	100	5%	1/10W
R111	1-216-081-00	METAL GLAZE	22K	5%	1/10W	R169	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R112	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R170	1-216-025-91	METAL GLAZE	100	5%	1/10W
R113	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R171	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R114	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R172	1-216-025-91	METAL GLAZE	100	5%	1/10W
R115	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R173	1-216-025-91	METAL GLAZE	100	5%	1/10W
R116	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R174	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R117	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R175	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R118	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R176	1-216-655-11	METAL CHIP	1.5K	0.5%	1/10W
R119	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R177	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R120	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R178	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R121	1-216-025-91	METAL GLAZE	100	5%	1/10W	R179	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R122	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R180	1-247-855-31	CARBON	10K	5%	1/4W
R123	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R181	1-216-699-11	METAL CHIP	100K	0.5%	1/10W
R124	1-216-681-11	METAL CHIP	18K	0.5%	1/10W	R182	1-216-699-11	METAL CHIP	100K	0.5%	1/10W
R125	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R183	1-247-855-11	CARBON	10K	5%	1/4W
R126	1-216-105-91	METAL GLAZE	220K	5%	1/10W	R184	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R127	1-216-017-91	METAL GLAZE	47	5%	1/10W	R185	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R128	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R186	1-216-025-91	METAL GLAZE	100	5%	1/10W
R129	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R187	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R130	1-216-091-00	METAL GLAZE	56K	5%	1/10W	R188	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R131	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R189	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R132	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R190	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R133	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	R191	1-216-655-11	METAL CHIP	1.5K	0.5%	1/10W
R134	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R192	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R135	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	R193	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R136	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R194	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R137	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R195	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R138	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	R196	1-216-025-91	METAL GLAZE	100	5%	1/10W
R139	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R197	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R140	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R198	1-216-025-91	METAL GLAZE	100	5%	1/10W
R141	1-216-643-11	METAL CHIP	470	0.5%	1/10W	R199	1-216-025-91	METAL GLAZE	100	5%	1/10W
R142	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R200	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R143	1-216-025-91	METAL GLAZE	100	5%	1/10W	R201	1-216-025-91	METAL GLAZE	100	5%	1/10W
R144	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R202	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R145	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R203	1-216-025-91	METAL GLAZE	100	5%	1/10W
R146	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R204	1-216-025-91	METAL GLAZE	100	5%	1/10W
R147	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R205	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R148	1-216-679-11	METAL CHIP	15K	0.5%	1/10W	R206	1-216-025-91	METAL GLAZE	100	5%	1/10W
R149	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R207	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R150	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R208	1-216-025-91	METAL GLAZE	100	5%	1/10W
R151	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R209	1-216-025-91	METAL GLAZE	100	5%	1/10W
R152	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	R210	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R153	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W	R211	1-216-025-91	METAL GLAZE	100	5%	1/10W
R154	1-216-692-11	METAL CHIP	51K	0.5%	1/10W	R212	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R155	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R213	1-216-025-91	METAL GLAZE	100	5%	1/10W
R156	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R214	1-216-025-91	METAL GLAZE	100	5%	1/10W
R157	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R215	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R158	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R216	1-216-025-91	METAL GLAZE	100	5%	1/10W
R159	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R217	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R160	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R218	1-216-025-91	METAL GLAZE	100	5%	1/10W
R161	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	R219	1-216-025-91	METAL GLAZE	100	5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R220	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R289	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R221	1-216-025-91	METAL GLAZE	100	5%	1/10W	R291	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R222	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R292	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R223	1-216-025-91	METAL GLAZE	100	5%	1/10W	R293	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R224	1-216-025-91	METAL GLAZE	100	5%	1/10W	R294	1-216-692-11	METAL CHIP	51K	0.5%	1/10W
R225	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R295	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R226	1-216-025-91	METAL GLAZE	100	5%	1/10W	R296	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R227	1-216-025-91	METAL GLAZE	100	5%	1/10W	R297	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R228	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R298	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R229	1-216-025-91	METAL GLAZE	100	5%	1/10W	R299	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R230	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R300	1-216-025-91	METAL GLAZE	100	5%	1/10W
R234	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R301	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R235	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R302	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R236	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R303	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R237	1-216-025-91	METAL GLAZE	100	5%	1/10W	R304	1-216-611-11	METAL CHIP	22	0.5%	1/10W
R238	1-216-025-91	METAL GLAZE	100	5%	1/10W	R305	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R239	1-216-658-11	METAL CHIP	2K	0.5%	1/10W	R306	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R240	1-216-647-11	METAL CHIP	680	0.5%	1/10W	R307	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R241	1-216-658-11	METAL CHIP	2K	0.5%	1/10W	R308	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R242	1-216-658-11	METAL CHIP	2K	0.5%	1/10W	R309	1-216-025-91	METAL GLAZE	100	5%	1/10W
R244	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R310	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R245	1-216-647-11	METAL CHIP	680	0.5%	1/10W	R311	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R246	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R312	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R247	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R313	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R253	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R314	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R254	1-216-025-91	METAL GLAZE	100	5%	1/10W	R315	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R255	1-216-025-91	METAL GLAZE	100	5%	1/10W	R316	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R256	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R317	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R257	1-216-025-91	METAL GLAZE	100	5%	1/10W	R318	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R258	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R319	1-216-025-91	METAL GLAZE	100	5%	1/10W
R259	1-216-025-91	METAL GLAZE	100	5%	1/10W	R320	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R260	1-216-025-91	METAL GLAZE	100	5%	1/10W	R321	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R261	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R322	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R262	1-216-025-91	METAL GLAZE	100	5%	1/10W	R323	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R263	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R324	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R264	1-216-025-91	METAL GLAZE	100	5%	1/10W	R325	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R265	1-216-025-91	METAL GLAZE	100	5%	1/10W	R326	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R266	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R327	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R267	1-216-025-91	METAL GLAZE	100	5%	1/10W	R328	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R268	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R329	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R269	1-216-025-91	METAL GLAZE	100	5%	1/10W	R330	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R270	1-216-025-91	METAL GLAZE	100	5%	1/10W	R331	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R271	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R332	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R272	1-216-655-11	METAL CHIP	1.5K	0.5%	1/10W	R333	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R273	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R334	1-216-025-91	METAL GLAZE	100	5%	1/10W
R274	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R335	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R275	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	R336	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R276	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	R337	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R277	1-216-051-00	METAL GLAZE	1.2K	5%	1/10W	R338	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R278	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R339	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R280	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R340	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R281	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	R341	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R282	1-216-045-00	METAL GLAZE	680	5%	1/10W	R342	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R283	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R343	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R284	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R344	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R285	1-216-025-91	METAL GLAZE	100	5%	1/10W	R345	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R286	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R346	1-216-025-91	METAL GLAZE	100	5%	1/10W
R287	1-216-681-11	METAL CHIP	18K	0.5%	1/10W	R347	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R288	1-216-679-11	METAL CHIP	15K	0.5%	1/10W	R348	1-216-683-11	METAL CHIP	22K	0.5%	1/10W

D

6-26

D

6-27



REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R589	1-216-025-91	METAL GLAZE	100	5%	1/10W	R647	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R590	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R648	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R591	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R649	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R592	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R650	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R593	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R651	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R594	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R652	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R595	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R653	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R596	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R654	1-216-025-91	METAL GLAZE	100	5%	1/10W
R597	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R655	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R598	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R656	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R599	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R657	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R600	1-216-025-91	METAL GLAZE	100	5%	1/10W	R658	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R601	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R659	1-216-097-91	METAL GLAZE	100K	5%	1/10W
R602	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R660	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W
R603	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R661	1-216-097-91	METAL GLAZE	100K	5%	1/10W
R604	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R662	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R605	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R663	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R606	1-216-611-11	METAL CHIP	22	0.5%	1/10W	R664	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R607	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R665	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R608	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R666	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R609	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R667	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R610	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R668	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R611	1-216-025-91	METAL GLAZE	100	5%	1/10W	R669	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W
R612	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R670	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R613	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R671	1-216-025-91	METAL GLAZE	100	5%	1/10W
R614	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R672	1-216-089-91	METAL GLAZE	47K	5%	1/10W
R615	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R673	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R616	1-216-611-11	METAL CHIP	22	0.5%	1/10W	R674	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R617	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R675	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R618	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R677	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R619	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R678	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R620	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R679	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R621	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R680	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R622	1-216-025-91	METAL GLAZE	100	5%	1/10W	R681	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R623	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R682	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R624	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R683	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R625	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R684	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R626	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R685	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R627	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R686	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R628	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R687	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R629	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R688	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R630	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R689	1-216-617-11	METAL CHIP	39	0.5%	1/10W
R631	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R690	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R632	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R691	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R633	1-216-025-91	METAL GLAZE	100	5%	1/10W	R692	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R634	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R693	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R635	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R694	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R636	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R695	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R637	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R696	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R638	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R697	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R639	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R698	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R640	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R699	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R641	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R700	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R642	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R701	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R643	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R702	1-216-685-11	METAL CHIP	27K	0.5%	1/10W
R644	1-216-025-91	METAL GLAZE	100	5%	1/10W	R703	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R645	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R704	1-216-685-11	METAL CHIP	27K	0.5%	1/10W
R646	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R705	1-216-627-11	METAL CHIP	100	0.5%	1/10W
						R706	1-216-627-11	METAL CHIP	100	0.5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R707	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R765	1-247-807-31	CARBON	100	5%	1/4W
R708	1-216-295-91	CONDUCTOR, CHIP (2012)				R766	1-247-807-31	CARBON	100	5%	1/4W
R709	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R767	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R710	1-216-295-91	CONDUCTOR, CHIP (2012)				R768	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R711	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R769	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R712	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R770	1-216-033-00	METAL GLAZE	220	5%	1/10W
R713	1-247-807-31	CARBON	100	5%	1/4W	R771	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R714	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R772	1-216-119-00	METAL GLAZE	820K	5%	1/10W
R715	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R774	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R716	1-247-807-31	CARBON	100	5%	1/4W	R775	1-216-081-00	METAL GLAZE	22K	5%	1/10W
R717	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R776	1-216-017-91	METAL GLAZE	47	5%	1/10W
R718	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R777	1-216-295-91	CONDUCTOR, CHIP (2012)			
R719	1-247-807-31	CARBON	100	5%	1/4W	R778	1-216-295-91	CONDUCTOR, CHIP (2012)			
R720	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R779	1-216-295-91	CONDUCTOR, CHIP (2012)			
R721	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R780	1-216-295-91	CONDUCTOR, CHIP (2012)			
R722	1-247-807-31	CARBON	100	5%	1/4W	R781	1-216-295-91	CONDUCTOR, CHIP (2012)			
R723	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R782	1-216-295-91	CONDUCTOR, CHIP (2012)			
R724	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R783	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R725	1-247-807-31	CARBON	100	5%	1/4W	R784	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R726	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R785	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R727	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R786	1-216-685-11	METAL CHIP	27K	0.5%	1/10W
R728	1-247-807-31	CARBON	100	5%	1/4W	R787	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R729	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R788	1-216-043-91	METAL GLAZE	560	5%	1/10W
R730	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R789	1-216-097-91	METAL GLAZE	100K	5%	1/10W
R731	1-247-807-31	CARBON	100	5%	1/4W	R790	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R732	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R791	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R733	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R792	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R734	1-247-807-31	CARBON	100	5%	1/4W	R793	1-218-754-11	METAL CHIP	120K	0.5%	1/10W
R735	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R794	1-216-681-11	METAL CHIP	18K	0.5%	1/10W
R736	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R795	1-216-681-11	METAL CHIP	18K	0.5%	1/10W
R737	1-247-807-31	CARBON	100	5%	1/4W	R796	1-216-681-11	METAL CHIP	18K	0.5%	1/10W
R738	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R797	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R739	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R798	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R740	1-247-807-31	CARBON	100	5%	1/4W	R799	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R741	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R801	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R742	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R802	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R743	1-247-807-31	CARBON	100	5%	1/4W	R803	1-216-025-91	METAL GLAZE	100	5%	1/10W
R744	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R804	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R745	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R805	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R746	1-247-807-31	CARBON	100	5%	1/4W	R806	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R747	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R807	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R748	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R808	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R749	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R809	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R750	1-247-807-31	CARBON	100	5%	1/4W	R810	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R751	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R811	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R752	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R812	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R753	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R813	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R754	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R814	1-216-025-91	METAL GLAZE	100	5%	1/10W
R755	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R815	1-216-025-91	METAL GLAZE	100	5%	1/10W
R756	1-247-807-31	CARBON	100	5%	1/4W	R816	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R757	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R817	1-216-025-91	METAL GLAZE	100	5%	1/10W
R758	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R818	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R759	1-247-807-31	CARBON	100	5%	1/4W	R819	1-216-025-91	METAL GLAZE	100	5%	1/10W
R760	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R820	1-216-025-91	METAL GLAZE	100	5%	1/10W
R761	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R821	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R762	1-247-807-31	CARBON	100	5%	1/4W	R822	1-216-025-91	METAL GLAZE	100	5%	1/10W
R763	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	R823	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W
R764	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R824	1-216-683-11	METAL CHIP	22K	0.5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
R825	1-216-677-11	METAL CHIP	12K	0.5%	1/10W		R884	1-216-097-91	METAL GLAZE	100K	5%	1/10W	
R826	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W		R885	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	
R827	1-216-692-11	METAL CHIP	51K	0.5%	1/10W		R886	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	
R828	1-216-033-00	METAL GLAZE	220	5%	1/10W		R887	1-216-693-11	METAL CHIP	56K	0.5%	1/10W	
R829	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W		R888	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
							R889	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
R830	1-218-756-11	METAL CHIP	150K	0.5%	1/10W		R890	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	
R831	1-218-768-11	METAL CHIP	470K	0.5%	1/10W		R891	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	
R832	1-216-691-11	METAL CHIP	47K	0.5%	1/10W		R892	1-214-800-11	METAL	2.2	1%	1/2W	
R833	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R893	1-214-800-11	METAL	2.2	1%	1/2W	
R834	1-218-768-11	METAL CHIP	470K	0.5%	1/10W		R894	1-215-892-11	METAL OXIDE	1K	5%	2W	F
R835	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R895	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R836	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R896	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R837	1-216-691-11	METAL CHIP	47K	0.5%	1/10W		R897	1-216-049-91	METAL GLAZE	1K	5%	1/10W	
R838	1-216-691-11	METAL CHIP	47K	0.5%	1/10W		R898	1-216-097-91	METAL GLAZE	100K	5%	1/10W	
R839	1-216-691-11	METAL CHIP	47K	0.5%	1/10W		R899	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	
R840	1-218-764-11	METAL CHIP	330K	0.5%	1/10W		R900	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	
R841	1-218-764-11	METAL CHIP	330K	0.5%	1/10W		R901	1-216-693-11	METAL CHIP	56K	0.5%	1/10W	
R842	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R902	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
R843	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R903	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
R844	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R904	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	
R845	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R905	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	
R846	1-218-756-11	METAL CHIP	150K	0.5%	1/10W		R906	1-214-800-11	METAL	2.2	1%	1/2W	
R847	1-218-756-11	METAL CHIP	150K	0.5%	1/10W		R907	1-214-800-11	METAL	2.2	1%	1/2W	
R848	1-216-025-91	METAL GLAZE	100	5%	1/10W		R908	1-215-892-11	METAL OXIDE	1K	5%	2W	F
R849	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R909	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R850	1-218-764-11	METAL CHIP	330K	0.5%	1/10W		R910	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R851	1-218-764-11	METAL CHIP	330K	0.5%	1/10W		R911	1-216-049-91	METAL GLAZE	1K	5%	1/10W	
R852	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R912	1-216-097-91	METAL GLAZE	100K	5%	1/10W	
R853	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R913	1-216-085-00	METAL GLAZE	11K	5%	1/10W	
R854	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R914	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R855	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R915	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R856	1-218-754-11	METAL CHIP	120K	0.5%	1/10W		R916	1-216-071-00	METAL GLAZE	10K	5%	1/10W	
R857	1-216-668-11	METAL CHIP	5.1K	0.5%	1/10W		R917	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R858	1-216-668-11	METAL CHIP	5.1K	0.5%	1/10W		R918	1-216-061-91	METAL GLAZE	3.9K	5%	1/10W	
R859	1-216-668-11	METAL CHIP	5.1K	0.5%	1/10W		R919	1-216-061-91	METAL GLAZE	3.9K	5%	1/10W	
R860	1-218-756-11	METAL CHIP	150K	0.5%	1/10W		R920	1-216-109-00	METAL GLAZE	330K	5%	1/10W	
R861	1-218-768-11	METAL CHIP	470K	0.5%	1/10W		R921	1-216-071-00	METAL GLAZE	10K	5%	1/10W	
R862	1-216-691-11	METAL CHIP	47K	0.5%	1/10W		R922	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R863	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R923	1-216-097-91	METAL GLAZE	100K	5%	1/10W	
R864	1-218-764-11	METAL CHIP	330K	0.5%	1/10W		R924	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
R865	1-218-764-11	METAL CHIP	330K	0.5%	1/10W		R925	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R866	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R926	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R867	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R927	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	
R868	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R928	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R869	1-216-627-11	METAL CHIP	100	0.5%	1/10W		R929	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R870	1-218-756-11	METAL CHIP	150K	0.5%	1/10W		R930	1-216-057-00	METAL GLAZE	2.2K	5%	1/10W	
R871	1-216-677-11	METAL CHIP	12K	0.5%	1/10W		R931	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R872	1-216-651-11	METAL CHIP	1K	0.5%	1/10W		R932	1-216-049-91	METAL GLAZE	1K	5%	1/10W	
R873	1-216-693-11	METAL CHIP	56K	0.5%	1/10W		R933	1-214-804-11	METAL	3.3	1%	1/2W	
R874	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		R934	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R875	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		R935	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R876	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W		R936	1-216-049-91	METAL GLAZE	1K	5%	1/10W	
R877	1-216-651-11	METAL CHIP	1K	0.5%	1/10W		R937	1-214-804-11	METAL	3.3	1%	1/2W	
R878	1-214-800-11	METAL	2.2	1%	1/2W		R938	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R879	1-214-800-11	METAL	2.2	1%	1/2W		R939	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R880	1-215-892-11	METAL OXIDE	1K	5%	2W	F	R940	1-216-049-91	METAL GLAZE	1K	5%	1/10W	
R881	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W		R941	1-214-804-11	METAL	3.3	1%	1/2W	
R882	1-216-081-00	METAL GLAZE	22K	5%	1/10W								
R883	1-216-049-91	METAL GLAZE	1K	5%	1/10W								

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R942	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1115	1-216-025-91	METAL GLAZE	100	5%	1/10W
R943	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R1116	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R944	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1117	1-216-627-11	METAL CHIP	100	0.5%	1/10W
						R1119	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R945	1-216-049-91	METAL GLAZE	1K	5%	1/10W						
R946	1-214-804-11	METAL	3.3	1%	1/2W	R1120	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R947	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1121	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R948	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1122	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R949	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R1123	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
						R1124	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R950	1-214-804-11	METAL	3.3	1%	1/2W						
R951	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1125	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R952	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1126	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R953	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R1127	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R954	1-214-804-11	METAL	3.3	1%	1/2W	R1128	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
						R1129	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R955	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R956	1-216-691-11	METAL CHIP	47K	0.5%	1/10W	R1130	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R960	1-218-754-11	METAL CHIP	120K	0.5%	1/10W	R1131	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R961	1-218-754-11	METAL CHIP	120K	0.5%	1/10W	R1133	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R962	1-218-756-11	METAL CHIP	150K	0.5%	1/10W	R1134	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
						R1135	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R963	1-218-756-11	METAL CHIP	150K	0.5%	1/10W						
R964	1-218-756-11	METAL CHIP	150K	0.5%	1/10W	R1142	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R965	1-216-105-91	METAL GLAZE	220K	5%	1/10W	R1143	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R966	1-216-105-91	METAL GLAZE	220K	5%	1/10W	R1144	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R967	1-216-105-91	METAL GLAZE	220K	5%	1/10W	R1145	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
						R1146	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R969	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R970	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1148	1-216-025-91	METAL GLAZE	100	5%	1/10W
R971	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1149	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R972	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1150	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
						R1151	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R973	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1153	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R974	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R975	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1154	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R976	1-249-417-11	CARBON	1K	5%	1/4W	R1155	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R977	1-249-417-11	CARBON	1K	5%	1/4W	R1156	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
						R1157	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R978	1-249-417-11	CARBON	1K	5%	1/4W	R1158	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R979	1-249-417-11	CARBON	1K	5%	1/4W						
R980	1-249-417-11	CARBON	1K	5%	1/4W	R1159	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R981	1-249-417-11	CARBON	1K	5%	1/4W	R1161	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R982	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R1163	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R1164	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R983	1-216-097-91	METAL GLAZE	100K	5%	1/10W	R1165	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R984	1-216-699-11	METAL CHIP	100K	0.5%	1/10W						
R985	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R1166	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R986	1-249-425-11	CARBON	4.7K	5%	1/4W	R1167	1-216-691-11	METAL CHIP	4.7K	0.5%	1/10W
R1005	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R1169	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
						R1171	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R1006	1-216-699-11	METAL CHIP	100K	0.5%	1/10W	R1175	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R1007	1-216-089-91	METAL GLAZE	47K	5%	1/10W						
R1008	1-216-085-00	METAL GLAZE	33K	5%	1/10W	R1181	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R1009	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R1182	1-216-025-91	METAL GLAZE	100	5%	1/10W
R1010	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R1184	1-216-627-11	METAL CHIP	100	0.5%	1/10W
						R1187	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R1011	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W	R1188	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R1101	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W						
R1102	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R1189	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R1103	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R1195	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R1104	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R1196	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
						R1197	1-216-025-91	METAL GLAZE	100	5%	1/10W
R1105	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R1198	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R1106	1-216-627-11	METAL CHIP	100	0.5%	1/10W						
R1107	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R1199	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R1109	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R1200	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R1111	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R1201	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R1202	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R1112	1-216-627-11	METAL CHIP	100	0.5%	1/10W	R1300	1-247-839-31	CARBON	2.2K	5%	1/4W

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C39	1-102-050-00	CERAMIC	0.01MF 0.99 500V			< IC >	
C40	1-162-318-11	CERAMIC	0.001MF 10% 500V	IC1	8-759-103-93	IC μ PC393C	
C41	1-102-852-91	CERAMIC	47PF 5% 50V	IC2	8-759-103-93	IC μ PC393C	
C42	1-128-563-11	ELECT	100MF 20% 100V	IC3	8-749-012-58	IC STK392-220	
C43	1-102-824-00	CERAMIC	470PF 5% 50V	IC4	8-749-012-58	IC STK392-220	
C44	1-102-050-00	CERAMIC	0.01MF 0.99 500V			< COIL >	
C45	1-128-563-11	ELECT	100MF 20% 100V	L1	1-406-975-21	COIL, CHOKE 47 μ H	
C46	1-162-318-11	CERAMIC	0.001MF 10% 500V	L2	1-406-975-21	COIL, CHOKE 47 μ H	
C47	1-162-318-11	CERAMIC	0.001MF 10% 500V	L3	1-406-975-21	COIL, CHOKE 47 μ H	
C48	1-162-318-11	CERAMIC	0.001MF 10% 500V	L4	1-406-975-21	COIL, CHOKE 47 μ H	
C49	1-102-050-00	CERAMIC	0.01MF 0.99 500V			< TRANSISTOR >	
C50	1-102-852-91	CERAMIC	47PF 5% 50V	Q1	8-729-207-82	TRANSISTOR 2SC3421-Y	
C51	1-128-563-11	ELECT	100MF 20% 100V	Q2	8-729-207-89	TRANSISTOR 2SA1358-Y	
C52	1-102-824-00	CERAMIC	470PF 5% 50V	Q3	8-729-030-03	TRANSISTOR DTC144ESA-TP	
C53	1-102-824-00	CERAMIC	470PF 5% 50V	Q4	8-729-030-03	TRANSISTOR DTC144ESA-TP	
C54	1-162-318-11	CERAMIC	0.001MF 10% 500V	Q5	8-729-119-78	TRANSISTOR 2SC2785-HFE	
C55	1-102-824-00	CERAMIC	470PF 5% 50V	Q6	8-729-119-76	TRANSISTOR 2SA1175-HFE	
C56	1-102-050-00	CERAMIC	0.01MF 0.99 500V	Q7	8-729-119-76	TRANSISTOR 2SA1175-HFE	
C57	1-162-318-11	CERAMIC	0.001MF 10% 500V	Q8	8-729-119-78	TRANSISTOR 2SC2785-HFE	
C58	1-128-563-11	ELECT	100MF 20% 100V	Q9	8-729-119-78	TRANSISTOR 2SC2785-HFE	
C59	1-162-318-11	CERAMIC	0.001MF 10% 500V	Q10	8-729-119-76	TRANSISTOR 2SA1175-HFE	
C60	1-102-824-00	CERAMIC	470PF 5% 50V	Q11	8-729-207-82	TRANSISTOR 2SC3421-Y	
C61	1-102-824-00	CERAMIC	470PF 5% 50V	Q12	8-729-207-82	TRANSISTOR 2SC3421-Y	
C62	1-162-318-11	CERAMIC	0.001MF 10% 500V			< RESISTOR >	
C63	1-102-852-91	CERAMIC	47PF 5% 50V	R1	1-247-807-31	CARBON 100 5% 1/4W	
C64	1-102-852-91	CERAMIC	47PF 5% 50V	R2	1-249-429-11	CARBON 10K 5% 1/4W	
C65	1-102-852-91	CERAMIC	47PF 5% 50V	R3	1-249-429-11	CARBON 10K 5% 1/4W	
C66	1-102-852-91	CERAMIC	47PF 5% 50V	R4	1-247-807-31	CARBON 100 5% 1/4W	
C67	1-102-824-00	CERAMIC	470PF 5% 50V	R5	1-249-429-11	CARBON 10K 5% 1/4W	
C68	1-102-824-00	CERAMIC	470PF 5% 50V	R6	1-249-437-11	CARBON 47K 5% 1/4W	
C69	1-102-824-00	CERAMIC	470PF 5% 50V	R7	1-249-437-11	CARBON 47K 5% 1/4W	
C70	1-102-824-00	CERAMIC	470PF 5% 50V	R8	1-249-441-11	CARBON 100K 5% 1/4W	
C71	1-162-318-11	CERAMIC	0.001MF 10% 500V	R9	1-249-441-11	CARBON 100K 5% 1/4W	
C72	1-102-050-00	CERAMIC	0.01MF 0.99 500V	R10	1-249-429-11	CARBON 10K 5% 1/4W	
C73	1-162-318-11	CERAMIC	0.001MF 10% 500V	R11	1-249-389-11	CARBON 4.7 5% 1/4W	F
C74	1-128-563-11	ELECT	100MF 20% 100V	R12	1-249-421-11	CARBON 2.2K 5% 1/4W	
C75	1-102-050-00	CERAMIC	0.01MF 0.99 500V	R13	1-249-421-11	CARBON 2.2K 5% 1/4W	
C76	1-162-318-11	CERAMIC	0.001MF 10% 500V	R14	1-249-413-11	CARBON 470 5% 1/4W	
C77	1-128-563-11	ELECT	100MF 20% 100V	R15	1-216-069-00	CARBON 6.8K 5% 1/4W	
C78	1-126-933-11	ELECT	100MF 20% 16V	R16	1-249-413-11	CARBON 470 5% 1/4W	
		< CONNECTOR >		R17	1-216-069-00	CARBON 6.8K 5% 1/4W	
CN302	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P		R18	1-249-389-11	CARBON 4.7 5% 1/4W	F
CN303	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P		R19	1-249-421-11	CARBON 2.2K 5% 1/4W	
CN304	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P		R20	1-249-421-11	CARBON 2.2K 5% 1/4W	
CN305	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P		R21	1-247-863-91	CARBON 22K 5% 1/4W	
CN306	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P		R22	1-249-441-11	CARBON 100K 5% 1/4W	
CN307	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P		R23	1-249-441-11	CARBON 100K 5% 1/4W	
		< DIODE >		R24	1-247-863-91	CARBON 22K 5% 1/4W	
D1	8-719-109-85	DIODE RD5.1ESB2		R25	1-216-389-11	METAL OXIDE 1 5% 3W	F
D2	8-719-109-85	DIODE RD5.1ESB2		R26	1-216-389-11	METAL OXIDE 1 5% 3W	F
D3	8-719-109-85	DIODE RD5.1ESB2		R27	1-249-429-11	CARBON 10K 5% 1/4W	
D4	8-719-109-85	DIODE RD5.1ESB2		R28	1-216-389-11	METAL OXIDE 1 5% 3W	F
D17	8-719-911-19	DIODE 1SS119-25		R29	1-216-389-11	METAL OXIDE 1 5% 3W	F
D18	8-719-911-19	DIODE 1SS119-25		R30	1-249-429-11	CARBON 10K 5% 1/4W	
				R31	1-247-807-31	CARBON 100 5% 1/4W	

DC

DCR

DD

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R32	1-247-807-31	CARBON	100	5%	1/4W	R91	1-247-815-91	CARBON	220	5%	1/4W
R33	1-247-807-31	CARBON	100	5%	1/4W	R92	1-247-815-91	CARBON	220	5%	1/4W
R34	1-249-429-11	CARBON	10K	5%	1/4W	R93	1-215-433-00	METAL	3.3K	1%	1/4W
R35	1-249-429-11	CARBON	10K	5%	1/4W	R94	1-215-413-00	METAL	470	1%	1/4W
R36	1-247-807-31	CARBON	100	5%	1/4W	R95	1-215-413-00	METAL	470	1%	1/4W
R37	1-247-863-91	CARBON	22K	5%	1/4W	R96	1-247-815-91	CARBON	220	5%	1/4W
R38	1-247-863-91	CARBON	22K	5%	1/4W	R97	1-215-413-00	METAL	470	1%	1/4W
R39	1-247-807-31	CARBON	100	5%	1/4W	R98	1-215-413-00	METAL	470	1%	1/4W
R40	1-247-807-31	CARBON	100	5%	1/4W	R99	1-215-433-00	METAL	3.3K	1%	1/4W
R41	1-247-863-91	CARBON	22K	5%	1/4W	R100	1-215-433-00	METAL	3.3K	1%	1/4W
R42	1-247-863-91	CARBON	22K	5%	1/4W	R101	1-215-433-00	METAL	3.3K	1%	1/4W
R43	1-249-425-11	CARBON	4.7K	5%	1/4W	R102	1-215-433-00	METAL	3.3K	1%	1/4W
R44	1-249-425-11	CARBON	4.7K	5%	1/4W	R103	1-249-405-11	CARBON	100	5%	1/4W
R45	1-247-863-91	CARBON	22K	5%	1/4W	R104	1-249-405-11	CARBON	100	5%	1/4W
R46	1-247-863-91	CARBON	22K	5%	1/4W	R105	1-216-475-11	METAL OXIDE	120	5%	3W
R47	1-249-425-11	CARBON	4.7K	5%	1/4W	R106	1-216-475-11	METAL OXIDE	120	5%	3W
R48	1-249-425-11	CARBON	4.7K	5%	1/4W	R107	1-216-475-11	METAL OXIDE	120	5%	3W
R49	1-249-441-11	CARBON	100K	5%	1/4W	R108	1-216-475-11	METAL OXIDE	120	5%	3W
R50	1-249-441-11	CARBON	100K	5%	1/4W	R109	1-216-475-11	METAL OXIDE	120	5%	3W
R51	1-247-863-91	CARBON	22K	5%	1/4W	R110	1-216-475-11	METAL OXIDE	120	5%	3W
R52	1-247-863-91	CARBON	22K	5%	1/4W	R111	1-247-903-00	CARBON	1M	5%	1/4W
R53	1-249-425-11	CARBON	4.7K	5%	1/4W	R112	1-247-903-00	CARBON	1M	5%	1/4W
R54	1-249-425-11	CARBON	4.7K	5%	1/4W	< TEST PIN >					
R55	1-247-863-91	CARBON	22K	5%	1/4W	TP1	1-537-864-11	PIN, POST			
R56	1-247-863-91	CARBON	22K	5%	1/4W	TP2	1-537-864-11	PIN, POST			
R57	1-247-863-91	CARBON	22K	5%	1/4W	TP3	1-537-864-11	PIN, POST			
R58	1-249-434-11	CARBON	27K	5%	1/4W	TP4	1-537-864-11	PIN, POST			
R59	1-249-434-11	CARBON	27K	5%	1/4W	TP5	1-537-864-11	PIN, POST			
R60	1-249-425-11	CARBON	4.7K	5%	1/4W	TP6	1-537-864-11	PIN, POST			
R61	1-247-863-91	CARBON	22K	5%	1/4W	TP7	1-537-864-11	PIN, POST			
R62	1-249-425-11	CARBON	4.7K	5%	1/4W	TP8	1-537-864-11	PIN, POST			
R63	1-247-807-31	CARBON	100	5%	1/4W	TP9	1-537-864-11	PIN, POST			
R64	1-247-807-31	CARBON	100	5%	1/4W	*****					
R65	1-247-815-91	CARBON	220	5%	1/4W	* A-1343-194-A DCR MOUNTED PC BOARD					
R66	1-215-433-00	METAL	3.3K	1%	1/4W	*****					
R67	1-247-815-91	CARBON	220	5%	1/4W	< CONNECTOR >					
R68	1-247-815-91	CARBON	220	5%	1/4W	CN2	* 1-774-245-11	CONNECTOR, BOARD TO BOARD 8P			
R69	1-215-433-00	METAL	3.3K	1%	1/4W	< RESISTOR >					
R70	1-247-815-91	CARBON	220	5%	1/4W	R1101	1-214-816-00	METAL	10	1%	1/2W
R71	1-215-413-00	METAL	470	1%	1/4W	R1102	1-214-816-00	METAL	10	1%	1/2W
R72	1-215-433-00	METAL	3.3K	1%	1/4W	R1103	1-214-816-00	METAL	10	1%	1/2W
R73	1-249-405-11	CARBON	100	5%	1/4W	R1104	1-214-816-00	METAL	10	1%	1/2W
R74	1-249-405-11	CARBON	100	5%	1/4W	R1105	1-214-816-00	METAL	10	1%	1/2W
R75	1-247-807-31	CARBON	100	5%	1/4W	R1109	1-214-816-00	METAL	10	1%	1/2W
R76	1-215-413-00	METAL	470	1%	1/4W	R1110	1-214-816-00	METAL	10	1%	1/2W
R77	1-215-433-00	METAL	3.3K	1%	1/4W	R1111	1-214-816-00	METAL	10	1%	1/2W
R78	1-247-807-31	CARBON	100	5%	1/4W	R1112	1-214-816-00	METAL	10	1%	1/2W
R79	1-249-405-11	CARBON	100	5%	1/4W	R1113	1-214-816-00	METAL	10	1%	1/2W
R80	1-215-433-00	METAL	3.3K	1%	1/4W	*****					
R81	1-249-405-11	CARBON	100	5%	1/4W	* A-1343-311-A DD MOUNTED PC BOARD					
R82	1-215-433-00	METAL	3.3K	1%	1/4W	*****					
R83	1-247-807-31	CARBON	100	5%	1/4W						
R84	1-247-815-91	CARBON	220	5%	1/4W						
R85	1-247-815-91	CARBON	220	5%	1/4W						
R86	1-247-815-91	CARBON	220	5%	1/4W						
R87	1-247-807-31	CARBON	100	5%	1/4W						
R88	1-247-815-91	CARBON	220	5%	1/4W						
R89	1-215-433-00	METAL	3.3K	1%	1/4W						
R90	1-247-815-91	CARBON	220	5%	1/4W						

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
< CAPACITOR >							R12	1-216-603-11	METAL CHIP	10	0.5%	1/10W	
C1	1-128-004-11	ELECT CHIP	10MF	20%	16V		R13	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
C2	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R14	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	
C3	1-128-004-11	ELECT CHIP	10MF	20%	16V		R15	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C4	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R16	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	
C5	1-128-004-11	ELECT CHIP	10MF	20%	16V		R17	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C6	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R18	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	
C7	1-128-004-11	ELECT CHIP	10MF	20%	16V		R19	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	
C8	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R20	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C9	1-163-251-11	CERAMIC CHIP	100PF	5%	50V		R21	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	
C10	1-128-004-11	ELECT CHIP	10MF	20%	16V		R22	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	
C11	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R23	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C12	1-128-004-11	ELECT CHIP	10MF	20%	16V		R24	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	
C13	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R25	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	
C14	1-163-239-11	CERAMIC CHIP	33PF	5%	50V		R26	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C15	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R27	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W	
C16	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R28	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	
C17	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R29	1-216-647-11	METAL CHIP	680	0.5%	1/10W	
C18	1-163-031-11	CERAMIC CHIP	0.01MF		50V		R30	1-218-774-11	METAL CHIP	820K	0.5%	1/10W	
C19	1-128-589-11	ELECT CHIP	47MF	20%	6.3V		R31	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	
C20	1-128-589-11	ELECT CHIP	47MF	20%	6.3V		R32	1-216-695-11	METAL CHIP	68K	0.5%	1/10W	
C21	1-164-346-11	CERAMIC CHIP	1MF		16V		R33	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C22	1-128-004-11	ELECT CHIP	10MF	20%	16V		R34	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C23	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		R35	1-216-025-91	METAL GLAZE	100	5%	1/10W	
C24	1-163-031-11	CERAMIC CHIP	0.01MF		50V		< VARIABLE RESISTOR >						
C25	1-163-031-11	CERAMIC CHIP	0.01MF		50V		RV1	1-238-787-11	RES, ADJ, CERMET 10K				
< CONNECTOR >							RV2	1-238-783-11	RES, ADJ, CERMET 500				
CN1	* 1-695-986-11	SOCKET, CONNECTOR 40P					RV3	1-238-786-11	RES, ADJ, CERMET 5K				
< DIODE >							< TEST PIN >						
D1	8-719-801-78	DIODE 1SS184					TP1	* 1-535-877-22	CHIP, CHECKER				
< IC >							TP2	* 1-535-877-22	CHIP, CHECKER				
IC1	8-759-445-84	IC AD835AR					TP3	* 1-535-877-22	CHIP, CHECKER				
IC2	8-752-068-37	IC CXA1726AM					*****						
IC3	8-759-239-55	IC TC74HC123AF					* A-1343-201-A	DM MOUNTED PC BOARD					
IC4	8-759-381-53	IC μ PC814G2-E2					*****						
IC5	8-759-381-53	IC μ PC814G2-E2					*****						
IC6	8-759-381-53	IC μ PC814G2-E2					* A-1346-534-A	E COMPLETE PC BOARD (Include EA Mounted PC BOARD)					
< TRANSISTOR >							*****						
Q1	8-729-105-73	TRANSISTOR 2SK523-L2					* X-4033-998-1	STAY ASSY					
Q2	8-729-216-22	TRANSISTOR 2SA1162-G					3-701-809-31	SCREW, TERMINAL (M3X8)					
< RESISTOR >							4-056-064-01	HOLDER (A), TR					
R1	1-216-025-91	METAL GLAZE	100	5%	1/10W		4-056-065-01	HOLDER (B), TR					
R2	1-216-025-91	METAL GLAZE	100	5%	1/10W		4-056-066-01	HOLDER (C), TR					
R3	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W		* 4-056-076-01	PIN, GUIDE					
R4	1-216-689-11	METAL CHIP	39K	0.5%	1/10W		4-056-102-01	LOCK, CARD					
R5	1-216-691-11	METAL CHIP	47K	0.5%	1/10W		7-626-317-21	PIN, SPRING 2.5X8					
R6	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W		7-682-949-01	SCREW +PSW 3X10					
R7	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W		7-685-646-79	SCREW +BVTP 3X8 TYPE2 N S					
R8	1-216-025-91	METAL GLAZE	100	5%	1/10W		* 7-322-065-72	RUBBER, RTV (SE-9168)(130G)					
R9	1-216-025-91	METAL GLAZE	100	5%	1/10W		< CAPACITOR >						
R10	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		C1	1-117-405-51	ELECT	4700MF	20%	16V	
R11	1-216-025-91	METAL GLAZE	100	5%	1/10W		C2	1-117-405-51	ELECT	4700MF	20%	16V	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C3	1-117-408-51	ELECT	4700MF 20% 16V	C155	1-136-153-00	FILM	0.01MF 5% 50V
C4	1-162-114-00	CERAMIC	0.0047MF 2KV	C156	1-136-165-00	FILM	0.1MF 5% 50V
C13	1-117-408-11	FILM	3900PF 0.03 2KV	C157	1-136-157-00	FILM	0.022MF 5% 50V
C14	1-117-408-11	FILM	3900PF 0.03 2KV	C158	1-128-475-11	ELECT	10MF 160V
C21	1-136-945-11	FILM	8.2MF 5% 200V	C159	1-107-746-11	ELECT	10MF 20% 200V
C22	1-136-945-11	FILM	8.2MF 5% 200V	C160	1-136-111-00	FILM	1MF 5% 200V
C23	1-136-945-11	FILM	8.2MF 5% 200V	C161	1-126-960-11	ELECT	1MF 20% 50V
C24	1-136-945-11	FILM	8.2MF 5% 200V	C162	1-136-111-00	FILM	1MF 5% 200V
C25	1-136-945-11	FILM	8.2MF 5% 200V	C163	1-126-964-11	ELECT	10MF 20% 50V
C26	1-136-945-11	FILM	8.2MF 5% 200V	C164	1-126-964-11	ELECT	10MF 20% 50V
C31	1-126-964-11	ELECT	10MF 20% 50V	C165	1-126-964-11	ELECT	10MF 20% 50V
C32	1-126-964-11	ELECT	10MF 20% 50V	C166	1-126-964-11	ELECT	10MF 20% 50V
C33	1-126-969-11	ELECT	220MF 20% 50V	C167	1-102-824-00	CERAMIC	470PF 5% 50V
C36	1-162-116-00	CERAMIC	680PF 10% 2KV	C168	1-136-153-00	FILM	0.01MF 5% 50V
C37	1-162-116-00	CERAMIC	680PF 10% 2KV	C169	1-124-768-11	ELECT	4.7MF 20% 50V
C38	1-162-116-00	CERAMIC	680PF 10% 2KV	C170	1-126-966-11	ELECT	33MF 20% 16V
C101	1-102-973-00	CERAMIC	100PF 5% 50V	C171	1-136-153-00	FILM	0.01MF 5% 50V
C102	1-136-159-00	FILM	0.033MF 5% 50V	C172	1-107-902-11	ELECT	1MF 20% 50V
C103	1-136-165-00	FILM	0.1MF 5% 50V	C173	1-126-966-11	ELECT	33MF 20% 16V
C104	1-136-165-00	FILM	0.1MF 5% 50V	C174	1-126-966-11	ELECT	33MF 20% 16V
C105	1-136-165-00	FILM	0.1MF 5% 50V	C175	1-136-722-11	FILM	0.008MF 0.03 1.6KV
C106	1-136-165-00	FILM	0.1MF 5% 50V	C176	1-104-999-11	MYLAR	0.1MF 10% 200V
C107	1-136-153-00	FILM	0.01MF 5% 50V	C177	1-126-964-11	ELECT	10MF 20% 50V
C108	1-102-824-00	CERAMIC	470PF 5% 50V	< CONNECTOR >			
C109	1-126-960-11	ELECT	1MF 20% 50V	CN232	* 1-750-916-11	PIN, CONNECTOR(DY)(PC BOARD)8P	
C110	1-126-933-11	ELECT	100MF 20% 16V	CN233	* 1-750-916-11	PIN, CONNECTOR(DY)(PC BOARD)8P	
C111	1-126-933-11	ELECT	100MF 20% 16V	CN234	* 1-750-916-11	PIN, CONNECTOR(DY)(PC BOARD)8P	
C112	1-126-933-11	ELECT	100MF 20% 16V	CN235	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P	
C113	1-126-965-11	ELECT	22MF 20% 50V	CN236	* 1-774-248-11	CONNECTOR, BOARD TO BOARD 8P	
C114	1-101-821-00	CERAMIC	0.0022MF 500V	< DIODE >			
C115	1-102-824-00	CERAMIC	470PF 5% 50V	D1	8-719-059-41	DIODE D082RC SONY	
C116	1-101-004-00	CERAMIC	0.01MF 50V	D2	8-719-054-88	DIODE DFC1STR	
C117	1-101-004-00	CERAMIC	0.01MF 50V	D3	8-719-054-88	DIODE DFC1STR	
C118	1-136-165-00	FILM	0.1MF 5% 50V	D4	8-719-054-88	DIODE DFC1STR	
C119	1-136-165-00	FILM	0.1MF 5% 50V	D5	8-719-054-88	DIODE DFC1STR	
C120	1-107-746-11	ELECT	10MF 20% 200V	D6	8-719-054-88	DIODE DFC1STR	
C121	1-136-165-00	FILM	0.1MF 5% 50V	D7	8-719-054-88	DIODE DFC1STR	
C122	1-136-165-00	FILM	0.1MF 5% 50V	D8	8-719-948-45	DIODE ERA22-08	
C125	1-136-153-00	FILM	0.01MF 5% 50V	D9	8-719-920-67	DIODE ERC91-02	
C126	1-137-364-11	FILM	0.001MF 5% 50V	D11	8-719-110-41	DIODE RD15ESB2	
C128	1-107-746-11	ELECT	10MF 20% 200V	D101	8-719-110-53	DIODE RD20ESB2	
C129	1-107-746-11	ELECT	10MF 20% 200V	D102	8-719-911-19	DIODE ISS119-25	
C133	1-109-889-11	ELECT	1MF 20% 50V	D103	8-719-911-19	DIODE ISS119-25	
C134	1-104-665-11	ELECT	100MF 20% 25V	D104	8-719-911-19	DIODE ISS119-25	
C135	1-104-665-11	ELECT	100MF 20% 25V	D105	8-719-948-45	DIODE ERA22-08	
C142	1-125-538-11	ELECT(BLOCK)	1000MF 20% 200V	D106	8-719-948-45	DIODE ERA22-08	
C143	1-102-824-00	CERAMIC	470PF 5% 50V	D107	8-719-110-41	DIODE RD15ESB2	
C144	1-136-165-00	FILM	0.1MF 5% 50V	D108	8-719-110-41	DIODE RD15ESB2	
C145	1-136-153-00	FILM	0.01MF 5% 50V	D109	8-719-948-45	DIODE ERA22-08	
C146	1-136-173-00	FILM	0.47MF 5% 50V	D110	8-719-911-19	DIODE ISS119-25	
C147	1-136-173-00	FILM	0.47MF 5% 50V	D111	8-719-911-19	DIODE ISS119-25	
C148	1-126-933-11	ELECT	100MF 20% 16V	D112	8-719-911-19	DIODE ISS119-25	
C149	1-126-964-11	ELECT	10MF 20% 50V	D113	8-719-911-19	DIODE ISS119-25	
C150	1-137-364-11	FILM	0.001MF 5% 50V	D114	8-719-110-53	DIODE RD20ESB2	
C151	1-126-960-11	ELECT	1MF 20% 50V	D115	8-719-110-53	DIODE RD20ESB2	
C152	1-136-165-00	FILM	0.1MF 5% 50V	D116	8-719-920-67	DIODE ERC91-02	
C153	1-126-966-11	ELECT	33MF 20% 16V	D117	8-719-911-19	DIODE ISS119-25	
C154	1-136-165-00	FILM	0.1MF 5% 50V				

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
D118	8-719-948-45	DIODE ERA22-08		L109	1-406-989-21	COIL, CHOKE 10mH	
D119	8-719-911-19	DIODE ISS119-25		L110	1-406-989-21	COIL, CHOKE 10mH	
D120	8-719-110-63	DIODE RD24ESB3		L111	1-410-093-11	INDUCTOR 33mH	
D121	8-719-911-19	DIODE ISS119-25		L113	1-410-680-31	INDUCTOR 330μH	
D122	8-719-110-63	DIODE RD24ESB3		L115	1-410-067-21	INDUCTOR 4.7mH	
D123	8-719-911-19	DIODE ISS119-25				< VARIABLE COIL >	
D124	8-719-948-45	DIODE ERA22-08		LV1	1-411-568-11	COIL, HORIZONTAL ADJUSTMENT	
D125	8-719-110-72	DIODE RD30ESB2		LV2	1-411-568-11	COIL, HORIZONTAL ADJUSTMENT	
D126	8-719-110-88	DIODE RD39ESB2		LV3	1-411-568-11	COIL, HORIZONTAL ADJUSTMENT	
D127	8-719-110-41	DIODE RD15ESB2				< TRANSISTOR >	
D128	8-719-110-41	DIODE RD15ESB2		Q1	8-729-142-69	TRANSISTOR 2SK817	
D129	8-719-110-41	DIODE RD15ESB2		Q2	8-729-142-68	TRANSISTOR 2SJ143	
D130	8-719-110-41	DIODE RD15ESB2		Q3	8-729-142-69	TRANSISTOR 2SK817	
D131	8-719-911-19	DIODE ISS119-25		Q4	8-729-142-68	TRANSISTOR 2SJ143	
D132	8-719-911-19	DIODE ISS119-25		Q5	8-729-142-69	TRANSISTOR 2SK817	
D133	8-719-911-19	DIODE ISS119-25		Q6	8-729-142-68	TRANSISTOR 2SJ143	
D134	8-719-300-80	DIODE RU-1C		Q7	8-729-033-56	TRANSISTOR 2SC5238-CB	
D135	8-719-300-80	DIODE RU-1C		Q8	8-729-033-56	TRANSISTOR 2SC5238-CB	
D136	8-719-300-80	DIODE RU-1C		Q11	8-729-119-76	TRANSISTOR 2SA1175-HFE	
D137	8-719-300-80	DIODE RU-1C		Q12	8-729-030-03	TRANSISTOR DTC144ESA-TP	
D138	8-719-911-19	DIODE ISS119-25		Q13	8-729-032-26	TRANSISTOR IRF19620GS	
D139	8-719-911-19	DIODE ISS119-25		Q101	8-729-105-74	TRANSISTOR 2SK523-M1	
D140	8-719-911-19	DIODE ISS119-25		Q102	8-729-030-03	TRANSISTOR DTC144ESA-TP	
D141	8-719-911-19	DIODE ISS119-25		Q103	8-729-119-78	TRANSISTOR 2SC2785-HFE	
D142	8-719-911-19	DIODE ISS119-25		Q104	8-729-119-76	TRANSISTOR 2SA1175-HFE	
D143	8-719-911-19	DIODE ISS119-25		Q105	8-729-030-03	TRANSISTOR DTC144ESA-TP	
D144	8-719-901-19	DIODE V11N		Q106	8-729-119-78	TRANSISTOR 2SC2785-HFE	
D145	8-719-911-19	DIODE ISS119-25		Q107	8-729-018-60	TRANSISTOR 2SD2012-LC	
D146	8-719-948-45	DIODE ERA22-08		Q108	8-729-140-96	TRANSISTOR 2SD774-34	
D147	8-719-110-72	DIODE RD30ESB2		Q111	8-729-143-42	TRANSISTOR 2SK929	
D149	8-719-911-19	DIODE ISS119-25		Q112	8-729-142-68	TRANSISTOR 2SJ143	
		< FERRITE BEAD >		Q113	8-729-119-78	TRANSISTOR 2SC2785-HFE	
FBI	1 410-396-41	FERRITE BEAD INDUCTOR 0.45μH		Q115	8-729-030-03	TRANSISTOR DTC144ESA-TP	
		< IC >		Q116	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC101	8-759-345-38	IC HD14538BP		Q117	8-729-119-76	TRANSISTOR 2SA1175-HFE	
IC102	8-759-145-58	IC μPC4558C		Q118	8-729-105-74	TRANSISTOR 2SK523-M1	
IC103	8-759-109-82	IC μPC814C		Q130	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC104	8-759-145-58	IC μPC4558C		Q131	8-729-119-76	TRANSISTOR 2SA1175-HFE	
IC105	8-759-145-58	IC μPC4558C		Q132	8-729-119-76	TRANSISTOR 2SA1175-HFE	
IC106	8-759-145-58	IC μPC4558C		Q133	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC107	8-759-433-43	IC MC1495BP		Q134	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC108	8-759-442-21	IC MC1436CPI		Q135	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC109	8-759-231-58	IC TA7812S		Q136	8-729-119-76	TRANSISTOR 2SA1175-HFE	
IC110	8-759-929-65	IC LM7912CT		Q137	8-729-119-80	TRANSISTOR 2SC2688-LK	
IC111	8-759-145-58	IC μPC4558C		Q138	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC112	8-759-145-58	IC μPC4558C		Q139	8-729-119-76	TRANSISTOR 2SA1175-HFE	
IC113	8-759-103-93	IC μPC393C		Q140	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC114	8-759-103-93	IC μPC393C		Q141	8-729-119-78	TRANSISTOR 2SC2785-HFE	
IC115	8-759-145-58	IC μPC4558C		Q142	8-729-143-42	TRANSISTOR 2SK929	
		< COIL >		Q143	8-729-119-80	TRANSISTOR 2SC2688-LK	
L103	1-406-663-21	COIL, CHOKE 47μH		Q144	8-729-905-86	TRANSISTOR 2SC4014N	
L104	1-406-663-21	COIL, CHOKE 47μH		Q145	8-729-402-03	TRANSISTOR 2SK755	
L106	1-406-976-11	COIL, CHOKE 68μH		Q146	8-729-119-80	TRANSISTOR 2SC2688-LK	
L107	1-410-067-21	INDUCTOR 4.7mH		Q147	8-729-905-86	TRANSISTOR 2SC4014N	
L108	1-410-067-21	INDUCTOR 4.7mH		Q148	8-729-802-71	TRANSISTOR 2SA1401-11	

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
< RESISTOR >							R106	1-215-445-00	METAL	10K	1%	1/4W	
R1	1-216-391-11	METAL OXIDE	1.5	5%	3W	F	R107	1-215-445-00	METAL	10K	1%	1/4W	
R2	1-216-391-11	METAL OXIDE	1.5	5%	3W	F	R108	1-249-417-11	CARBON	1K	5%	1/4W	
R3	1-216-391-11	METAL OXIDE	1.5	5%	3W	F	R109	1-249-429-11	CARBON	10K	5%	1/4W	
R11	1-214-820-00	METAL	15	1%	1/2W		R110	1-249-417-11	CARBON	1K	5%	1/4W	
R12	1-214-820-00	METAL	15	1%	1/2W		R111	1-249-429-11	CARBON	10K	5%	1/4W	
R13	1-214-820-00	METAL	15	1%	1/2W		R112	1-215-429-00	METAL	2.2K	1%	1/4W	
R16	1-217-210-11	WIREWOUND	6.8	10%	2W	F	R113	1-247-807-31	CARBON	100	5%	1/4W	
R21	1-214-820-00	METAL	15	1%	1/2W		R114	1-249-417-11	CARBON	1K	5%	1/4W	
R22	1-214-820-00	METAL	15	1%	1/2W		R115	1-215-445-00	METAL	10K	1%	1/4W	
R23	1-214-820-00	METAL	15	1%	1/2W		R116	1-215-445-00	METAL	10K	1%	1/4W	
R26	1-249-441-11	CARBON	100K	5%	1/4W		R117	1-215-433-00	METAL	3.3K	1%	1/4W	
R31	1-214-820-00	METAL	15	1%	1/2W		R118	1-247-843-11	CARBON	3.3K	5%	1/4W	
R32	1-214-820-00	METAL	15	1%	1/2W		R119	1-215-457-00	METAL	33K	1%	1/4W	
R33	1-214-820-00	METAL	15	1%	1/2W		R120	1-215-457-00	METAL	33K	1%	1/4W	
R34	1-214-820-00	METAL	15	1%	1/2W		R121	1-215-445-00	METAL	10K	1%	1/4W	
R35	1-214-820-00	METAL	15	1%	1/2W		R122	1-249-425-11	CARBON	4.7K	5%	1/4W	
R36	1-214-820-00	METAL	15	1%	1/2W		R123	1-215-445-00	METAL	10K	1%	1/4W	
R37	1-214-820-00	METAL	15	1%	1/2W		R124	1-215-445-00	METAL	10K	1%	1/4W	
R38	1-214-820-00	METAL	15	1%	1/2W		R125	1-215-455-00	METAL	27K	1%	1/4W	
R39	1-214-820-00	METAL	15	1%	1/2W		R126	1-215-457-00	METAL	33K	1%	1/4W	
R40	1-214-820-00	METAL	15	1%	1/2W		R127	1-215-447-00	METAL	12K	1%	1/4W	
R41	1-214-820-00	METAL	15	1%	1/2W		R128	1-215-445-00	METAL	10K	1%	1/4W	
R42	1-214-820-00	METAL	15	1%	1/2W		R129	1-215-447-00	METAL	12K	1%	1/4W	
R43	1-215-469-00	METAL	100K	1%	1/4W		R130	1-249-425-11	CARBON	4.7K	5%	1/4W	
R44	1-215-429-00	METAL	2.2K	1%	1/4W		R131	1-215-445-00	METAL	10K	1%	1/4W	
R45	1-215-429-00	METAL	2.2K	1%	1/4W		R132	1-215-449-00	METAL	15K	1%	1/4W	
R46	1-215-429-00	METAL	2.2K	1%	1/4W		R133	1-249-425-11	CARBON	4.7K	5%	1/4W	
R47	1-215-429-00	METAL	2.2K	1%	1/4W		R134	1-215-453-00	METAL	22K	1%	1/4W	
R48	1-249-417-11	CARBON	1K	5%	1/4W		R135	1-249-429-11	CARBON	10K	5%	1/4W	
R49	1-249-417-11	CARBON	1K	5%	1/4W		R136	1-215-433-00	METAL	10K	1%	1/4W	
R50	1-249-429-11	CARBON	10K	5%	1/4W		R137	1-247-843-11	CARBON	3.3K	5%	1/4W	
R51	1-207-688-00	WIREWOUND	220	10%	5W	F	R138	1-215-433-00	METAL	3.3K	1%	1/4W	
R52	1-249-425-11	CARBON	4.7K	5%	1/4W		R139	1-249-425-11	CARBON	4.7K	5%	1/4W	
R53	1-215-905-11	METAL OXIDE	10	5%	3W	F	R140	1-249-417-11	CARBON	1K	5%	1/4W	
R54	1-260-304-51	CARBON	10	5%	1/2W		R141	1-249-421-11	CARBON	2.2K	5%	1/4W	
R57	1-247-807-31	CARBON	100	5%	1/4W		R142	1-249-421-11	CARBON	2.2K	5%	1/4W	
R58	1-247-807-31	CARBON	100	5%	1/4W		R143	1-249-420-11	CARBON	1.8K	5%	1/4W	
R59	1-247-807-31	CARBON	100	5%	1/4W		R144	1-249-421-11	CARBON	2.2K	5%	1/4W	
R60	1-247-807-31	CARBON	100	5%	1/4W		R145	1-215-433-00	METAL	3.3K	1%	1/4W	
R61	1-247-807-31	CARBON	100	5%	1/4W		R146	1-215-451-00	METAL	18K	1%	1/4W	
R62	1-247-807-31	CARBON	100	5%	1/4W		R147	1-249-421-11	CARBON	2.2K	5%	1/4W	
R63	1-260-306-51	CARBON	15	5%	1/2W		R148	1-215-467-00	METAL	82K	1%	1/4W	
R64	1-260-306-51	CARBON	15	5%	1/2W		R149	1-249-417-11	CARBON	1K	5%	1/4W	
R65	1-260-306-51	CARBON	15	5%	1/2W		R150	1-215-461-00	METAL	47K	1%	1/4W	
R66	1-216-400-11	METAL OXIDE	8.2	5%	3W	F	R151	1-215-445-00	METAL	10K	1%	1/4W	
R67	1-216-400-11	METAL OXIDE	8.2	5%	3W	F	R152	1-215-445-00	METAL	10K	1%	1/4W	
R68	1-216-400-11	METAL OXIDE	8.2	5%	3W	F	R153	1-215-433-00	METAL	3.3K	1%	1/4W	
R69	1-216-400-11	METAL OXIDE	8.2	5%	3W	F	R154	1-249-417-11	CARBON	1K	5%	1/4W	
R70	1-216-400-11	METAL OXIDE	8.2	5%	3W	F	R155	1-215-445-00	METAL	10K	1%	1/4W	
R71	1-249-417-11	CARBON	1K	5%	1/4W		R156	1-215-445-00	METAL	10K	1%	1/4W	
R72	1-216-400-11	METAL OXIDE	8.2	5%	3W	F	R157	1-215-445-00	METAL	10K	1%	1/4W	
R73	1-249-425-11	CARBON	4.7K	5%	1/4W		R158	1-215-445-00	METAL	10K	1%	1/4W	
R74	1-215-905-11	METAL OXIDE	10	5%	3W	F	R159	1-249-429-11	CARBON	10K	5%	1/4W	
R101	1-215-457-00	METAL	33K	1%	1/4W		R160	1-249-417-11	CARBON	1K	5%	1/4W	
R102	1-249-429-11	CARBON	10K	5%	1/4W		R161	1-215-469-00	METAL	100K	1%	1/4W	
R103	1-249-429-11	CARBON	10K	5%	1/4W		R162	1-249-417-11	CARBON	1K	5%	1/4W	
R104	1-249-429-11	CARBON	10K	5%	1/4W		R163	1-215-461-00	METAL	47K	1%	1/4W	
R105	1-249-429-11	CARBON	10K	5%	1/4W								

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R164	1-214-830-21	METAL	39	1%	1/2W	R244	1-247-843-11	CARBON	3.3K	5%	1/4W
R165	1-215-445-00	METAL	10K	1%	1/4W	R245	1-215-455-00	METAL	27K	1%	1/4W
R166	1-214-830-21	METAL	39	1%	1/2W	R246	1-215-435-00	METAL	3.9K	1%	1/4W
R167	1-249-437-11	CARBON	47K	5%	1/4W	R247	1-249-421-11	CARBON	2.2K	5%	1/4W
R168	1-215-912-11	METAL OXIDE	150	5%	3W	R248	1-249-425-11	CARBON	4.7K	5%	1/4W
R169	1-260-340-11	CARBON	10K	5%	1/2W	R249	1-215-421-00	METAL	1K	1%	1/4W
R170	1-249-425-11	CARBON	4.7K	5%	1/4W	R250	1-215-445-00	METAL	10K	1%	1/4W
R171	1-247-807-31	CARBON	100	5%	1/4W	R251	1-247-887-00	CARBON	220K	5%	1/4W
R172	1-247-807-31	CARBON	100	5%	1/4W	R252	1-249-429-11	CARBON	10K	5%	1/4W
R173	1-202-961-11	WIREWOUND	1.8	5%	10W	R254	1-247-807-31	CARBON	100	5%	1/4W
R174	1-260-300-11	CARBON	4.7	5%	1/2W	R255	1-249-417-11	CARBON	1K	5%	1/4W
R175	1-247-843-11	CARBON	3.3K	5%	1/4W	R256	1-249-441-11	CARBON	100K	5%	1/4W
R176	1-260-328-11	CARBON	1K	5%	1/2W	R257	1-249-437-11	CARBON	47K	5%	1/4W
R177	1-215-445-00	METAL	10K	1%	1/4W	R258	1-215-435-00	METAL	3.9K	1%	1/4W
R178	1-249-417-11	CARBON	1K	5%	1/4W	R259	1-215-439-00	METAL	5.6K	1%	1/4W
R179	1-249-429-11	CARBON	10K	5%	1/4W	R260	1-215-445-00	METAL	10K	1%	1/4W
R180	1-215-433-00	METAL	3.3K	1%	1/4W	R261	1-249-429-11	CARBON	10K	5%	1/4W
R181	1-249-441-11	CARBON	100K	5%	1/4W	R262	1-247-807-31	CARBON	100	5%	1/4W
R182	1-249-421-11	CARBON	2.2K	5%	1/4W	R263	1-215-878-00	METAL OXIDE	33K	5%	1W
R183	1-247-807-31	CARBON	100	5%	1/4W	R264	1-249-429-11	CARBON	10K	5%	1/4W
R184	1-249-425-11	CARBON	4.7K	5%	1/4W	R265	1-247-807-31	CARBON	100	5%	1/4W
R185	1-249-429-11	CARBON	10K	5%	1/4W	R266	1-249-441-11	CARBON	100K	5%	1/4W
R186	1-249-437-11	CARBON	47K	5%	1/4W	R267	1-215-379-00	METAL	18	1%	1/4W
R187	1-215-461-00	METAL	47K	1%	1/4W	R268	1-215-379-00	METAL	18	1%	1/4W
R188	1-247-863-91	CARBON	22K	5%	1/4W	R269	1-215-421-00	METAL	1K	1%	1/4W
R189	1-247-863-91	CARBON	22K	5%	1/4W	R270	1-215-415-00	METAL	560	1%	1/4W
R191	1-247-843-11	CARBON	3.3K	5%	1/4W	R271	1-215-924-00	METAL OXIDE	15K	5%	3W
R192	1-247-863-91	CARBON	22K	5%	1/4W	R272	1-260-298-51	CARBON	3.3	5%	1/2W
R193	1-247-903-00	CARBON	1M	5%	1/4W	R273	1-249-427-11	CARBON	6.8K	5%	1/4W
R194	1-247-843-11	CARBON	3.3K	5%	1/4W	R274	1-249-427-11	CARBON	6.8K	5%	1/4W
R195	1-247-843-11	CARBON	3.3K	5%	1/4W	R275	1-249-427-11	CARBON	6.8K	5%	1/4W
R196	1-247-883-00	CARBON	150K	5%	1/4W	R276	1-249-427-11	CARBON	6.8K	5%	1/4W
R197	1-247-807-31	CARBON	100	5%	1/4W	R277	1-249-427-11	CARBON	6.8K	5%	1/4W
R198	1-215-447-00	METAL	12K	1%	1/4W	R278	1-249-427-11	CARBON	6.8K	5%	1/4W
R199	1-247-843-11	CARBON	3.3K	5%	1/4W	R279	1-215-413-00	METAL	470	1%	1/4W
R200	1-249-417-11	CARBON	1K	5%	1/4W	R281	1-260-296-11	CARBON	2.2	5%	1/2W
R202	1-260-296-11	CARBON	2.2	5%	1/2W	R282	1-260-296-11	CARBON	2.2	5%	1/2W
R203	1-260-298-51	CARBON	3.3	5%	1/2W	R284	1-215-467-00	METAL	82K	1%	1/4W
R204	1-260-296-11	CARBON	2.2	5%	1/2W	R285	1-215-445-00	METAL	10K	1%	1/4W
R210	1-215-451-00	METAL	18K	1%	1/4W	R286	1-215-911-11	METAL OXIDE	100	5%	3W
R219	1-215-445-00	METAL	10K	1%	1/4W	R287	1-202-727-00	SOLID	4.7M	20%	1/2W
R220	1-215-445-00	METAL	10K	1%	1/4W	R288	1-202-727-00	SOLID	4.7M	20%	1/2W
R223	1-249-429-11	CARBON	10K	5%	1/4W	R289	1-202-727-00	SOLID	4.7M	20%	1/2W
R224	1-249-429-11	CARBON	10K	5%	1/4W	R290	1-202-727-00	SOLID	4.7M	20%	1/2W
R226	1-215-445-00	METAL	10K	1%	1/4W	R296	1-249-429-11	CARBON	10K	5%	1/4W
R230	1-260-288-11	CARBON	0.47	5%	1/2W	< VARIABLE RESISTOR >					
R231	1-260-288-11	CARBON	0.47	5%	1/2W	RV101	1-238-791-11	RES, ADJ, CERMET 200K			
R232	1-249-437-11	CARBON	47K	5%	1/4W	RV102	1-238-787-11	RES, ADJ, CERMET 10K			
R233	1-249-417-11	CARBON	1K	5%	1/4W	RV104	1-238-790-11	RES, ADJ, CERMET 100K			
R234	1-249-417-11	CARBON	1K	5%	1/4W	< RELAY >					
R235	1-249-437-11	CARBON	47K	5%	1/4W	RY1	* 1-515-868-11	RELAY			
R236	1-249-437-11	CARBON	47K	5%	1/4W	< TRANSFORMER >					
R237	1-249-441-11	CARBON	100K	5%	1/4W	T102	1-439-480-11	TRANSFORMER, HORIZONTAL OUTPUT			
R238	1-249-399-11	CARBON	33	5%	1/4W	T103	1-437-144-11	TRANSFORMER, FERRITE (HDT)			
R239	1-247-843-11	CARBON	3.3K	5%	1/4W	T104	1-437-144-11	TRANSFORMER, FERRITE (HDT)			
R240	1-249-441-11	CARBON	100K	5%	1/4W						
R241	1-249-437-11	CARBON	47K	5%	1/4W						
R242	1-215-461-00	METAL	47K	1%	1/4W						
R243	1-215-469-00	METAL	100K	1%	1/4W						

REF NO	PART NO	DESCRIPTION	REMARK				REF NO	PART NO	DESCRIPTION	REMARK			
T105	1-429-981-11	TRANSFORMER, HORIZONTAL LINEAR					R719	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
T106	1-429-981-11	TRANSFORMER, HORIZONTAL LINEAR					R720	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
< TEST PIN >													
TP1	1-537-864-11	PIN, POST					R721	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
TP2	1-537-864-11	PIN, POST					*****						
TP3	1-537-864-11	PIN, POST					* A-1343-198-A EB MOUNTED PC BOARD						
TP4	1-537-864-11	PIN, POST					*****						
TP5	1-537-864-11	PIN, POST					* A-1346-535-A EB COMPLETE PC BOARD)						
TP6	1-537-864-11	PIN, POST					(Include EBA, EBB Mounted PC BOARD)						
TP7	1-537-864-11	PIN, POST					*****						
TP8	1-537-864-11	PIN, POST					3-701-809-31	SCREW, TERMINAL (M3X8)					
TP9	1-537-864-11	PIN, POST					7-682-549-04	SCREW, TERMINAL (M3X10)					

* A-1343-259-A EA MOUNTED PC BOARD													

< CAPACITOR >													
C701	1-136-153-00	FILM	0.01MF	5%	50V								
C702	1-136-165-00	FILM	0.1MF	5%	50V								
C703	1-163-133-00	CERAMIC CHIP	470PF	5%	50V								
C704	1-163-133-00	CERAMIC CHIP	470PF	5%	50V								
C705	1-136-165-00	FILM	0.1MF	5%	50V								
C706	1-136-153-00	FILM	0.01MF	5%	50V								
C707	1-163-133-00	CERAMIC CHIP	470PF	5%	50V								
C708	1-163-133-00	CERAMIC CHIP	470PF	5%	50V								
C709	1-136-153-00	FILM	0.01MF	5%	50V								
C710	1-163-133-00	CERAMIC CHIP	470PF	5%	50V								
C711	1-163-133-00	CERAMIC CHIP	470PF	5%	50V								
< CONNECTOR >													
CN535	* 1-774-245-11	CONNECTOR, BOARD TO BOARD 8P											
CN536	* 1-774-245-11	CONNECTOR, BOARD TO BOARD 8P											
< IC >													
IC701	8-759-100-96	IC μ PC4558G2											
IC702	8-759-100-96	IC μ PC4558G2											
IC703	8-759-100-96	IC μ PC4558G2											
< RESISTOR >													
R701	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R702	1-216-049-91	METAL GLAZE	1K	5%	1/10W								
R703	1-216-049-91	METAL GLAZE	1K	5%	1/10W								
R704	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R705	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R706	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R707	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R708	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R709	1-216-049-91	METAL GLAZE	1K	5%	1/10W								
R710	1-216-049-91	METAL GLAZE	1K	5%	1/10W								
R711	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R712	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R713	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R714	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R715	1-216-675-11	METAL CHIP	10K	0.5%	1/10W								
R716	1-216-049-91	METAL GLAZE	1K	5%	1/10W								
R717	1-216-049-91	METAL GLAZE	1K	5%	1/10W								
R718	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
< CAPACITOR >													
C700	1-107-930-91	ELECT	22MF	20%	63V								
C701	1-107-923-11	ELECT	330MF	20%	63V								
C702	1-106-367-00	MYLAR	0.01MF	10%	100V								
C703	1-107-504-11	CERAMIC	10PF	0.5PF	500V								
C704	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V								
C705	1-107-930-91	ELECT	22MF	20%	63V								
C706	1-106-367-00	MYLAR	0.01MF	10%	100V								
C717	1-107-906-11	ELECT	10MF	20%	50V								
C718	1-107-909-11	ELECT	47MF	20%	50V								
C720	1-163-031-11	CERAMIC CHIP	0.01MF	50V									
C721	1-136-169-00	FILM	0.22MF	5%	50V								
C722	1-163-031-11	CERAMIC CHIP	0.01MF	50V									
C726	1-107-909-11	ELECT	47MF	20%	50V								
C801	1-107-930-91	ELECT	22MF	20%	63V								
C802	1-106-367-00	MYLAR	0.01MF	10%	100V								
C803	1-107-504-11	CERAMIC	10PF	0.5PF	500V								
C804	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V								
C805	1-107-930-91	ELECT	22MF	20%	63V								
C806	1-106-367-00	MYLAR	0.01MF	10%	100V								
C807	1-107-909-11	ELECT	47MF	20%	50V								
C808	1-163-031-11	CERAMIC CHIP	0.01MF	50V									
C809	1-136-169-00	FILM	0.22MF	5%	50V								
C810	1-107-909-11	ELECT	47MF	20%	50V								
C811	1-163-031-11	CERAMIC CHIP	0.01MF	50V									
C817	1-107-906-11	ELECT	10MF	20%	50V								
C901	1-107-930-91	ELECT	22MF	20%	63V								
C902	1-106-367-00	MYLAR	0.01MF	10%	100V								
C903	1-107-504-11	CERAMIC	10PF	0.5PF	500V								
C904	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V								
C905	1-107-930-91	ELECT	22MF	20%	63V								
C906	1-106-367-00	MYLAR	0.01MF	10%	100V								
C907	1-107-909-11	ELECT	47MF	20%	50V								
C908	1-163-031-11	CERAMIC CHIP	0.01MF	50V									
C909	1-136-169-00	FILM	0.22MF	5%	50V								
C910	1-107-909-11	ELECT	47MF	20%	50V								

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C911	1-163-031-11	CERAMIC CHIP	0.01MF 50V	Q704	8-729-207-89	TRANSISTOR 2SA1358-Y	
C917	1-107-906-11	ELECT	10MF 20% 50V	Q705	8-729-207-89	TRANSISTOR 2SA1358-Y	
C1001	1-107-914-11	ELECT	1000MF 20% 25V	Q706	8-729-207-82	TRANSISTOR 2SC3421-Y	
C1002	1-128-526-11	ELECT	100MF 20% 25V	Q707	8-729-021-75	TRANSISTOR 2SC4689-RO	
C1003	1-163-031-11	CERAMIC CHIP	0.01MF 50V	Q801	8-729-207-89	TRANSISTOR 2SA1358-Y	
C1004	1-104-653-11	ELECT	220MF 20% 16V	Q802	8-729-021-75	TRANSISTOR 2SC4689-RO	
C1006	1-128-526-11	ELECT	100MF 20% 25V	Q803	8-729-021-76	TRANSISTOR 2SA1804-RO	
C1007	1-163-031-11	CERAMIC CHIP	0.01MF 50V	Q804	8-729-207-89	TRANSISTOR 2SA1358-Y	
C1008	1-104-653-11	ELECT	220MF 20% 16V	Q805	8-729-207-89	TRANSISTOR 2SA1358-Y	
C1009	1-107-923-11	ELECT	330MF 20% 63V	Q806	8-729-207-82	TRANSISTOR 2SC3421-Y	
C1010	1-107-914-11	ELECT	1000MF 20% 25V	Q807	8-729-021-75	TRANSISTOR 2SC4689-RO	
C1011	1-108-702-11	MYLAR	0.068MF 10% 100V	Q901	8-729-207-89	TRANSISTOR 2SA1358-Y	
C1012	1-107-923-11	ELECT	330MF 20% 63V	Q902	8-729-021-75	TRANSISTOR 2SC4689-RO	
C1014	1-107-906-11	ELECT	10MF 20% 50V	Q903	8-729-021-76	TRANSISTOR 2SA1804-RO	
C1015	1-108-702-11	MYLAR	0.068MF 10% 100V	Q904	8-729-207-89	TRANSISTOR 2SA1358-Y	
C1016	1-107-914-11	ELECT	1000MF 20% 25V	Q905	8-729-207-89	TRANSISTOR 2SA1358-Y	
C1017	1-107-923-11	ELECT	330MF 20% 63V	Q906	8-729-207-82	TRANSISTOR 2SC3421-Y	
C1020	1-102-050-00	CERAMIC	0.01MF 0.99 500V	Q907	8-729-021-75	TRANSISTOR 2SC4689-RO	
C1021	1-102-050-00	CERAMIC	0.01MF 0.99 500V	Q1001	8-729-142-69	TRANSISTOR 2SK817	
< CONNECTOR >				Q1003	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
CN142	* 1-774-249-11	CONNECTOR, BOARD TO BOARD 10P		Q1004	8-729-142-68	TRANSISTOR 2SJ143	
CN143	* 1-774-249-11	CONNECTOR, BOARD TO BOARD 10P		Q1005	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
CN144	* 1-774-249-11	CONNECTOR, BOARD TO BOARD 10P		< RESISTOR >			
CN145	* 1-774-249-11	CONNECTOR, BOARD TO BOARD 10P		R701	1-249-393-11	CARBON 10 5% 1/4W	F
CN147	* 1-774-246-11	CONNECTOR, BOARD TO BOARD 10P		R702	1-216-647-11	METAL CHIP 680 0.5% 1/10W	
< DIODE >				R703	1-216-623-11	METAL CHIP 68 0.5% 1/10W	
D701	8-719-801-78	DIODE 1SS184		R704	1-215-874-11	METAL OXIDE 6.8K 5% 1W	F
D801	8-719-801-78	DIODE 1SS184		R705	1-215-875-11	METAL OXIDE 10K 5% 1W	F
D901	8-719-801-78	DIODE 1SS184		R706	1-260-304-51	CARBON 10 5% 1/2W	
D1001	8-719-801-78	DIODE 1SS184		R707	1-216-341-11	METAL OXIDE 0.22 5% 1W	F
D1002	8-719-025-11	DIODE D8LC20UR		R708	1-216-341-11	METAL OXIDE 0.22 5% 1W	F
D1003	8-719-801-78	DIODE 1SS184		R709	1-260-304-51	CARBON 10 5% 1/2W	
D1004	8-719-106-89	DIODE RD15M-T1B2		R713	1-216-033-00	METAL GLAZE 220 5% 1/10W	
D1005	8-719-025-10	DIODE D8LC20U		R714	1-216-633-11	METAL CHIP 180 0.5% 1/10W	
D1006	8-719-105-82	DIODE RD5.1M-B2		R715	1-216-391-11	METAL OXIDE 1.5 5% 3W	F
D1007	8-719-106-89	DIODE RD15M-T1B2		R716	1-249-393-11	CARBON 10 5% 1/4W	F
< IC >				R730	1-260-304-51	CARBON 10 5% 1/2W	
IC704	8-759-336-63	IC LM675T		R731	1-216-341-11	METAL OXIDE 0.22 5% 1W	F
IC801	8-759-336-63	IC LM675T		R732	1-216-391-11	METAL OXIDE 1.5 5% 3W	F
IC901	8-759-336-63	IC LM675T		R735	1-249-389-11	CARBON 4.7 5% 1/4W	F
IC1001	8-759-701-88	IC NJM7912FA		R739	1-216-675-11	METAL CHIP 10K 0.5% 1/10W	
IC1002	8-759-231-58	IC TA7812S		R740	1-249-389-11	CARBON 4.7 5% 1/4W	
< COIL >				R741	1-249-380-11	CARBON 0.82 5% 1/4W	F
L1001	1-412-533-21	INDUCTOR 47μH		R744	1-216-675-11	METAL CHIP 10K 0.5% 1/10W	
L1002	1-412-533-21	INDUCTOR 47μH		R746	1-216-651-11	METAL CHIP 1K 0.5% 1/10W	
L1003	1-412-533-21	INDUCTOR 47μH		R747	1-216-651-11	METAL CHIP 1K 0.5% 1/10W	
L1004	1-410-645-31	INDUCTOR 100μH		R748	1-216-379-11	METAL OXIDE 6.8 5% 2W	F
L1005	1-412-533-21	INDUCTOR 47μH		R749	1-249-389-11	CARBON 4.7 5% 1/4W	F
L1006	1-410-645-31	INDUCTOR 100μH		R801	1-249-393-11	CARBON 10 5% 1/4W	F
L1007	1-406-975-21	COIL, CHOKE 47μH		R802	1-216-647-11	METAL CHIP 680 0.5% 1/10W	
L1008	1-406-975-21	COIL, CHOKE 47μH		R803	1-216-623-11	METAL CHIP 68 0.5% 1/10W	
< TRANSISTOR >				R804	1-215-874-11	METAL OXIDE 6.8K 5% 1W	F
Q701	8-729-207-89	TRANSISTOR 2SA1358-Y		R805	1-215-875-11	METAL OXIDE 10K 5% 1W	F
Q702	8-729-021-75	TRANSISTOR 2SC4689-RO		R806	1-260-304-51	CARBON 10 5% 1/2W	
Q703	8-729-021-76	TRANSISTOR 2SA1804-RO		R807	1-216-341-11	METAL OXIDE 0.22 5% 1W	F
				R808	1-216-341-11	METAL OXIDE 0.22 5% 1W	F
				R809	1-260-304-51	CARBON 10 5% 1/2W	
				R813	1-216-033-00	METAL GLAZE 220 5% 1/10W	

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
R814	1-216-633-11	METAL CHIP	180	0.5%	1/10W		C303	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R815	1-216-391-11	METAL OXIDE	1.5	5%	3W	F	C305	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R816	1-249-393-11	CARBON	10	5%	1/4W	F	C307	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	
R817	1-249-389-11	CARBON	4.7	5%	1/4W	F	C308	1-136-169-00	FILM	0.22MF	5%	50V	
R818	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		C309	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R819	1-216-651-11	METAL CHIP	1K	0.5%	1/10W		< CONNECTOR >						
R820	1-249-380-11	CARBON	0.82	5%	1/4W	F	CN147	* 1-774-246-11	CONNECTOR, BOARD TO BOARD 10P				
R821	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		< IC >						
R822	1-249-389-11	CARBON	4.7	5%	1/4W		IC301	8-759-100-96	IC μPC4558G2				
R824	1-216-651-11	METAL CHIP	1K	0.5%	1/10W		IC302	8-759-381-53	IC μPC814G2-E2				
R825	1-216-379-11	METAL OXIDE	6.8	5%	2W	F	< RESISTOR >						
R826	1-249-389-11	CARBON	4.7	5%	1/4W	F	R301	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W	
R830	1-260-304-51	CARBON	10	5%	1/2W		R302	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	
R831	1-216-341-11	METAL OXIDE	0.22	5%	1W	F	R303	1-216-677-11	METAL CHIP	12K	0.5%	1/10W	
R832	1-216-391-11	METAL OXIDE	1.5	5%	3W	F	R304	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	
R901	1-249-393-11	CARBON	10	5%	1/4W	F	R305	1-216-627-11	METAL CHIP	100	0.5%	1/10W	
R902	1-216-647-11	METAL CHIP	680	0.5%	1/10W		R306	1-216-668-11	METAL CHIP	5.1K	0.5%	1/10W	
R903	1-216-623-11	METAL CHIP	68	0.5%	1/10W		R307	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W	
R904	1-215-874-11	METAL OXIDE	6.8K	5%	1W	F	R309	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
R905	1-215-875-11	METAL OXIDE	10K	5%	1W	F	R310	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
R906	1-260-304-51	CARBON	10	5%	1/2W		R312	1-216-025-91	METAL GLAZE	100	5%	1/10W	
R907	1-216-341-11	METAL OXIDE	0.22	5%	1W	F	R313	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
R908	1-216-341-11	METAL OXIDE	0.22	5%	1W	F	R314	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W	
R909	1-260-304-51	CARBON	10	5%	1/2W		R315	1-216-675-11	METAL CHIP	10K	0.5%	1/10W	
R913	1-216-033-00	METAL GLAZE	220	5%	1/10W		R316	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W	
R914	1-216-633-11	METAL CHIP	180	0.5%	1/10W		R317	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
R915	1-216-391-11	METAL OXIDE	1.5	5%	3W	F	R318	1-216-677-11	METAL CHIP	1.2K	0.5%	1/10W	
R917	1-249-393-11	CARBON	10	5%	1/4W	F	R319	1-216-645-11	METAL CHIP	560	0.5%	1/10W	
R918	1-249-389-11	CARBON	4.7	5%	1/4W	F	*****						
R919	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		* A-1343-197-A 1-BB MOUNTED PC BOARD						
R920	1-216-651-11	METAL CHIP	1K	0.5%	1/10W		*****						
R921	1-249-380-11	CARBON	0.82	5%	1/4W	F	< CAPACITOR >						
R922	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		C401	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R923	1-249-389-11	CARBON	4.7	5%	1/4W		C402	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R925	1-216-651-11	METAL CHIP	1K	0.5%	1/10W		C403	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R926	1-216-379-11	METAL OXIDE	6.8	5%	2W	F	C404	1-163-131-00	CERAMIC CHIP	390PF	5%	50V	
R927	1-249-389-11	CARBON	4.7	5%	1/4W	F	C406	1-136-169-00	FILM	0.22MF	5%	50V	
R930	1-260-304-51	CARBON	10	5%	1/2W		C407	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R931	1-216-341-11	METAL OXIDE	0.22	5%	1W	F	C408	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R932	1-216-391-11	METAL OXIDE	1.5	5%	3W	F	C409	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R1001	1-216-073-00	METAL GLAZE	10K	5%	1/10W		C411	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R1002	1-216-005-00	METAL GLAZE	15	5%	1/10W		< CONNECTOR >						
R1003	1-216-089-91	METAL GLAZE	47K	5%	1/10W		CN146	* 1-774-246-11	CONNECTOR, BOARD TO BOARD 10P				
R1004	1-216-049-91	METAL GLAZE	1K	5%	1/10W		< DIODE >						
R1005	1-216-089-91	METAL GLAZE	47K	5%	1/10W		D401	8-719-801-78	DIODE 1SS184				
R1006	1-216-073-00	METAL GLAZE	10K	5%	1/10W		D402	8-719-801-78	DIODE 1SS184				
R1007	1-216-091-00	METAL GLAZE	56K	5%	1/10W		D403	8-719-801-78	DIODE 1SS184				
R1008	1-216-089-91	METAL GLAZE	47K	5%	1/10W		< IC >						
R1009	1-216-005-00	METAL GLAZE	15	5%	1/10W		IC401	8-759-105-49	IC μPC319G2				

* A-1343-196-A EBA MOUNTED PC BOARD													

< CAPACITOR >													
C301	1-163-031-11	CERAMIC CHIP	0.01MF		50V		IC402	8-759-105-49	IC μPC319G2				
C302	1-136-169-00	FILM	0.22MF	5%	50V								

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
< TRANSISTOR >				< CAPACITOR >			
Q401	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		C1	1-107-910-11	ELECT 100MF 20% 50V	
Q402	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		C2	1-107-906-11	ELECT 10MF 20% 50V	
Q403	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		C3	1-107-910-11	ELECT 100MF 20% 50V	
Q404	8-729-216-22	TRANSISTOR 2SA1162-G		C4	1-107-906-11	ELECT 10MF 20% 50V	
Q405	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		C6	1-107-906-11	ELECT 10MF 20% 50V	
Q406	8-729-033-10	TRANSISTOR 2SC3776-CD-AA		C7	1-128-526-11	ELECT 100MF 20% 16V	
Q407	8-729-216-22	TRANSISTOR 2SA1162-G		C101	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	
< RESISTOR >				C104	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V	
R401	1-216-089-91	METAL GLAZE 47K 5% 1/10W		C105	1-107-504-11	CERAMIC 10PF 0.5PF 500V	
R402	1-216-041-00	METAL GLAZE 470 5% 1/10W		C106	1-107-930-91	ELECT 22MF 20% 63V	
R403	1-216-077-00	METAL GLAZE 15K 5% 1/10W		C107	1-107-930-91	ELECT 22MF 20% 63V	
R404	1-216-041-00	METAL GLAZE 470 5% 1/10W		C111	1-107-889-11	ELECT 220MF 20% 25V	
R405	1-216-073-00	METAL GLAZE 10K 5% 1/10W		C112	1-163-038-91	CERAMIC CHIP 0.1MF 25V	
R406	1-216-001-00	METAL GLAZE 10 5% 1/10W		C113	1-107-889-11	ELECT 220MF 20% 25V	
R407	1-216-049-91	METAL GLAZE 1K 5% 1/10W		C114	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
R408	1-216-691-11	METAL CHIP 47K 0.5% 1/10W		C115	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
R409	1-216-691-11	METAL CHIP 47K 0.5% 1/10W		C201	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	
R410	1-216-017-91	METAL GLAZE 47 5% 1/10W		C204	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V	
R411	1-216-017-91	METAL GLAZE 47 5% 1/10W		C205	1-107-504-11	CERAMIC 10PF 0.5PF 500V	
R412	1-216-017-91	METAL GLAZE 47 5% 1/10W		C206	1-107-930-91	ELECT 22MF 20% 63V	
R413	1-216-073-00	METAL GLAZE 10K 5% 1/10W		C207	1-107-930-91	ELECT 22MF 20% 63V	
R414	1-216-049-91	METAL GLAZE 1K 5% 1/10W		C211	1-107-889-11	ELECT 220MF 20% 25V	
R415	1-216-691-11	METAL CHIP 47K 0.5% 1/10W		C212	1-163-038-91	CERAMIC CHIP 0.1MF 25V	
R416	1-216-001-00	METAL GLAZE 10 5% 1/10W		C213	1-107-889-11	ELECT 220MF 20% 25V	
R417	1-216-001-00	METAL GLAZE 10 5% 1/10W		C214	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
R418	1-216-089-91	METAL GLAZE 47K 5% 1/10W		C215	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
R419	1-216-041-00	METAL GLAZE 470 5% 1/10W		C301	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	
R420	1-216-043-91	METAL GLAZE 560 5% 1/10W		C304	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V	
R421	1-216-077-00	METAL GLAZE 15K 5% 1/10W		C305	1-107-504-11	CERAMIC 10PF 0.5PF 500V	
R422	1-216-041-00	METAL GLAZE 470 5% 1/10W		C306	1-107-930-91	ELECT 22MF 20% 63V	
R423	1-216-073-00	METAL GLAZE 10K 5% 1/10W		C307	1-107-930-91	ELECT 22MF 20% 63V	
R424	1-216-017-91	METAL GLAZE 47 5% 1/10W		C311	1-107-889-11	ELECT 220MF 20% 25V	
R425	1-216-089-91	METAL GLAZE 47K 5% 1/10W		C312	1-163-038-91	CERAMIC CHIP 0.1MF 25V	
R426	1-216-041-00	METAL GLAZE 470 5% 1/10W		C313	1-107-889-11	ELECT 220MF 20% 25V	
R427	1-216-017-91	METAL GLAZE 47 5% 1/10W		C314	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
R428	1-216-041-00	METAL GLAZE 470 5% 1/10W		C315	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
R429	1-216-047-91	METAL GLAZE 820 5% 1/10W		C401	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	
R430	1-216-073-00	METAL GLAZE 10K 5% 1/10W		C404	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V	
R431	1-216-077-00	METAL GLAZE 15K 5% 1/10W		C405	1-107-504-11	CERAMIC 10PF 0.5PF 500V	
R432	1-216-017-91	METAL GLAZE 47 5% 1/10W		C406	1-107-930-91	ELECT 22MF 20% 63V	
R433	1-216-017-91	METAL GLAZE 47 5% 1/10W		C407	1-107-930-91	ELECT 22MF 20% 63V	
R434	1-216-001-00	METAL GLAZE 10 5% 1/10W		C411	1-107-889-11	ELECT 220MF 20% 25V	
*****				C412	1-163-038-91	CERAMIC CHIP 0.1MF 25V	
* A-1346-536-A EC COMPLETE PC BOARD				C413	1-107-889-11	ELECT 220MF 20% 25V	
(Include ECA Mounted PC BOARD)				C414	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
*****				C415	1-163-031-11	CERAMIC CHIP 0.01MF 50V	
3-701-809-31	SCREW, TERMINAL (M3X8)			C430	1-107-914-11	ELECT 1000MF 20% 25V	
* 4-056-076-01	PIN, GUIDE			C431	1-136-165-00	FILM 0.1MF 5% 50V	
4-056-086-01	HOLDER (EC), TR			C432	1-107-905-11	ELECT 4.7MF 20% 50V	
* 4-056-087-01	HEAT SINK (EC)			C433	1-136-165-00	FILM 0.1MF 5% 50V	
* 4-056-088-01	SHEET (EC), INSULATING			C434	1-107-906-11	ELECT 10MF 20% 50V	
* 4-378-611-51	HEAT SINK (E)(Q430)			C435	1-136-165-00	FILM 0.1MF 5% 50V	
* 7-322-065-72	RUBBER, RTV (SE-9168) (130G)			C436	1-107-909-11	ELECT 47MF 20% 50V	
7-682-949-01	SCREW +PSW 3X10 (Q430)			C437	1-107-909-11	ELECT 47MF 20% 50V	
				C438	1-104-664-11	ELECT 47MF 20% 25V	
				C501	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	
				C504	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C505	1-107-904-11	CERAMIC	10PF 0.5PF 500V	Q102	8-729-207-89	TRANSISTOR 2SA1358-Y	
C506	1-107-930-91	ELECT	22MF 20% 63V	Q103	8-729-207-89	TRANSISTOR 2SA1358-Y	
C507	1-107-930-91	ELECT	22MF 20% 63V	Q104	8-729-207-82	TRANSISTOR 2SC3421-Y	
C511	1-107-889-11	ELECT	220MF 20% 25V	Q105	8-729-033-01	TRANSISTOR 2SD1459	
C512	1-163-038-91	CERAMIC CHIP	0.1MF 25V	Q106	8-729-805-98	TRANSISTOR 2SB1037-Q	
C513	1-107-889-11	ELECT	220MF 20% 25V	Q107	8-729-027-59	TRANSISTOR DTC144EKA-T146	
C514	1-163-031-11	CERAMIC CHIP	0.01MF 50V	Q201	8-729-207-89	TRANSISTOR 2SA1358-Y	
C515	1-163-031-11	CERAMIC CHIP	0.01MF 50V	Q202	8-729-207-89	TRANSISTOR 2SA1358-Y	
C601	1-163-017-00	CERAMIC CHIP	0.0047MF 10% 50V	Q203	8-729-207-89	TRANSISTOR 2SA1358-Y	
C604	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V	Q204	8-729-207-82	TRANSISTOR 2SC3421-Y	
C605	1-107-504-11	CERAMIC	10PF 0.5PF 500V	Q205	8-729-033-01	TRANSISTOR 2SD1459	
C606	1-107-930-91	ELECT	22MF 20% 63V	Q206	8-729-805-98	TRANSISTOR 2SB1037-Q	
C607	1-107-930-91	ELECT	22MF 20% 63V	Q207	8-729-027-59	TRANSISTOR DTC144EKA-T146	
C611	1-107-889-11	ELECT	220MF 20% 25V	Q301	8-729-207-89	TRANSISTOR 2SA1358-Y	
C612	1-163-038-91	CERAMIC CHIP	0.1MF 25V	Q302	8-729-207-89	TRANSISTOR 2SA1358-Y	
C613	1-107-889-11	ELECT	220MF 20% 25V	Q303	8-729-207-89	TRANSISTOR 2SA1358-Y	
C614	1-163-031-11	CERAMIC CHIP	0.01MF 50V	Q304	8-729-207-82	TRANSISTOR 2SC3421-Y	
C615	1-163-031-11	CERAMIC CHIP	0.01MF 50V	Q305	8-729-033-01	TRANSISTOR 2SD1459	
< CONNECTOR >				Q306	8-729-805-98	TRANSISTOR 2SB1037-Q	
CN132	* 1-774-249-11	CONNECTOR, BOARD TO BOARD 10P		Q307	8-729-027-59	TRANSISTOR DTC144EKA-T146	
CN133	* 1-774-249-11	CONNECTOR, BOARD TO BOARD 10P		Q401	8-729-207-89	TRANSISTOR 2SA1358-Y	
CN134	* 1-774-249-11	CONNECTOR, BOARD TO BOARD 10P		Q402	8-729-207-89	TRANSISTOR 2SA1358-Y	
< DIODE >				Q403	8-729-207-89	TRANSISTOR 2SA1358-Y	
D1	8-719-801-78	DIODE 1SS184		Q404	8-729-207-82	TRANSISTOR 2SC3421-Y	
D2	8-719-801-78	DIODE 1SS184		Q405	8-729-033-01	TRANSISTOR 2SD1459	
D3	8-719-105-82	DIODE RD5.1M-B2		Q406	8-729-805-98	TRANSISTOR 2SB1037-Q	
D102	8-719-801-78	DIODE 1SS184		Q407	8-729-027-59	TRANSISTOR DTC144EKA-T146	
D202	8-719-801-78	DIODE 1SS184		Q430	8-729-033-97	TRANSISTOR 2SB1566E	
D302	8-719-801-78	DIODE 1SS184		Q431	8-729-140-96	TRANSISTOR 2SD774-34	
D402	8-719-801-78	DIODE 1SS184		Q432	8-729-027-59	TRANSISTOR DTC144EKA-T146	
D430	8-719-801-78	DIODE 1SS184		Q501	8-729-207-89	TRANSISTOR 2SA1358-Y	
D431	8-719-801-78	DIODE 1SS184		Q502	8-729-207-89	TRANSISTOR 2SA1358-Y	
D432	8-719-801-78	DIODE 1SS184		Q503	8-729-207-89	TRANSISTOR 2SA1358-Y	
D502	8-719-801-78	DIODE 1SS184		Q504	8-729-207-82	TRANSISTOR 2SC3421-Y	
D602	8-719-801-78	DIODE 1SS184		Q505	8-729-033-01	TRANSISTOR 2SD1459	
< IC >				Q506	8-729-805-98	TRANSISTOR 2SB1037-Q	
IC1	8-759-231-58	IC TA7812S		Q507	8-729-027-59	TRANSISTOR DTC144EKA-T146	
IC2	8-759-701-88	IC NJM7912FA		Q601	8-729-207-89	TRANSISTOR 2SA1358-Y	
IC430	8-759-100-96	IC μ PC4558G2		Q602	8-729-207-89	TRANSISTOR 2SA1358-Y	
IC431	8-759-100-96	IC μ PC4558G2		Q603	8-729-207-89	TRANSISTOR 2SA1358-Y	
IC432	8-759-908-15	IC TL431CLP		Q604	8-729-207-82	TRANSISTOR 2SC3421-Y	
IC433	8-759-947-34	IC LM35DZ		Q605	8-729-033-01	TRANSISTOR 2SD1459	
< COIL >				Q606	8-729-805-98	TRANSISTOR 2SB1037-Q	
L1	1-406-663-21	COIL, CHOKER	47 μ H	Q607	8-729-027-59	TRANSISTOR DTC144EKA-T146	
L2	1-406-663-21	COIL, CHOKER	47 μ H	< RESISTOR >			
L3	1-412-533-21	INDUCTOR	47 μ H	R1	1-216-089-91	METAL GLAZE	47K 5% 1/10W
L4	1-412-533-21	INDUCTOR	47 μ H	R2	1-216-049-91	METAL GLAZE	1K 5% 1/10W
L430	1-406-657-11	COIL, CHOKER	47 μ H	R3	1-216-089-91	METAL GLAZE	47K 5% 1/10W
< TRANSISTOR >				R4	1-216-091-00	METAL GLAZE	56K 5% 1/10W
Q1	8-729-230-49	TRANSISTOR 2SC2712-YG-TE851		R5	1-216-089-91	METAL GLAZE	47K 5% 1/10W
Q3	8-729-230-49	TRANSISTOR 2SC2712-YG-TE851		R6	1-216-073-00	METAL GLAZE	10K 5% 1/10W
Q4	8-729-027-38	TRANSISTOR DTA144EKA-T146		R7	1-216-089-91	METAL GLAZE	47K 5% 1/10W
Q5	8-729-230-49	TRANSISTOR 2SC2712-YG-TE851		R8	1-216-089-91	METAL GLAZE	47K 5% 1/10W
Q101	8-729-207-89	TRANSISTOR 2SA1358-Y		R101	1-216-625-11	METAL CHIP	82 0.5% 1/10W
				R109	1-216-037-00	METAL GLAZE	330 5% 1/10W
				R110	1-216-437-00	METAL OXIDE	5.6K 5% 1W
				R111	1-216-633-11	METAL CHIP	180 0.5% 1/10W
				R112	1-216-061-00	METAL GLAZE	3.3K 5% 1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
R113	1-216-089-91	METAL GLAZE	47K	5%	1/10W		R439	1-216-049-91	METAL GLAZE	1K	5%	1/10W	
R114	1-216-643-11	METAL CHIP	470	0.5%	1/10W		R440	1-216-687-11	METAL CHIP	33K	0.5%	1/10W	
							R441	1-216-697-91	METAL CHIP	82K	0.5%	1/10W	
R115	1-260-304-51	CARBON	10	5%	1/2W		R442	1-216-025-91	METAL GLAZE	100	5%	1/10W	
R116	1-260-304-51	CARBON	10	5%	1/2W								
R117	1-249-397-11	CARBON	22	5%	1/4W	F	R443	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	
R118	1-249-397-11	CARBON	22	5%	1/4W	F	R444	1-216-361-00	METAL OXIDE	0.22	5%	2W	F
R119	1-249-389-11	CARBON	4.7	5%	1/4W	F	R445	1-215-867-00	METAL OXIDE	470	5%	1W	F
							R446	1-249-417-11	CARBON	1K	5%	1/4W	
R120	1-249-389-11	CARBON	4.7	5%	1/4W	F	R501	1-216-625-11	METAL CHIP	82	0.5%	1/10W	
R123	1-216-378-11	METAL OXIDE	5.6	5%	2W	F							
R201	1-216-625-11	METAL CHIP	82	0.5%	1/10W		R509	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R209	1-216-037-00	METAL GLAZE	330	5%	1/10W		R510	1-216-437-00	METAL OXIDE	5.6K	5%	1W	F
R210	1-216-437-00	METAL OXIDE	5.6K	5%	1W	F	R511	1-216-633-11	METAL CHIP	180	0.5%	1/10W	
							R512	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
R211	1-216-633-11	METAL CHIP	180	0.5%	1/10W		R513	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R212	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W								
R213	1-216-089-91	METAL GLAZE	47K	5%	1/10W		R514	1-216-643-11	METAL CHIP	470	0.5%	1/10W	
R214	1-216-643-11	METAL CHIP	470	0.5%	1/10W		R515	1-260-304-51	CARBON	10	5%	1/2W	
R215	1-260-304-51	CARBON	10	5%	1/2W		R516	1-260-304-51	CARBON	10	5%	1/2W	
							R517	1-249-397-11	CARBON	22	5%	1/4W	F
R216	1-260-304-51	CARBON	10	5%	1/2W		R518	1-249-397-11	CARBON	22	5%	1/4W	F
R217	1-249-397-11	CARBON	22	5%	1/4W	F							
R218	1-249-397-11	CARBON	22	5%	1/4W	F	R519	1-249-389-11	CARBON	4.7	5%	1/4W	F
R219	1-249-389-11	CARBON	4.7	5%	1/4W	F	R520	1-249-389-11	CARBON	4.7	5%	1/4W	F
R220	1-249-389-11	CARBON	4.7	5%	1/4W	F	R523	1-216-378-11	METAL OXIDE	5.6	5%	2W	F
							R601	1-216-625-11	METAL CHIP	82	0.5%	1/10W	
R223	1-216-378-11	METAL OXIDE	5.6	5%	2W	F	R609	1-216-037-00	METAL GLAZE	330	5%	1/10W	
R301	1-216-625-11	METAL CHIP	82	0.5%	1/10W								
R309	1-216-037-00	METAL GLAZE	330	5%	1/10W		R610	1-216-437-00	METAL OXIDE	5.6K	5%	1W	F
R310	1-216-437-00	METAL OXIDE	5.6K	5%	1W	F	R611	1-216-633-11	METAL CHIP	180	0.5%	1/10W	
R311	1-216-633-11	METAL CHIP	180	0.5%	1/10W		R612	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W	
							R613	1-216-089-91	METAL GLAZE	47K	5%	1/10W	
R312	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W		R614	1-216-643-11	METAL CHIP	470	0.5%	1/10W	
R313	1-216-089-91	METAL GLAZE	47K	5%	1/10W								
R314	1-216-643-11	METAL CHIP	470	0.5%	1/10W		R615	1-260-304-51	CARBON	10	5%	1/2W	
R315	1-260-304-51	CARBON	10	5%	1/2W		R616	1-260-304-51	CARBON	10	5%	1/2W	
R316	1-260-304-51	CARBON	10	5%	1/2W		R617	1-249-397-11	CARBON	22	5%	1/4W	F
							R618	1-249-397-11	CARBON	22	5%	1/4W	F
R317	1-249-397-11	CARBON	22	5%	1/4W	F	R619	1-249-389-11	CARBON	4.7	5%	1/4W	F
R318	1-249-397-11	CARBON	22	5%	1/4W	F							
R319	1-249-389-11	CARBON	4.7	5%	1/4W	F	R620	1-249-389-11	CARBON	4.7	5%	1/4W	F
R320	1-249-389-11	CARBON	4.7	5%	1/4W	F	R623	1-216-378-11	METAL OXIDE	5.6	5%	2W	F
R323	1-216-378-11	METAL OXIDE	5.6	5%	2W	F							
							< VARIABLE RESISTOR >						
R401	1-216-625-11	METAL CHIP	82	0.5%	1/10W		RV430	1-238-801-11	RES, ADJ, CERMET 5K				
R409	1-216-037-00	METAL GLAZE	330	5%	1/10W								
R410	1-216-437-00	METAL OXIDE	5.6K	5%	1W	F							
R411	1-216-633-11	METAL CHIP	180	0.5%	1/10W								
R412	1-216-061-00	METAL GLAZE	3.3K	5%	1/10W								
							< TEST PIN >						
R413	1-216-089-91	METAL GLAZE	47K	5%	1/10W		TP430	1-537-864-11	PIN, POST				
R414	1-216-643-11	METAL CHIP	470	0.5%	1/10W		TP431	1-537-864-11	PIN, POST				
R415	1-260-304-51	CARBON	10	5%	1/2W								
R416	1-260-304-51	CARBON	10	5%	1/2W		*****						
R417	1-249-397-11	CARBON	22	5%	1/4W	F							
							* A 1343 199 A ECA MOUNTED PC BOARD						
R418	1-249-397-11	CARBON	22	5%	1/4W	F							
R419	1-249-389-11	CARBON	4.7	5%	1/4W	F							
R420	1-249-389-11	CARBON	4.7	5%	1/4W	F							
R423	1-216-378-11	METAL OXIDE	5.6	5%	2W	F							
R430	1-216-677-11	METAL CHIP	12K	0.5%	1/10W								
							< CAPACITOR >						
R432	1-216-675-11	METAL CHIP	10K	0.5%	1/10W		C101	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R433	1-216-073-00	METAL GLAZE	10K	5%	1/10W		C102	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R434	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W		C103	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R435	1-216-049-91	METAL GLAZE	1K	5%	1/10W		C201	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R436	1-216-683-11	METAL CHIP	22K	0.5%	1/10W		C202	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
							C203	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
R438	1-216-073-00	METAL GLAZE	10K	5%	1/10W								

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
< CONNECTOR >				< RESISTOR >			
CN135	* 1 / / 4 246-11	CONNECTOR, BOARD TO BOARD 10P		R151	Δ 1-202-847-00	SOLID 560K 20% 1/2W	
< IC >				R152	Δ 9-910-999-31	FUSIBLE 1 5% 5W	F
IC'101	8-759-381-53	IC μPC814G2-E2		R153	Δ 9-910-999-31	FUSIBLE 1 5% 5W	F
IC'201	8-759-381-53	IC μPC814G2-E2		R154	Δ 9-910-999-31	FUSIBLE 1 5% 5W	F
< RESISTOR >				R155	Δ 9-910-999-31	FUSIBLE 1 5% 5W	F
R101	1-216-665-11	METAL CHIP 3.9K 0.5% 1/10W		R156	Δ 9-910-999-31	FUSIBLE 1 5% 5W	F
R102	1-216-665-11	METAL CHIP 3.9K 0.5% 1/10W		R157	Δ 1-202-847-00	SOLID 560K 20% 1/2W	
R103	1-216-653-11	METAL CHIP 1.2K 0.5% 1/10W		R201	Δ 1-215-885-00	METAL OXIDE 68 5% 2W	F
R104	1-216-675-11	METAL CHIP 10K 0.5% 1/10W		< RELAY >			
R105	1-216-681-11	METAL CHIP 18K 0.5% 1/10W		RY151	Δ 1-515-450-21	RELAY, POWER	
< VARISTOR >				< VARISTOR >			
R106	1-216-675-11	METAL CHIP 10K 0.5% 1/10W		VDR151	Δ 1-809-581-11	VARISTOR	
R107	1-216-663-11	METAL CHIP 3.3K 0.5% 1/10W		VDR152	Δ 1-809-581-11	VARISTOR	
R108	1-216-073-00	METAL GLAZE 10K 5% 1/10W		*****			
R109	1-216-025-91	METAL GLAZE 100 5% 1/10W		Δ * A-1245-590-A FA COMPLETE PC BOARD			
R201	1-216-665-11	METAL CHIP 3.9K 0.5% 1/10W		(Include FAA, FAB Mounted PC BOARD)			
R202	1-216-665-11	METAL CHIP 3.9K 0.5% 1/10W		*****			
R203	1-216-653-11	METAL CHIP 1.2K 0.5% 1/10W		4-034-094-01	SHEET, INSULATOR		
R204	1-216-675-11	METAL CHIP 10K 0.5% 1/10W		* 4-054-527-11	HEAT SINK (GA)		
R205	1-216-681-11	METAL CHIP 18K 0.5% 1/10W		4-056-103-01	SUPPORT, FA		
R206	1-216-675-11	METAL CHIP 10K 0.5% 1/10W		* 4-374-846-01	COVER, CAPACITOR, CAPTYPE (IC'160)		
R207	1-216-663-11	METAL CHIP 3.3K 0.5% 1/10W		4-382-854-11	SCREW (M3X10), P, SW (+)		
R208	1-216-073-00	METAL GLAZE 10K 5% 1/10W		4-382-854-11	SCREW (M3X10), P, SW (+)		
R209	1-216-025-91	METAL GLAZE 100 5% 1/10W		< CAPACITOR >			
*****				C112	Δ 1-104-665-11	ELECT 100MF 20% 25V	
Δ * A-1245-594-A F COMPLETE PC BOARD				C114	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
*****				C151	Δ 1-117-228-11	FILM 2.2MF 10% 450V	
* 7-322-065-72	RUBBER, RTV (SE-9168) (130G)			C152	Δ 1-117-228-11	FILM 2.2MF 10% 450V	
< CAPACITOR >				C153	Δ 1-117-228-11	FILM 2.2MF 10% 450V	
C154	Δ 1-113-920-11	CERAMIC 0.0022MF 20% 250V		C154	Δ 1-109-987-11	ELECT 270MF 20% 450V	
C155	Δ 1-113-920-11	CERAMIC 0.0022MF 20% 250V		C156	Δ 1-117-228-11	FILM 2.2MF 10% 450V	
C156	Δ 1-113-920-11	CERAMIC 0.0022MF 20% 250V		C157	Δ 1-104-665-11	ELECT 100MF 20% 25V	
C157	Δ 1-113-920-11	CERAMIC 0.0022MF 20% 250V		C158	Δ 1-126-960-11	ELECT 1MF 20% 50V	
C158	Δ 1-113-920-11	CERAMIC 0.0022MF 20% 250V		C159	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
C159	Δ 1-113-920-11	CERAMIC 0.0022MF 20% 250V		C160	Δ 1-113-912-11	CERAMIC 0.0047MF 20% 250V	
C160	Δ 1-107-533-11	FILM 1MF 20% 250V		< CONNECTOR >			
C161	Δ 1-137-110-11	FILM 0.47MF 20% 250V		CN172	Δ * 1-569-967-11	SOCKET, CONNECTOR 11P	
C162	Δ 1-137-110-11	FILM 0.47MF 20% 250V		CN174	Δ 1-778-896-11	SOCKET, CONNECTOR (PLUG)	
< CONNECTOR >				CN175	Δ 1-778-896-11	SOCKET, CONNECTOR (PLUG)	
CN102	Δ * 1-535-419-00	TAB, FASTEN (PCB)		< DIODE >			
CN103	Δ * 1-535-419-00	TAB, FASTEN (PCB)		D151	Δ 8-719-060-53	DIODE RBV-2506	
< DIODE >				D152	Δ 8-719-044-70	DIODE S16L60	
D201	Δ 8-719-921-20	DIODE 1SS119-25TD		D153	Δ 8-719-510-18	DIODE D1NS4-TA	
< COIL >				D154	Δ 8-719-510-18	DIODE D1NS4-TA	
L151	Δ 1-429-983-11	TRANSFORMER, LINE FILTER		D155	Δ 8-719-510-18	DIODE D1NS4-TA	
L152	Δ 1-429-984-11	TRANSFORMER, LINE FILTER		D156	Δ 8-719-112-64	DIODE RD10ESB2	
L153	Δ 1-415-985-11	COIL, CHOKE 90μH		D157	Δ 8-719-030-48	DIODE 1JH46-TPA3	
L154	Δ 1-415-985-11	COIL, CHOKE 90μH		D158	Δ 8-719-030-48	DIODE 1JH46-TPA3	
< COIL >				D159	Δ 8-719-921-20	DIODE 1SS119-25TD	
< COIL >				D160	Δ 8-719-921-20	DIODE 1SS119-25TD	

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

FA

FAA

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
< FERRITE BEAD >				R185	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W	
FB101	Δ 1-410-396-41	FERRITE BEAD INDUCTOR 0.45 μ H		R186	Δ 1-249-429-11	CARBON 10K 5% 1/4W	
FB102	Δ 1-410-396-41	FERRITE BEAD INDUCTOR 0.45 μ H		R187	Δ 1-249-425-11	CARBON 4.7K 5% 1/4W	
FB103	Δ 1-410-396-41	FERRITE BEAD INDUCTOR 0.45 μ H		R188	Δ 1-249-425-11	CARBON 4.7K 5% 1/4W	
				R189	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
< IC >				< THERMAL SWITCH >			
IC151	Δ 8-759-198-31	IC μ PC1093J-1-T		TS151	Δ 1-692-110-11	SWITCH, THERMAL GUARD	
< COIL >				*****			
L151	Δ 1-415-986-11	COIL CHOKE 420 μ H		Δ * A-1241-264-A FAA MOUNTED PC BOARD			
< TRANSISTOR >				*****			
Q151	Δ 8-729-041-01	TRANSISTOR 2SK2198		< CAPACITOR >			
Q152	Δ 8-729-041-01	TRANSISTOR 2SK2198		C1501	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
Q153	Δ 8-729-041-01	TRANSISTOR 2SK2198		C1502	Δ 1-136-173-00	FILM 0.47MF 5% 50V	
Q155	Δ 8-729-188-22	TRANSISTOR 2SD882-Q		C1503	Δ 1-136-169-00	FILM 0.22MF 5% 50V	
Q156	Δ 8-729-177-22	TRANSISTOR 2SB772-Q		C1504	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
Q157	Δ 8-729-140-99	TRANSISTOR 2SB734-34		C1505	Δ 1-102-030-00	CERAMIC 330PP 10% 500V	
Q158	Δ 8-729-188-22	TRANSISTOR 2SD882-Q		C1506	Δ 1-130-471-00	FILM 0.001MF 5% 50V	
Q159	Δ 8-729-177-22	TRANSISTOR 2SB772-Q		C1507	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
Q160	Δ 8-729-188-22	TRANSISTOR 2SD882-Q		C1508	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
Q161	Δ 8-729-177-22	TRANSISTOR 2SB772-Q		C1509	Δ 1-130-471-00	MYLAR 0.001MF 5% 50V	
Q162	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE		C1510	Δ 1-162-117-00	CERAMIC 100PP 10% 500V	
Q163	Δ 8-729-140-97	TRANSISTOR 2SB734-34		C1511	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
Q165	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE		C1512	Δ 1-136-165-00	FILM 0.1MF 5% 50V	
Q166	Δ 8-729-139-98	TRANSISTOR 2SA1175-HFE		< CONNECTOR >			
Q167	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE		CN1173	Δ * 1-569-968-11	PLUG (WITH CONNECTOR) (L) 11P	
< RESISTOR >				< DIODE >			
R151	Δ 1-216-381-11	METAL OXIDE 0.22 5% 3W F		D1501	Δ 8-719-510-49	DIODE D1N20R-TA	
R152	Δ 1-216-381-11	METAL OXIDE 0.22 5% 3W F		D1502	Δ 8-719-510-18	DIODE D1NS4-TA	
R153	Δ 1-216-381-11	METAL OXIDE 0.22 5% 3W F		D1503	Δ 8-719-510-18	DIODE D1NS4-TA	
R154	Δ 1-216-381-11	METAL OXIDE 0.22 5% 3W F		D1504	Δ 8-719-112-34	DIODE RD7.5ESB2	
R155	Δ 1-249-401-11	CARBON 47 5% 1/4W F		D1505	Δ 8-719-921-20	DIODE 1SS119-2STD	
R156	Δ 1-249-401-11	CARBON 47 5% 1/4W F		D1507	Δ 8-719-050-84	DIODE RB441Q-40E77	
R157	Δ 1-249-381-11	CARBON 1 5% 1/4W F		< IC >			
R158	Δ 1-249-381-11	CARBON 1 5% 1/4W F		IC1501	Δ 8-759-191-54	IC UC3854N	
R159	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W		IC1502	Δ 8-759-135-80	IC μ PC358C	
R160	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W		< TRANSISTOR >			
R161	Δ 1-249-401-11	CARBON 47 5% 1/4W F		Q1501	Δ 8-729-139-98	TRANSISTOR 2SA1175-HFE	
R162	Δ 1-249-381-11	CARBON 1 5% 1/4W F		< RESISTOR >			
R163	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W		R1501	Δ 1-247-897-11	CARBON 560K 5% 1/4W	
R164	Δ 1-215-397-00	METAL 100 1% 1/4W		R1502	Δ 1-247-895-91	CARBON 470K 5% 1/4W	
R165	Δ 1-215-485-00	METAL 470K 1% 1/4W		R1503	Δ 1-249-441-11	CARBON 100K 5% 1/4W	
R166	Δ 1-215-485-00	METAL 470K 1% 1/4W		R1504	Δ 1-247-863-91	CARBON 22K 5% 1/4W	
R167	Δ 1-215-485-00	METAL 470K 1% 1/4W		R1505	Δ 1-247-897-11	CARBON 560K 5% 1/4W	
R168	Δ 1-215-449-00	METAL 15K 1% 1/4W		R1506	Δ 1-247-895-91	CARBON 470K 5% 1/4W	
R169	Δ 1-249-417-11	CARBON 1K 5% 1/4W		R1507	Δ 1-247-887-00	CARBON 220K 5% 1/4W	
R170	Δ 1-249-417-11	CARBON 1K 5% 1/4W		R1508	Δ 1-215-449-00	METAL 15K 1% 1/4W	
R171	Δ 1-249-401-11	CARBON 47 5% 1/4W		R1509	Δ 1-247-883-00	CARBON 150K 5% 1/4W	
R172	Δ 1-249-401-11	CARBON 47 5% 1/4W		R1510	Δ 1-249-441-11	CARBON 100K 5% 1/4W	
R173	Δ 1-249-401-11	CARBON 47 5% 1/4W					
R175	Δ 1-215-485-00	METAL 470K 1% 1/4W					
R176	Δ 1-249-417-11	CARBON 1K 5% 1/4W					
R177	Δ 1-247-822-11	CARBON 430 5% 1/4W					
R178	Δ 1-249-417-11	CARBON 1K 5% 1/4W					
R183	Δ 1-215-445-00	METAL 10K 1% 1/4W					
R184	Δ 1-249-437-11	CARBON 47K 5% 1/4W					

FAA

FAB

GA

The components identified by shading and marked Δ are critical for safety.

Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.

Ne les remplacer que par une pièce portant le numéro spécifié.

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
R1511 Δ	1-249-437-11	CARBON	47K 5% 1/4W	< COIL >			
R1512 Δ	1-249-441-11	CARBON	100K 5% 1/4W	L2201 Δ	1-406-703-11	COIL, CHOKE (PC8-3R3M) 3.3 μ H	
R1513 Δ	1-247-903-00	CARBON	1M 5% 1/4W	L2202 Δ	1-406-703-11	COIL, CHOKE (PC8-3R3M) 3.3 μ H	
R1514 Δ	1-215-435-00	METAL	3.9K 1% 1/4W	< PHOTO COUPLER >			
R1515 Δ	1-247-863-91	CARBON	22K 5% 1/4W	PH2101	8-749-010-64	PHOTO COUPLER PC123F2	
R1516 Δ	1-215-435-00	METAL	3.9K 1% 1/4W	< TRANSISTOR >			
R1517 Δ	1-215-421-00	METAL	1K 1% 1/4W	Q2103 Δ	8-729-177-22	TRANSISTOR 2SB772-Q	
R1518 Δ	1-215-453-00	METAL	22K 1% 1/4W	Q2201 Δ	8-729-139-98	TRANSISTOR 2SA1175-HFE	
R1519 Δ	1-249-429-11	CARBON	10K 5% 1/4W	Q2203 Δ	8-729-139-96	TRANSISTOR 2SC2785-HFE	
R1520 Δ	1-249-429-11	CARBON	10K 5% 1/4W	< RESISTOR >			
R1522 Δ	1-247-895-91	CARBON	470K 5% 1/4W	R2101 Δ	1-249-470-11	CARBON	0.47 5% 1/2W F
R1524 Δ	1-249-429-11	CARBON	10K 5% 1/4W	R2102 Δ	1-247-887-00	CARBON	220K 5% 1/4W
R1529 Δ	1-215-475-00	METAL	180K 1% 1/4W	R2103 Δ	1-247-887-00	CARBON	220K 5% 1/4W
R1530 Δ	1-215-475-00	METAL	180K 1% 1/4W	R2104 Δ	1-247-887-00	CARBON	220K 5% 1/4W
R1531 Δ	1-215-475-00	METAL	180K 1% 1/4W	R2105 Δ	1-247-887-00	CARBON	220K 5% 1/4W
R1532 Δ	1-215-425-00	METAL	1.5K 1% 1/4W	R2106 Δ	1-249-381-11	CARBON	1 5% 1/4W
R1533 Δ	1-215-444-00	METAL	9.1K 1% 1/4W	R2107 Δ	1-249-381-11	CARBON	1 5% 1/4W
< VARIABLE RESISTOR >				R2110 Δ	1-249-417-11	CARBON	1K 5% 1/4W
RV1501 Δ	1-241-762-11	RES, ADJ, CARBON 2.2K		R2111 Δ	1-249-429-11	CARBON	10K 5% 1/4W
*****				R2113 Δ	1-249-421-11	CARBON	2.2K 5% 1/4W
Δ * A-1241-266-A FAB MOUNTED PC BOARD				R2206 Δ	1-215-429-00	METAL	2.2K 1% 1/4W
*****				R2207 Δ	1-215-428-00	METAL	2K 1% 1/4W
< CAPACITOR >				R2208 Δ	1-247-807-31	CARBON	100 5% 1/4W
C2101 Δ	1-136-209-11	FILM	0.1MF 10% 630V	R2209 Δ	1-249-429-11	CARBON	10K 5% 1/4W
C2102 Δ	1-164-644-11	CERAMIC	330PF 10% 500V	R2210 Δ	1-249-413-11	CARBON	470 5% 1/4W
C2103 Δ	1-164-644-11	CERAMIC	330PF 10% 500V	R2211 Δ	1-249-429-11	CARBON	10K 5% 1/4W
C2104 Δ	1-136-066-00	FILM	0.003MF 0.03 2KV	R2212 Δ	1-249-429-11	CARBON	10K 5% 1/4W
C2105 Δ	1-136-162-00	FILM	0.056MF 5% 50V	< TRANSFORMER >			
C2106 Δ	1-136-162-00	FILM	0.056MF 5% 50V	T2101 Δ	1-429-987-11	TRANSFORMER, CONVERTER (PTT)	
C2107 Δ	1-136-167-00	FILM	0.15MF 5% 50V	T2102 Δ	1-429-992-11	TRANSFORMER, CONVERTER (PRT)	
C2108 Δ	1-136-167-00	FILM	0.15MF 5% 50V	*****			
C2110 Δ	1-111-084-11	ELECT	220MF 20% 35V	Δ * A-1316-285-A GA COMPLETE PC BOARD			
C2112 Δ	1-136-165-00	FILM	0.1MF 5% 50V	(Include GC Mounted PC BOARD)			
C2201 Δ	1-115-742-11	ELECT	0.0027F 20% 10V	*****			
C2202 Δ	1-126-941-11	ELECT	470MF 20% 25V	4-382-854-11	SCREW (M3X10), P, SW (+)		
C2203 Δ	1-126-933-11	ELECT	100MF 20% 10V	< CAPACITOR >			
C2204 Δ	1-104-665-11	ELECT	100MF 20% 25V	C102 Δ	1-137-499-11	FILM	0.015MF 5% 630V
C2205 Δ	1-136-165-00	FILM	0.1MF 5% 50V	C103 Δ	1-137-499-11	FILM	0.015MF 5% 630V
C2206 Δ	1-136-171-00	FILM	0.33MF 5% 50V	C105 Δ	1-107-792-11	CERAMIC	100PF 5% 1KV
C2207 Δ	1-136-165-00	FILM	0.1MF 5% 50V	C106 Δ	1-107-792-11	CERAMIC	100PF 5% 1KV
C2208 Δ	1-107-905-11	ELECT	4.7MF 20% 50V	C107 Δ	1-117-228-11	FILM	2.2MF 10% 450V
< CONNECTOR >				C108 Δ	1-104-665-11	ELECT	100MF 20% 25V
CN2177 Δ	1-778-897-11	SOCKET, CONNECTOR (RECEPTACLE)		C130 Δ	1-109-987-11	ELECT	270MF 20% 450V
CN2178 Δ	1-778-897-11	SOCKET, CONNECTOR (RECEPTACLE)		C131 Δ	1-109-987-11	ELECT	270MF 20% 450V
< DIODE >				C152 Δ	1-137-499-11	FILM	0.015MF 5% 630V
D2108 Δ	8-719-510-39	DIODE D10LC20U		C153 Δ	1-137-499-11	FILM	0.015MF 5% 630V
D2201 Δ	8-719-510-12	DIODE D10SC4M		C155 Δ	1-107-792-11	CERAMIC	100PF 5% 1KV
D2202 Δ	8-719-510-12	DIODE D10SC4M		C156 Δ	1-107-792-11	CERAMIC	100PF 5% 1KV
D2203 Δ	8-719-921-20	DIODE ISS119-25TD		C157 Δ	1-117-228-11	FILM	2.2MF 10% 450V
< IC >				C158 Δ	1-126-941-11	ELECT	470MF 20% 25V
IC2201 Δ	8-759-198-31	IC μ PC1093J-1-T		C201 Δ	1-117-407-11	ELECT	47MF 160V

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

GA

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C202	Δ 1-107-965-11	ELECT	100MF 20% 250V	Q253	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE	
C203	Δ 1-107-943-11	ELECT	10MF 20% 160V	Q254	Δ 8-729-139-98	TRANSISTOR 2SA1175-HFE	
C204	Δ 1-107-957-11	ELECT	1MF 20% 250V	Q255	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE	
C205	Δ 1-104-664-11	ELECT	47MF 20% 25V	< RESISTOR >			
C206	Δ 1-136-165-00	FILM	0.1MF 5% 50V	R101	Δ 1-249-425-11	CARBON 4.7K 5% 1/4W	
C208	Δ 1-130-479-00	MYLAR	0.0047MF 5% 50V	R102	Δ 1-249-425-11	CARBON 4.7K 5% 1/4W	
C209	Δ 1-130-467-00	MYLAR	470PF 5% 50V	R103	Δ 1-202-933-61	FUSIBLE 10% 10% 1/2W	F
C211	Δ 1-117-407-11	ELECT	47MF 160V	R104	Δ 1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C212	Δ 1-107-965-11	ELECT	100MF 20% 250V	R105	Δ 1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C222	Δ 1-104-665-11	ELECT	100MF 20% 25V	R106	Δ 1-249-414-11	CARBON 560 5% 1/4W	
C251	Δ 1-117-407-11	ELECT	47MF 160V	R107	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
C252	Δ 1-117-407-11	ELECT	47MF 160V	R109	Δ 1-247-863-91	CARBON 22K 5% 1/4W	
C253	Δ 1-107-943-11	ELECT	10MF 20% 160V	R151	Δ 1-249-425-11	CARBON 4.7K 5% 1/4W	
C254	Δ 1-130-467-00	MYLAR	470PF 5% 50V	R152	Δ 1-249-425-11	CARBON 4.7K 5% 1/4W	
C255	Δ 1-130-479-00	MYLAR	0.0047MF 5% 50V	R153	Δ 1-202-933-61	FUSIBLE 10% 10% 1/2W	F
C256	Δ 1-104-664-11	ELECT	47MF 20% 25V	R154	Δ 1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C257	Δ 1-117-407-11	ELECT	47MF 160V	R155	Δ 1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C260	Δ 1-130-471-00	MYLAR	0.001MF 5% 50V	R156	Δ 1-249-414-11	CARBON 560 5% 1/4W	
< CONNECTOR >				R157	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
CN112	Δ *1-573-896-11	SOCKET, CONNECTOR 12P		R158	Δ 1-249-407-11	CARBON 150 5% 1/4W	
CN113	Δ *1-573-896-11	SOCKET, CONNECTOR 12P		R159	Δ 1-247-863-91	CARBON 22K 5% 1/4W	
< DIODE >				R201	Δ 1-215-479-00	METAL 270K 1% 1/4W	
D131	Δ 8-719-030-48	DIODE 1JH46-TPA3		R202	Δ 1-215-476-00	METAL 200K 1% 1/4W	
D201	Δ 8-719-059-74	DIODE F10P40F		R203	Δ 1-215-444-00	METAL 9.1K 1% 1/4W	
D202	Δ 8-719-054-38	DIODE PCF10A60		R204	Δ 1-249-405-11	CARBON 100 5% 1/4W	F
D221	Δ 8-719-030-48	DIODE 1JH46-TPA3		R205	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
D251	Δ 8-719-059-74	DIODE F10P40F		R206	Δ 1-247-895-91	CARBON 470K 5% 1/4W	
< IC >				R207	Δ 1-249-441-11	CARBON 100K 5% 1/4W	
IC201	Δ 8-759-198-31	IC μ PC1093J-1-T		R208	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W	
IC202	Δ 8-759-135-80	IC μ PC358C		R210	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
< COIL >				R211	Δ 1-249-429-11	CARBON 10K 5% 1/4W	
L101	Δ 1-406-979-11	COIL, CHOKE 220 μ H		R212	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
L151	Δ 1-406-979-11	COIL, CHOKE 220 μ H		R213	Δ 1-215-481-00	METAL 330K 1% 1/4W	
L201	Δ 1-412-525-31	INDUCTOR 10 μ H		R214	Δ 1-215-477-00	METAL 220K 1% 1/4W	
L202	Δ 1-403-588-11	CIL, CHOKE 22 μ H		R215	Δ 1-215-445-00	METAL 10K 1% 1/4W	
L251	Δ 1-412-525-31	INDUCTOR 10 μ H		R220	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
< PHOTO COUPLER >				R231	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
PH101	Δ 8-749-010-63	PHOTO COUPLER PC123FY2		R232	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W	
PH102	Δ 8-749-010-65	PHOTO COUPLER PC123FY2		R233	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W	
PH151	Δ 8-749-010-65	PHOTO COUPLER PC123FY2		R251	Δ 1-215-479-00	METAL 270K 1% 1/4W	
PH152	Δ 8-749-010-65	PHOTO COUPLER PC123FY2		R252	Δ 1-215-476-00	METAL 200K 1% 1/4W	
< TRANSISTOR >				R253	Δ 1-215-444-00	METAL 9.1K 1% 1/4W	
Q101	Δ 8-729-023-20	TRANSISTOR 2SK1567		R254	Δ 1-249-405-11	CARBON 100 5% 1/4W	F
Q102	Δ 8-729-023-20	TRANSISTOR 2SK1567		R255	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
Q151	Δ 8-729-023-20	TRANSISTOR 2SK1567		R256	Δ 1-247-895-91	CARBON 470K 5% 1/4W	
Q152	Δ 8-729-023-20	TRANSISTOR 2SK1567		R257	Δ 1-249-441-11	CARBON 100K 5% 1/4W	
Q201	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE		R258	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W	
Q202	Δ 8-729-029-41	TRANSISTOR DTA124ESA-TP		R260	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
Q203	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE		R261	Δ 1-249-429-11	CARBON 10K 5% 1/4W	
Q204	Δ 8-729-139-98	TRANSISTOR 2SA1175-HFE		R262	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
Q205	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE		R263	Δ 1-215-481-00	METAL 330K 1% 1/4W	
Q251	Δ 8-729-139-96	TRANSISTOR 2SC2785-HFE		R264	Δ 1-215-477-00	METAL 220K 1% 1/4W	
Q252	Δ 8-729-029-41	TRANSISTOR DTA124ESA-TP		R265	Δ 1-215-445-00	METAL 10K 1% 1/4W	
				R281	Δ 1-249-417-11	CARBON 1K 5% 1/4W	
				R282	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W	
				R283	Δ 1-249-421-11	CARBON 2.2K 5% 1/4W	

GA

GB

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
< VARIABLE RESISTOR >				< DIODE >			
RV201 Δ	1-241-762-11	RES, ADJ, CARBON 2.2K		D131	8-719-030-48	DIODE 1JH46-TPA3	
RV231 Δ	1-241-762-11	RES, ADJ, CARBON 2.2K		D201	8-719-500-41	DIODE D8LCA20	
< TRANSFORMER >				D202	8-719-500-42	DIODE D8LCA20R	
T101 Δ	1-429-988-11	TRANSFORMER, CONVERTER (PIT)		D221	8-719-030-48	DIODE 1JH46-TPA3	
T151 Δ	1-429-989-11	TRANSFORMER, CONVERTER (PIT)		D251	8-719-510-09	DIODE D10SC6M	
*****				D252	8-719-988-31	DIODE D10SC6MR	
* A-1316-286-A GB COMPLETE PC BOARD (Include GC Mounted PC BOARD)				D253	8-719-052-92	DIODE D10SBS4F	
*****				< IC >			
4-382-854-11	SCREW (M3X10), P, SW (+)			IC201	8-759-198-31	IC μ PC1093J-1-T	
< CAPACITOR >				IC202	8-759-135-80	IC μ PC358C	
C102	1-137-499-11	FILM	0.015MF 5% 630V	< COIL >			
C103	1-137-499-11	FILM	0.015MF 5% 630V	L101	1-406-979-11	COIL, CHOKE 220 μ H	
C105	1-107-792-11	CERAMIC	100PF 5% 1KV	L151	1-406-979-11	COIL, CHOKE 220 μ H	
C106	1-107-792-11	CERAMIC	100PF 5% 1KV	L201	1-406-703-11	COIL, CHOKE (PC8-3R3M) 3.3 μ H	
C107	1-117-228-11	FILM	2.2MF 10% 450V	L202	1-406-703-11	COIL, CHOKE (PC8-3R3M) 3.3 μ H	
C108	1-104-665-11	ELECT	100MF 20% 25V	L251	1-406-703-11	COIL, CHOKE (PC8-3R3M) 3.3 μ H	
C130	1-109-987-11	ELECT	270MF 20% 450V	L252	1-406-703-11	COIL, CHOKE (PC8-3R3M) 3.3 μ H	
C131	1-109-987-11	ELECT	270MF 20% 450V	L253	1-406-703-11	COIL, CHOKE (PC8-3R3M) 3.3 μ H	
C152	1-137-499-11	FILM	0.015MF 5% 630V	L254	1-412-523-41	INDUCTOR 6.8 μ H	
C153	1-137-499-11	FILM	0.015MF 5% 630V	< PHOTO COUPLER >			
C155	1-107-792-11	CERAMIC	100PF 5% 1KV	PH101	8-749-010-64	PHOTO COUPLER PC123F2	
C156	1-107-792-11	CERAMIC	100PF 5% 1KV	PH102	8-749-010-64	PHOTO COUPLER PC123F2	
C157	1-117-228-11	FILM	2.2MF 10% 450V	PH151	8-749-010-64	PHOTO COUPLER PC123F2	
C158	1-104-665-11	ELECT	100MF 20% 25V	< TRANSISTOR >			
C201	1-111-154-51	ELECT	0.001F 20% 63V	Q101	8-729-023-20	TRANSISTOR 2SK1567	
C202	1-111-154-51	ELECT	0.001F 20% 63V	Q102	8-729-023-20	TRANSISTOR 2SK1567	
C203	1-111-136-11	ELECT	47MF 20% 63V	Q151	8-729-023-20	TRANSISTOR 2SK1567	
C204	1-111-154-51	ELECT	0.001F 20% 63V	Q152	8-729-023-20	TRANSISTOR 2SK1567	
C205	1-111-154-51	ELECT	0.001F 20% 63V	Q205	8-729-119-78	TRANSISTOR 2SC2785-HFE	
C206	1-111-136-11	ELECT	47MF 20% 63V	Q221	8-729-029-40	TRANSISTOR DTA124ESA	
C207	1-136-171-00	FILM	0.33MF 5% 50V	Q222	8-729-119-78	TRANSISTOR 2SC2785-HFE	
C208	1-130-479-00	MYLAR	0.0047MF 5% 50V	Q223	8-729-119-78	TRANSISTOR 2SC2785-HFE	
C220	1-104-665-11	ELECT	100MF 20% 25V	Q224	8-729-119-76	TRANSISTOR 2SA1175-HFE	
C221	1-136-165-00	FILM	0.1MF 5% 50V	Q227	8-729-119-78	TRANSISTOR 2SC2785-HFE	
C223	1-104-664-11	ELECT	47MF 20% 25V	< RESISTOR >			
C251	1-111-075-51	ELECT	0.0033F 20% 25V	R101	1-249-425-11	CARBON 4.7K 5% 1/4W	
C252	1-111-075-51	ELECT	0.0033F 20% 25V	R102	1-249-425-11	CARBON 4.7K 5% 1/4W	
C253	1-104-665-11	ELECT	100MF 20% 25V	R103	1-202-933-61	FUSIBLE 10% 10% 1/2W	F
C254	1-111-075-51	ELECT	0.0033F 20% 25V	R104	1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C255	1-111-075-51	ELECT	0.0033F 20% 25V	R105	1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C256	1-104-665-11	ELECT	100MF 20% 25V	R106	1-249-415-11	CARBON 680 5% 1/4W	
C257	1-111-021-11	ELECT	0.0033F 20% 10V	R107	1-249-417-11	CARBON 1K 5% 1/4W	
C258	1-111-021-11	ELECT	0.0033F 20% 10V	R109	1-247-863-91	CARBON 22K 5% 1/4W	
C259	1-126-933-11	ELECT	100MF 20% 10V	R151	1-249-425-11	CARBON 4.7K 5% 1/4W	
C260	1-111-014-11	ELECT	560MF 20% 10V	R152	1-249-425-11	CARBON 4.7K 5% 1/4W	
C261	1-126-933-11	ELECT	100MF 20% 10V	R153	1-202-933-61	FUSIBLE 10% 10% 1/2W	F
C262	1-136-153-00	FILM	0.01MF 5% 50V	R154	1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C263	1-130-479-00	MYLAR	0.0047MF 5% 50V	R155	1-216-361-00	METAL OXIDE 0.22 5% 2W	F
C265	1-111-075-51	ELECT	0.0033F 20% 25V	R156	1-249-415-11	CARBON 680 5% 1/4W	
< CONNECTOR >				R159	1-247-863-91	CARBON 22K 5% 1/4W	
CN122	* 1-573-896-11	SOCKET, CONNECTOR 12P		R201	1-215-456-00	METAL 30K 1% 1/4W	
CN123	* 1-573-896-11	SOCKET, CONNECTOR 12P		R202	1-215-426-00	METAL 1.6K 1% 1/4W	

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
R203	1-249-417-11	CARBON	1K	5%	1/4W		< TRANSISTOR >						
R205	1-247-863-91	CARBON	22K	5%	1/4W		Q301	Δ 8-729-114-68	TRANSISTOR 2SB810-H				
R206	1-249-421-11	CARBON	2.2K	5%	1/4W		Q302	Δ 8-729-114-68	TRANSISTOR 2SB810-H				
							Q303	Δ 8-729-140-00	TRANSISTOR 2SD774-34				
R208	1-249-417-11	CARBON	1K	5%	1/4W		< RESISTOR >						
R211	1-215-477-00	METAL	220K	1%	1/4W		R301	Δ 1-249-389-11	CARBON	4.7	5%	1/4W	
R212	1-249-429-11	CARBON	10K	5%	1/4W		R302	Δ 1-249-389-11	CARBON	4.7	5%	1/4W	
R220	1-249-429-11	CARBON	10K	5%	1/4W		R303	Δ 1-249-425-11	CARBON	4.7K	5%	1/4W	
R225	1-249-429-11	CARBON	10K	5%	1/4W		R304	Δ 1-249-425-11	CARBON	4.7K	5%	1/4W	
							R305	Δ 1-249-421-11	CARBON	2.2K	5%	1/4W	
R226	1-249-417-11	CARBON	1K	5%	1/4W								
R227	1-249-421-11	CARBON	2.2K	5%	1/4W		R306	Δ 1-249-421-11	CARBON	2.2K	5%	1/4W	
R228	1-249-417-11	CARBON	1K	5%	1/4W		R307	Δ 1-247-791-91	CARBON	22	5%	1/4W	
R229	1-249-421-11	CARBON	2.2K	5%	1/4W		R308	Δ 1-247-843-11	CARBON	3.3K	5%	1/4W	
R251	1-215-426-00	METAL	1.6K	1%	1/4W		R309	Δ 1-247-815-91	CARBON	220	5%	1/4W	
							R310	Δ 1-249-441-11	CARBON	100K	5%	1/4W	
R252	1-215-421-00	METAL	1K	1%	1/4W								
R253	1-249-417-11	CARBON	1K	5%	1/4W		R311	Δ 1-249-417-11	CARBON	1K	5%	1/4W	
R254	1-249-437-11	CARBON	47K	5%	1/4W		R312	Δ 1-249-425-11	CARBON	4.7K	5%	1/4W	
R255	1-249-421-11	CARBON	2.2K	5%	1/4W		R313	Δ 1-249-431-11	CARBON	15K	5%	1/4W	
R256	1-249-417-11	CARBON	1K	5%	1/4W		R314	Δ 1-249-425-11	CARBON	4.7K	5%	1/4W	
							R316	Δ 1-249-425-11	CARBON	4.7K	5%	1/4W	
R270	1-249-421-11	CARBON	2.2K	5%	1/4W								
R271	1-249-417-11	CARBON	1K	5%	1/4W		R317	Δ 1-249-421-11	CARBON	2.2K	5%	1/4W	
< VARIABLE RESISTOR >							< VARIABLE RESISTOR >						
RV251	1-241-760-11	RES. ADJ. CARBON 470					< TRANSFORMER >						
< TRANSFORMER >							RV301	Δ 1-241-784-11	RES. ADJ. CERMET 4.7K				
T101	1-429-990-11	TRANSFORMER, CONVERTER (PIT)					< TRANSFORMER >						
T151	1-429-991-11	TRANSFORMER, CONVERTER (PIT)					T301	Δ 1-429-741-11	TRANSFORMER, DRIVE				
*****							*****						
Δ * A-1311-518-A GC MOUNTED PC BOARD							*****						
< CAPACITOR >							* A 1390-695-A L MOUNTED PC BOARD						

C301	Δ 1-130-475-00	MYLAR	0.0022MF	5%	50V		* 7-322-065-72 RUBBER, RTV (SE-9168) (130G)						
C302	Δ 1-130-475-00	MYLAR	0.0022MF	5%	50V		< CAPACITOR >						
C303	Δ 1-130-467-00	MYLAR	470PF	5%	50V		C501	1-126-967-11	ELECT	47MF	20%	16V	
C304	Δ 1-130-467-00	MYLAR	470PF	5%	50V		C502	1-107-906-11	ELECT	10MF	20%	50V	
C305	Δ 1-136-165-00	FILM	0.1MF	5%	50V		< CONNECTOR >						
C306	Δ 1-136-165-00	FILM	0.1MF	5%	50V		CN105	* 1-774-244-11	CONNECTOR, BOARD TO BOARD 5P				
C307	Δ 1-136-153-00	FILM	0.01MF	5%	50V		CN107	* 1-774-245-11	CONNECTOR, BOARD TO BOARD 8P				
C308	Δ 1-130-467-00	MYLAR	470PF	5%	50V		< DIODE >						
C309	Δ 1-130-012-00	FILM	330PF	5%	50V		D501	8-719-801-78	DIODE 1SS184				
C310	Δ 1-136-169-00	FILM	0.22MF	5%	50V		< IC >						
C311	Δ 1-136-165-00	FILM	0.1MF	5%	50V		IC501	8-759-100-93	IC μPC393G2				
C312	Δ 1-136-173-00	FILM	0.47MF	5%	50V		IC502	8-759-100-93	IC μPC393G2				
< DIODE >							< TRANSISTOR >						
D301	Δ 8-719-210-21	DIODE 11EQS04					Q501	8-729-027-59	TRANSISTOR DTC144EKA-T146				
D302	Δ 8-719-210-21	DIODE 11EQS04					< RESISTOR >						
D303	Δ 8-719-050-84	DIODE RB441Q-40T-77					R501	1-216-081-00	METAL GLAZE	22K	5%	1/10W	
D304	Δ 8-719-050-84	DIODE RB441Q-40T-77					R502	1-216-073-00	METAL GLAZE	10K	5%	1/10W	
D305	Δ 8-719-911-19	DIODE 1SS119-25											
D306	Δ 8-719-929-15	DIODE HZS9.1NB2											
< IC >													
IC301	Δ 8-759-298-87	IC CXA8038P											

REF NO.	PART NO.	DESCRIPTION	REMARK
R503	1-216-105-91	METAL GLAZE	220K 5% 1/10W
R504	1-216-105-91	METAL GLAZE	220K 5% 1/10W
R505	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R506	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R507	1-216-025-91	METAL GLAZE	100 5% 1/10W
R508	1-216-105-91	METAL GLAZE	220K 5% 1/10W
R509	1-216-105-91	METAL GLAZE	220K 5% 1/10W
R510	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R511	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R512	1-216-025-91	METAL GLAZE	100 5% 1/10W
R513	1-216-083-00	METAL GLAZE	27K 5% 1/10W
R514	1-216-083-00	METAL GLAZE	27K 5% 1/10W
R515	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R516	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R517	1-216-025-91	METAL GLAZE	100 5% 1/10W
R518	1-216-097-91	METAL GLAZE	100K 5% 1/10W
R519	1-216-097-91	METAL GLAZE	100K 5% 1/10W
R520	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R521	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R522	1-216-025-91	METAL GLAZE	100 5% 1/10W
R523	1-216-025-91	METAL GLAZE	100 5% 1/10W
R524	1-247-855-31	CARBON	10K 5% 1/4W

* A-1304-112-A MF MOUNTED PC BOARD

< CAPACITOR >

C1 1-113-706-11 ELECT(BLOCK) 0.027PF 20% 200V

< CONNECTOR >

CN201 * 1-564-508-11 PLUG, CONNECTOR 5P
CN202 * 1-564-508-11 PLUG, CONNECTOR 5P
CN203 * 1-564-508-11 PLUG, CONNECTOR 5P
CN204 1-564-511-11 PLUG, CONNECTOR 8P
CN211 * 1-564-506-11 PLUG, CONNECTOR 1P

CN212 1-564-506-11 PLUG, CONNECTOR 1P
CN213 * 1-564-506-11 PLUG, CONNECTOR 3P
CN221 * 1-564-507-11 PLUG, CONNECTOR 4P
CN222 * 1-564-507-11 PLUG, CONNECTOR 4P
CN223 * 1-564-507-11 PLUG, CONNECTOR 4P

CN251 * 1-564-507-11 PLUG, CONNECTOR 4P
CN252 * 1-564-507-11 PLUG, CONNECTOR 4P
CN253 * 1-564-507-11 PLUG, CONNECTOR 4P
CN263 * 1-564-512-11 PLUG, CONNECTOR 9P
CN264 * 1-564-512-11 PLUG, CONNECTOR 9P

CN265 * 1-564-512-11 PLUG, CONNECTOR 9P
CN271 * 1-564-510-11 PLUG, CONNECTOR 7P
CN272 1-564-510-11 PLUG, CONNECTOR 7P
CN273 * 1-564-510-11 PLUG, CONNECTOR 7P
CN281 * 1-564-509-11 PLUG, CONNECTOR 6P

CN282 * 1-564-509-11 PLUG, CONNECTOR 6P
CN283 * 1-564-509-11 PLUG, CONNECTOR 6P
CN601 * 1-564-507-11 PLUG, CONNECTOR 4P
CN605 * 1-774-247-11 CONNECTOR, BOARD TO BOARD 5P
CN607 * 1-774-248-11 CONNECTOR, BOARD TO BOARD 8P

REF NO.	PART NO.	DESCRIPTION	REMARK
< RESISTOR >			
R1	1-202-961-11	WIREWOUND	1.8 5% 10W
R2	1-202-961-11	WIREWOUND	1.8 5% 10W
R26	1-216-483-11	METAL OXIDE	2.7K 5% 3W F
R27	1-216-483-11	METAL OXIDE	2.7K 5% 3W F

* A-1304-113-A MR MOUNTED PC BOARD

* 1-533-701-11 HOLDER, FUSE (F1)
* 7-322-065-72 RUBBER, RTV (SE-9168) (130G)

< CAPACITOR >

C1 1-126-942-61 ELECT 1000MF 20% 25V
C2 1-126-942-61 ELECT 1000MF 20% 25V
C3 1-126-942-61 ELECT 1000MF 20% 25V
C4 1-104-666-11 ELECT 220MF 20% 25V
C5 1-104-666-11 ELECT 220MF 20% 25V

C6 1-104-666-11 ELECT 220MF 20% 25V
C7 1-126-964-11 ELECT 10MF 20% 50V

< CONNECTOR >

CN6 * 1-535-419-00 TAB, FASTEN (PCB)
CN7 * 1-535-419-00 TAB, FASTEN (PCB)
CN151 * 1-564-506-11 PLUG, CONNECTOR 3P
CN152 * 1-564-506-11 PLUG, CONNECTOR 3P
CN153 * 1-564-506-11 PLUG, CONNECTOR 3P

< TRANSISTOR >

Q1 8-729-030-03 TRANSISTOR DTC144ESA-TP
Q2 8-729-030-03 TRANSISTOR DTC144ESA-TP
Q3 8-729-030-03 TRANSISTOR DTC144ESA-TP
Q4 8-729-030-03 TRANSISTOR DTC144ESA-TP

< RESISTOR >

R1 1-215-908-00 METAL OXIDE 33 5% 3W F
R2 1-215-908-00 METAL OXIDE 33 5% 3W F
R3 1-215-908-00 METAL OXIDE 33 5% 3W F
R4 1-247-887-00 CARBON 220K 5% 1/4W
R5 1-247-887-00 CARBON 220K 5% 1/4W

R6 1-247-887-00 CARBON 220K 5% 1/4W
R7 1-249-417-11 CARBON 1K 5% 1/4W
R8 1-249-417-11 CARBON 1K 5% 1/4W
R9 1-249-417-11 CARBON 1K 5% 1/4W
R10 1-215-914-11 METAL OXIDE 330 5% 3W F

R11 1-215-914-11 METAL OXIDE 330 5% 3W F
R12 1-215-914-11 METAL OXIDE 330 5% 3W F
R13 1-215-914-11 METAL OXIDE 330 5% 3W F
R14 1-215-914-11 METAL OXIDE 330 5% 3W F
R15 1-215-914-11 METAL OXIDE 330 5% 3W F

R16 1-215-914-11 METAL OXIDE 330 5% 3W F
R17 1-215-914-11 METAL OXIDE 330 5% 3W F
R18 1-215-914-11 METAL OXIDE 330 5% 3W F
R19 1-215-915-11 METAL OXIDE 470 5% 3W F
R20 1-215-915-11 METAL OXIDE 470 5% 3W F

R21 1-215-915-11 METAL OXIDE 470 5% 3W F
R22 1-249-417-11 CARBON 1K 5% 1/4W
R23 1-249-437-11 CARBON 47K 5% 1/4W

MR

MT

NA

NB

REF NO.	PART NO.	DESCRIPTION	REMARK
R24	1-215-914-11	METAL OXIDE 330 5% 3W	F
R25	1-215-914-11	METAL OXIDE 330 5% 3W	F
R26	1-215-914-11	METAL OXIDE 330 5% 3W	F
R27	1-216-471-11	METAL OXIDE 27 5% 3W	F
R28	1-216-471-11	METAL OXIDE 27 5% 3W	F
R29	1-216-471-11	METAL OXIDE 27 5% 3W	F

* A-1304-114-A MT MOUNTED PC BOARD

4-389-026-11 SHEET, BN
 * 4-393-411-21 HEAT SINK, SOUND
 7-682-949-01 SCREW +PSW 3X10

< CAPACITOR >

C1	1-107-943-11	ELECT 10MF 20% 160V	
C2	1-126-795-11	ELECT 10MF 20% 50V	
C3	1-107-943-11	ELECT 10MF 20% 160V	
C4	1-107-961-91	ELECT 10MF 20% 250V	
C5	1-107-961-91	ELECT 10MF 20% 250V	

C6	1-126-795-11	ELECT 10MF 20% 50V	
C7	1-107-939-11	ELECT 1MF 20% 160V	
C8	1-107-957-11	ELECT 1MF 20% 250V	

< CONNECTOR >

CN550 1-564-511-11 PLUG, CONNECTOR 8P

< DIODE >

D1	8-719-109-89	DIODE RD5.6ESB2	
D2	8-719-109-89	DIODE RD5.6ESB2	

< TRANSISTOR >

Q1	8-729-111-74	TRANSISTOR 2SD1289-Q	
Q2	8-729-207-82	TRANSISTOR 2SC3421-Y	
Q3	8-729-111-74	TRANSISTOR 2SD1289-Q	
Q4	8-729-821-02	TRANSISTOR 2SC3503-DE	

< RESISTOR >

R1	1-249-417-11	CARBON 1K 5% 1/4W	F
R2	1-216-486-00	METAL OXIDE 8.2K 5% 3W	F
R3	1-216-443-11	METAL OXIDE 56K 5% 1W	F
R4	1-215-465-00	METAL 68K 1% 1/4W	
R5	1-215-451-00	METAL 18K 1% 1/4W	
R6	1-215-439-00	METAL 5.6K 1% 1/4W	
R7	1-249-416-11	CARBON 820 5% 1/4W	F
R8	1-215-461-00	METAL 47K 1% 1/4W	
R9	1-215-451-00	METAL 18K 1% 1/4W	
R10	1-215-429-00	METAL 2.2K 1% 1/4W	
R11	1-215-433-00	METAL 3.3K 1% 1/4W	
R12	1-216-487-11	METAL OXIDE 12K 5% 3W	F
R13	1-216-443-11	METAL OXIDE 56K 5% 1W	F

* A-1390-675-A NA MOUNTED PC BOARD

* 4-398-771-01 CAP, LED

REF NO.	PART NO.	DESCRIPTION	REMARK
< CAPACITOR >			
C851	1-124-589-11	ELECT 47MF 20% 16V	
C852	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C853	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C854	1-164-232-11	CERAMIC CHIP 0.01MF 10% 50V	
C863	1-163-243-11	CERAMIC CHIP 47PF 5% 50V	

< CONNECTOR >

CN750 * 1-564-528-11 PLUG, CONNECTOR 13P

< DIODE >

D851	8-719-955-04	DIODE PY5504S-1	
D852	8-719-920-66	DIODE SLR-54VC12	
D853	8-719-962-02	DIODE GL-6P202	

< IC >

IC851	8-742-020-00	HYB IC SBX1610-09	
IC852	8-759-926-77	IC SN74HC541ANS	
IC853	8-759-044-95	IC MC14495P1	
IC854	8-759-044-95	IC MC14495P1	

< TRANSISTOR >

Q851	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q852	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q853	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q854	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
Q855	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	

< RESISTOR >

R851	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R852	1-216-033-00	METAL GLAZE 220 5% 1/10W	
R853	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R854	1-216-081-00	METAL GLAZE 22K 5% 1/10W	
R855	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
R856	1-216-097-91	METAL GLAZE 100K 5% 1/10W	
R857	1-216-097-91	METAL GLAZE 100K 5% 1/10W	
R858	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R860	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R861	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R862	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R863	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R864	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R865	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R866	1-216-025-91	METAL GLAZE 100 5% 1/10W	
R867	1-216-025-91	METAL GLAZE 100 5% 1/10W	

* A-1390-679-A NB MOUNTED PC BOARD

* 4-374-987-01 GUIDE, LIGHT
 * 4-381-686-01 BRACKET (B), BAR, OPTICAL

< CAPACITOR >

C650	1-124-589-11	ELECT 47MF 20% 16V	
C651	1-163-243-11	CERAMIC CHIP 47PF 5% 50V	

NB**PA**

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
< CONNECTOR >				C42	1-107-883-11	ELECT	330MF 20% 16V
CN650	* 1-564-518-11	PLUG, CONNECTOR 3P		C43	1-102-973-00	CERAMIC	100PF 5% 50V
< IC >				C44	1-126-933-11	ELECT	100MF 20% 16V
IC650	8-741-820-59	HYB IC SBX1820-59		C45	1-102-973-00	CERAMIC	100PF 5% 50V
*****				C46	1-102-973-00	CERAMIC	100PF 5% 50V
* A-1195-114-A PA COMPLETE PC BOARD				C47	1-126-929-11	ELECT	4700MF 20% 10V
*****				C48	1-136-729-11	FILM	1.5MF 5% 400V
4-056-066-01	HOLDER (C), TR			C49	1-126-964-11	ELECT	10MF 20% 50V
4-393-406-01	SHEET (R), RADIATION			C50	1-137-364-11	FILM	0.001MF 5% 50V
7-322-065-19	RUBBER, SILICON RTV (KE490W)			C51	1-126-968-11	ELECT	100MF 20% 50V
* 7-322-065-72	RUBBER, RTV (SE-9168) (130G)			C52	1-126-964-11	ELECT	10MF 20% 50V
7-682-949-01	SCREW +PSW 3X10			C53	1-137-366-11	FILM	0.0022MF 5% 50V
< CAPACITOR >				C54	1-126-929-11	ELECT	4700MF 20% 10V
C1	1-101-004-00	CERAMIC	0.01MF 50V	C55	1-123-024-21	ELECT	33MF 160V
C2	1-136-169-00	FILM	0.22MF 5% 50V	C56	1-126-964-11	ELECT	10MF 20% 50V
C3	1-126-964-11	ELECT	10MF 20% 50V	C57	1-136-169-00	FILM	0.22MF 5% 50V
C4	1-128-551-11	ELECT	22MF 20% 25V	C58	1-137-370-11	FILM	0.01MF 5% 50V
C5	1-126-961-11	ELECT	2.2MF 20% 50V	C59	1-126-964-11	ELECT	10MF 20% 50V
C6	1-126-964-11	ELECT	10MF 20% 50V	C60	1-107-906-11	ELECT	10MF 20% 16V
C7	1-104-987-11	FILM	0.001MF 5% 200V	C61	1-102-244-00	CERAMIC	220PF 10% 500V
C8	1-102-973-00	CERAMIC	100PF 5% 50V	C62	1-136-103-00	FILM	0.1MF 5% 200V
C9	1-126-963-11	ELECT	4.7MF 20% 50V	C63	1-136-613-11	FILM	0.0068MF 0.03 2KV
C10	1-126-964-11	ELECT	10MF 20% 50V	C64	1-123-024-21	ELECT	33MF 160V
C11	1-126-964-11	ELECT	10MF 20% 50V	C65	1-123-024-21	ELECT	33MF 160V
C12	1-102-973-00	CERAMIC	100PF 5% 50V	C66	1-136-085-00	FILM	0.016MF 0.03 2KV
C13	1-101-004-00	CERAMIC	0.01MF 50V	C67	1-102-973-00	CERAMIC	100PF 5% 50V
C14	1-102-973-00	CERAMIC	100PF 5% 50V	C68	1-102-973-00	CERAMIC	100PF 5% 50V
C15	1-107-651-11	ELECT	4.7MF 20% 250V	C69	1-101-004-00	CERAMIC	0.01MF 50V
C16	1-107-651-11	ELECT	4.7MF 20% 250V	C70	1-104-987-11	FILM	0.001MF 5% 200V
C17	1-101-004-00	CERAMIC	0.01MF 50V	C71	1-125-538-11	ELECT(BLACK)	1000MF 20% 200V
C18	1-101-004-00	CERAMIC	0.01MF 50V	C72	1-136-153-00	FILM	0.01MF 5% 50V
C19	1-126-960-11	ELECT	1MF 20% 50V	C73	1-126-600-11	ELECT	100MF 20% 160V
C20	1-136-165-00	FILM	0.1MF 5% 50V	C74	1-107-370-11	FILM	0.1MF 10% 200V
C21	1-136-165-00	FILM	0.1MF 5% 50V	C75	1-107-364-11	FILM	0.01MF 10% 200V
C22	1-126-964-11	ELECT	10MF 20% 50V	C76	1-107-370-11	FILM	0.1MF 10% 200V
C23	1-102-973-00	CERAMIC	100PF 5% 50V	C77	1-115-176-11	FILM	12000PF 0.03 2KV
C24	1-101-004-00	CERAMIC	0.01MF 50V	C78	1-109-889-11	ELECT	1MF 20% 50V
C25	1-136-165-00	FILM	0.1MF 5% 50V	C79	1-104-989-91	FILM	0.0022MF 5% 200V
C26	1-136-165-00	FILM	0.1MF 5% 50V	C80	1-126-933-11	ELECT	100MF 20% 16V
C27	1-126-964-11	ELECT	10MF 20% 50V	C81	1-126-933-11	ELECT	100MF 20% 16V
C28	1-126-933-11	ELECT	100MF 20% 16V	C82	1-136-165-00	FILM	0.1MF 5% 50V
C29	1-104-665-11	ELECT	100MF 20% 25V	C83	1-136-561-11	FILM	0.0068MF 10% 630V
C30	1-107-883-11	ELECT	330MF 20% 16V	C84	1-126-600-11	ELECT	100MF 20% 160V
C31	1-136-169-00	FILM	0.22MF 5% 50V	C85	1-126-960-11	ELECT	1MF 20% 50V
C32	1-137-366-11	FILM	0.0022MF 5% 50V	C86	1-102-030-00	CERAMIC	330PF 10% 500V
C33	1-104-666-11	ELECT	220MF 20% 25V	C87	1-126-600-11	ELECT	100MF 20% 160V
C34	1-137-368-11	FILM	0.0047MF 5% 50V	C88	1-136-159-00	FILM	0.033MF 5% 50V
C35	1-102-978-00	CERAMIC	220PF 5% 50V	C89	1-102-973-00	CERAMIC	100PF 5% 50V
C36	1-137-364-11	FILM	0.001MF 5% 50V	C90	1-126-964-11	ELECT	10MF 20% 50V
C37	1-104-666-11	ELECT	220MF 20% 25V	C91	1-126-964-11	ELECT	10MF 20% 50V
C38	1-129-718-00	FILM	0.022MF 10% 630V	C92	1-126-960-11	ELECT	1MF 20% 50V
C39	1-101-004-00	CERAMIC	0.01MF 50V	C93	1-126-964-11	ELECT	10MF 20% 50V
C40	1-126-943-11	ELECT	2200MF 20% 25V	C94	1-126-964-11	ELECT	10MF 20% 50V
C41	1-126-929-11	ELECT	4700MF 20% 10V	C95	1-126-960-11	ELECT	1MF 20% 50V
				C96	1-126-963-11	ELECT	4.7MF 20% 50V
				C97	1-107-662-11	ELECT	22MF 20% 250V
				C98	1-126-963-11	ELECT	4.7MF 20% 50V
				C99	1-126-964-11	ELECT	10MF 20% 50V
				C100	1-101-004-00	CERAMIC	0.01MF 50V

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

PA

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C101	1-136-165-00	FILM	0.1MF 5% 50V	D45	8-719-911-19	DIODE 1SS119-25	
C102	1-136-165-00	FILM	0.1MF 5% 50V	D46	8-719-911-19	DIODE 1SS119-25	
C103	1-136-165-00	FILM	0.1MF 5% 50V				
< CONNECTOR >				D51	8-719-911-19	DIODE 1SS119-25	
CN401	* 1-750-916-11	PIN, CONNECTOR(DY)(PC BOARD)8P		D52	8-719-911-19	DIODE 1SS119-25	
CN402	* 1-564-506-11	PLUG, CONNECTOR 3P		D53	8-719-911-19	DIODE 1SS119-25	
CN403	* 1-564-509-11	PLUG, CONNECTOR 6P		D54	8-719-979-58	DIODE EGP10D	
CN404	* 1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P		D55	8-719-900-95	DIODE V09G	
CN405	* 1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P					
CN406	* 1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P		D56	8-719-911-19	DIODE 1SS119-25	
CN407	* 1-564-507-11	PLUG, CONNECTOR 4P		D57	8-719-911-19	DIODE 1SS119-25	
CN408	* 1-564-506-11	PLUG, CONNECTOR 3P		D58	8-719-911-19	DIODE 1SS119-25	
< DIODE >				< FERRITE BEAD >			
D1	8-719-109-85	DIODE RD5.1ESB2		FB1	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D2	8-719-911-19	DIODE 1SS119-25		FB2	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D3	8-719-911-19	DIODE 1SS119-25		FB3	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D4	8-719-911-19	DIODE 1SS119-25		FB4	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D5	8-719-911-19	DIODE 1SS119-25		FB5	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D6	8-719-911-19	DIODE 1SS119-25					
D7	8-719-911-19	DIODE 1SS119-25		FB6	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D8	8-719-911-19	DIODE 1SS119-25		FB7	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D9	8-719-911-19	DIODE 1SS119-25		FB8	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D10	8-719-979-58	DIODE EGP10D		FB9	1-410-396-41	FERRITE BEAD INDUCTOR	0.45μH
D11	8-719-911-19	DIODE 1SS119-25		< IC >			
D12	8-719-109-66	DIODE RD3.3ESB2		IC1	8-759-103-93	IC μPC393C	
D13	8-719-979-58	DIODE EGP10D		IC2	8-759-040-01	IC MC14001BCP	
D14	8-719-054-86	DIODE ERC88M-009		IC3	8-759-503-91	IC TL082ACP	
D15	8-719-900-95	DIODE V09G		IC4	8-759-140-11	IC UPD4011BC	
D16	8-719-054-86	DIODE ERC88M-009		IC5	8-759-103-93	IC μPC393C	
D17	8-719-110-36	DIODE RD13ESB2					
D18	8-719-911-19	DIODE 1SS119-25		IC7	8-759-103-93	IC μPC393C	
D19	8-719-110-36	DIODE RD13ESB2		IC8	8-759-929-65	IC LM7912CT	
D20	8-719-911-19	DIODE 1SS119-25		IC9	8-759-240-40	IC TC4040BP	
D21	8-719-054-86	DIODE ERC88M-009		IC10	8-759-503-91	IC TL082ACP	
D22	8-719-900-95	DIODE V09G		IC11	8-759-231-58	IC TA7812S	
D24	8-719-901-19	DIODE V11N					
D25	8-719-110-78	DIODE RD33ESB2		IC12	8-759-045-72	IC MC14572UBCP	
D26	8-719-911-19	DIODE 1SS119-25		IC13	8-759-908-15	IC TL431CLP	
D27	8-719-920-67	DIODE ERC91-02		IC14	8-759-145-58	IC μPC4558C	
D28	8-719-920-67	DIODE ERC91-02		IC15	8-759-100-75	IC μPC1394C	
D29	8-719-920-67	DIODE ERC91-02		IC16	8-759-145-58	IC μPC4558C	
D30	8-719-911-19	DIODE 1SS119-25					
D31	8-719-945-81	DIODE ERC06-1SSA		IC18	8-759-145-58	IC μPC4558C	
D32	8-719-945-81	DIODE ERC06-1SSA		< COIL >			
D33	8-719-043-14	DIODE ESAD39M-06C		L1	1-459-155-00	COIL (WITH CORE)	45μH
D34	8-719-911-19	DIODE 1SS119-25		L2	1-412-521-31	INDUCTOR	4.7μH
D35	8-719-911-19	DIODE 1SS119-25		L3	1-412-521-31	INDUCTOR	4.7μH
D36	8-719-110-36	DIODE RD13ESB2		L4	1-459-155-00	COIL (WITH CORE)	45μH
D37	8-719-110-36	DIODE RD13ESB2		L5	1-459-155-00	COIL (WITH CORE)	45μH
D38	8-719-920-67	DIODE ERC91-02					
D39	8-719-911-19	DIODE 1SS119-25		L6	Δ 1-409-543-12	COIL, CHOKE	420μH
D40	8-719-911-19	DIODE 1SS119-25		L7	Δ 1-409-543-12	COIL, CHOKE	420μH
D41	8-719-911-19	DIODE 1SS119-25		L8	1-459-483-00	COIL (WITH CORE)	
D42	8-719-911-19	DIODE 1SS119-25		L9	1-410-686-11	INDUCTOR	1mH
D43	8-719-109-85	DIODE RD5.1ESB2		L10	1-411-566-11	COIL, CHOKE	1mH
D44	8-719-911-19	DIODE 1SS119-25					
				L11	1-459-614-11	COIL, CHOKE	90μH
				L12	1-459-614-11	COIL, CHOKE	90μH
				< TRANSISTOR >			
				Q1	8-729-119-78	TRANSISTOR 2SC2785-HFE	
				Q2	8-729-119-78	TRANSISTOR 2SC2785-HFE	
				Q3	8-729-119-78	TRANSISTOR 2SC2785-HFE	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
Q4	8-729-119-76	TRANSISTOR 2SA1175-HFE		R19	1-215-469-00	METAL 100K 1%	1/4W
Q5	8-729-119-78	TRANSISTOR 2SC2785-HFE		R20	1-249-429-11	CARBON 10K 5%	1/4W
Q6	8-729-119-78	TRANSISTOR 2SC2785-HFE		R21	1-249-425-11	CARBON 4.7K 5%	1/4W
Q7	8-729-119-76	TRANSISTOR 2SA1175-HFE		R22	1-249-439-11	CARBON 68K 5%	1/4W
Q11	8-729-030-03	TRANSISTOR DTC144ESA-TP		R23	1-247-843-11	CARBON 3.3K 5%	1/4W
Q12	8-729-140-96	TRANSISTOR 2SD774-34		R24	1-249-417-11	CARBON 1K 5%	1/4W
Q13	8-729-140-97	TRANSISTOR 2SB734-34		R25	1-249-431-11	CARBON 15K 5%	1/4W
Q14	8-729-119-78	TRANSISTOR 2SC2785-HFE		R26	1-249-417-11	CARBON 1K 5%	1/4W
Q15	8-729-119-76	TRANSISTOR 2SA1175-HFE		R27	1-249-429-11	CARBON 10K 5%	1/4W
Q16	8-729-802-71	TRANSISTOR 2SA1407-D		R28	1-249-429-11	CARBON 10K 5%	1/4W
Q17	8-729-821-87	TRANSISTOR 2SD1878-CA		R29	1-247-807-31	CARBON 100 5%	1/4W
Q18	8-729-030-03	TRANSISTOR DTC144ESA-TP		R30	1-249-441-11	CARBON 100K 5%	1/4W
Q19	8-729-119-80	TRANSISTOR 2SC2688-LK		R31	1-249-417-11	CARBON 1K 5%	1/4W
Q20	8-729-119-78	TRANSISTOR 2SC2785-HFE		R32	1-249-436-11	CARBON 39K 5%	1/4W
Q21	8-729-119-76	TRANSISTOR 2SA1175-HFE		R33	1-249-436-11	CARBON 39K 5%	1/4W
Q22	8-729-033-57	TRANSISTOR IRFP350LF20		R34	1-249-436-11	CARBON 39K 5%	1/4W
Q23	8-729-207-89	TRANSISTOR 2SA1358-Y		R35	1-249-429-11	CARBON 10K 5%	1/4W
Q24	8-729-119-80	TRANSISTOR 2SC2688-LK		R36	1-247-843-11	CARBON 3.3K 5%	1/4W
Q25	8-729-119-78	TRANSISTOR 2SC2785-HFE		R37	1-215-863-11	METAL OXIDE 100 5%	1W F
Q26	8-729-140-96	TRANSISTOR 2SD774-34		R38	1-215-432-00	METAL 3K 1%	1/4W
Q27	8-729-820-71	TRANSISTOR 2SC3998CA		R39	1-215-432-00	METAL 3K 1%	1/4W
Q28	8-729-024-38	TRANSISTOR IRFP250		R40	1-215-432-00	METAL 3K 1%	1/4W
Q29	8-729-143-42	TRANSISTOR 2SK929		R41	1-249-437-11	CARBON 47K 5%	1/4W
Q30	8-729-140-97	TRANSISTOR 2SB734-34		R42	1-247-863-91	CARBON 22K 5%	1/4W
Q31	8-729-105-74	TRANSISTOR 2SK523-M1		R43	1-247-807-31	CARBON 100 5%	1/4W
Q32	8-729-119-76	TRANSISTOR 2SA1175-HFE		R44	1-249-417-11	CARBON 1K 5%	1/4W
Q33	8-729-031-68	TRANSISTOR 2SC4630LS		R45	1-247-895-91	CARBON 470K 5%	1/4W
Q34	8-729-119-78	TRANSISTOR 2SC2785-HFE		R46	1-247-807-31	CARBON 100 5%	1/4W
Q35	8-729-119-78	TRANSISTOR 2SC2785-HFE		R47	1-247-807-31	CARBON 100 5%	1/4W
Q36	8-729-119-76	TRANSISTOR 2SA1175-HFE		R48	1-215-432-00	METAL 1K 1%	1/4W
Q37	8-729-119-76	TRANSISTOR 2SA1175-HFE		R49	1-215-432-00	METAL 1K 1%	1/4W
Q38	8-729-030-03	TRANSISTOR DTC144ESA-TP		R50	1-215-432-00	METAL 1K 1%	1/4W
Q39	8-729-801-88	TRANSISTOR 2SA1381-E		R51	1-215-863-11	METAL OXIDE 100 5%	1W F
Q40	8-729-031-68	TRANSISTOR 2SC4630LS		R52	1-249-401-11	CARBON 47 5%	1/4W F
Q41	8-729-031-68	TRANSISTOR 2SC4630LS		R53	1-249-439-11	CARBON 68K 5%	1/4W
Q42	8-729-119-78	TRANSISTOR 2SC2785-HFE		R54	1-247-903-00	CARBON 1M 5%	1/4W
Q43	8-729-119-78	TRANSISTOR 2SC2785-HFE		R55	1-249-417-11	CARBON 1K 5%	1/4W
Q44	8-729-119-76	TRANSISTOR 2SA1175-HFE		R56	1-249-417-11	CARBON 1K 5%	1/4W
Q100	8-729-029-56	TRANSISTOR DTA144ESA		R57	1-249-429-11	CARBON 10K 5%	1/4W
< RESISTOR >				R58	1-249-411-11	CARBON 330 5%	1/4W
R1	1-215-473-00	METAL 150K 1%	1/4W	R59	1-249-429-11	CARBON 10K 5%	1/4W
R2	1-249-440-11	CARBON 82K 5%	1/4W	R60	1-249-429-11	CARBON 10K 5%	1/4W
R3	1-249-417-11	CARBON 1K 5%	1/4W	R61	1-249-431-11	CARBON 15K 5%	1/4W
R4	1-247-843-11	CARBON 3.3K 5%	1/4W	R62	1-215-905-11	METAL OXIDE 10 5%	3W F
R5	1-247-863-91	CARBON 22K 5%	1/4W	R63	1-215-905-11	METAL OXIDE 10 5%	3W F
R6	1-249-441-11	CARBON 100K 5%	1/4W	R64	1-215-905-11	METAL OXIDE 10 5%	3W F
R7	1-215-463-00	METAL 56K 1%	1/4W	R65	1-247-807-31	CARBON 100 5%	1/4W
R8	1-249-417-11	CARBON 1K 5%	1/4W	R66	1-247-903-00	CARBON 1M 5%	1/4W
R9	1-247-807-31	CARBON 100 5%	1/4W	R67	1-249-425-11	CARBON 4.7K 5%	1/4W
R10	1-249-429-11	CARBON 10K 5%	1/4W	R68	1-249-417-11	CARBON 1K 5%	1/4W
R11	1-249-436-11	CARBON 39K 5%	1/4W	R69	1-215-447-00	METAL 12K 1%	1/4W
R12	1-249-429-11	CARBON 10K 5%	1/4W	R70	1-215-456-00	METAL 30K 1%	1/4W
R13	1-249-429-11	CARBON 10K 5%	1/4W	R71	1-249-417-11	CARBON 1K 5%	1/4W
R14	1-215-457-00	METAL 33K 1%	1/4W	R72	1-247-807-31	CARBON 100 5%	1/4W
R15	1-249-417-11	CARBON 1K 5%	1/4W	R74	1-249-417-11	CARBON 1K 5%	1/4W
R16	1-247-843-11	CARBON 3.3K 5%	1/4W	R75	1-249-429-11	CARBON 10K 5%	1/4W
R17	1-215-469-00	METAL 100K 1%	1/4W	R76	1-215-455-00	METAL 27K 1%	1/4W
R18	1-215-475-00	METAL 180K 1%	1/4W	R77	1-215-447-00	METAL 12K 1%	1/4W

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
R78	1-215-445-00	METAL	10K	1%	1/4W		R137	1-215-895-11	METAL OXIDE	3.3K	5%	2W	F
R79	1-247-843-11	CARBON	3.3K	5%	1/4W		R138	1-215-895-11	METAL OXIDE	3.3K	5%	2W	F
R80	1-260-300-11	CARBON	4.7	5%	1/2W		R139	1-215-870-11	METAL OXIDE	1.5K	5%	1W	F
R81	1-260-300-11	CARBON	4.7	5%	1/2W		R140	1-249-425-11	CARBON	4.7K	5%	1/4W	
							R141	1-249-429-11	CARBON	10K	5%	1/4W	
R82	1-260-294-11	CARBON	1.5	5%	1/2W								
R83	1-260-300-11	CARBON	4.7	5%	1/2W		R142	1-249-429-11	CARBON	10K	5%	1/4W	
R84	1-247-807-31	CARBON	100	5%	1/4W		R143	1-249-429-11	CARBON	10K	5%	1/4W	
R85	1-249-417-11	CARBON	1K	5%	1/4W	F	R144	1-249-429-11	CARBON	10K	5%	1/4W	
R86	1-215-923-00	METAL OXIDE	10K	5%	3W	F	R145	1-249-441-11	CARBON	100K	5%	1/4W	
							R146	1-249-427-11	CARBON	6.8K	5%	1/4W	
R87	1-249-429-11	CARBON	10K	5%	1/4W								
R88	1-216-353-00	METAL OXIDE	2.2	5%	1W	F	R147	1-247-807-31	CARBON	100	5%	1/4W	
R89	1-247-843-11	CARBON	3.3K	5%	1/4W		R148	1-249-425-11	CARBON	4.7K	5%	1/4W	
R90	1-249-420-11	CARBON	1.8K	5%	1/4W	F	R149	1-216-381-11	METAL OXIDE	0.22	5%	3W	F
R91	1-249-441-11	CARBON	100K	5%	1/4W		R150	1-247-807-31	CARBON	100	5%	1/4W	
							R151	1-249-441-11	CARBON	100K	5%	1/4W	
R92	1-249-417-11	CARBON	1K	5%	1/4W								
R93	1-249-421-11	CARBON	2.2K	5%	1/4W		R152	1-249-429-11	CARBON	10K	5%	1/4W	
R94	1-215-457-00	METAL	33K	1%	1/4W		R153	1-202-549-00	SOLID	100	20%	1/2W	
R95	1-249-417-11	CARBON	1K	5%	1/4W	F	R154	1-249-432-11	CARBON	18K	5%	1/4W	
R96	1-215-421-00	METAL	1K	1%	1/4W		R156	1-202-838-00	SOLID	100K	20%	1/2W	
							R157	1-215-457-00	METAL	33K	1%	1/4W	
R97	1-215-453-00	METAL	22K	1%	1/4W								
R98	1-215-421-00	METAL	1K	1%	1/4W		R158	1-249-437-11	CARBON	47K	5%	1/4W	
R99	1-249-417-11	CARBON	1K	5%	1/4W		R159	1-249-429-11	CARBON	10K	5%	1/4W	
R100	1-215-892-11	METAL OXIDE	1K	5%	2W	F	R160	1-249-429-11	CARBON	10K	5%	1/4W	
R101	1-215-892-11	METAL OXIDE	1K	5%	2W	F	R161	1-249-429-11	CARBON	10K	5%	1/4W	
							R162	1-202-549-00	SOLID	100	20%	1/2W	
R102	1-247-807-31	CARBON	100	5%	1/4W								
R103	1-247-807-31	CARBON	100	5%	1/4W		R163	1-249-432-11	CARBON	18K	5%	1/4W	
R104	1-249-413-11	CARBON	470	5%	1/4W		R164	1-202-838-00	SOLID	100K	20%	1/2W	
R105	1-249-417-11	CARBON	1K	5%	1/4W		R165	1-249-437-11	CARBON	47K	5%	1/4W	
R106	1-215-922-11	METAL OXIDE	6.8K	5%	3W	F	R166	1-249-429-11	CARBON	10K	5%	1/4W	
							R167	1-202-549-00	SOLID	100	20%	1/2W	
R107	1-249-431-11	CARBON	15K	5%	1/4W								
R108	1-202-843-11	SOLID	270K	20%	1/2W		R168	1-249-429-11	CARBON	10K	5%	1/4W	
R109	1-202-843-11	SOLID	270K	20%	1/2W		R169	1-249-432-11	CARBON	18K	5%	1/4W	
R110	1-202-843-11	SOLID	270K	20%	1/2W		R170	1-202-838-00	SOLID	100K	20%	1/2W	
R111	1-249-441-11	CARBON	100K	5%	1/4W		R171	1-249-437-11	CARBON	47K	5%	1/4W	
							R172	1-249-429-11	CARBON	10K	5%	1/4W	
R112	1-215-421-00	METAL	1K	1%	1/4W								
R113	1-249-425-11	CARBON	4.7K	5%	1/4W		R173	1-215-461-00	METAL	47K	1%	1/4W	
R114	1-249-399-11	CARBON	33	5%	1/4W		R174						
R115	1-202-843-11	SOLID	270K	20%	1/2W			1-249-441-11	CARBON	100K	5%	1/4W	
R116	1-202-843-11	SOLID	270K	20%	1/2W		R175	1-249-441-11	CARBON	100K	5%	1/4W	
							R176	1-249-441-11	CARBON	100K	5%	1/4W	
R117	1-202-843-11	SOLID	270K	20%	1/2W		R177	1-249-429-11	CARBON	10K	5%	1/4W	F
R118	1-215-445-00	METAL	10K	1%	1/4W								
R119	1-249-424-11	CARBON	3.9K	5%	1/4W	F	R178	1-249-437-11	CARBON	47K	5%	1/4W	
R120	1-247-895-91	CARBON	470K	5%	1/4W		R179	1-249-429-11	CARBON	10K	5%	1/4W	
R121	1-249-437-11	CARBON	47K	5%	1/4W		R180	1-249-425-11	CARBON	4.7K	5%	1/4W	
							R181	1-249-431-11	CARBON	15K	5%	1/4W	
R122	1-249-421-11	CARBON	2.2K	5%	1/4W		R182	1-247-895-91	CARBON	470K	5%	1/4W	
R123	1-215-866-11	METAL OXIDE	330	5%	1W	F							
R124	1-249-425-11	CARBON	4.7K	5%	1/4W		R183	1-247-895-91	CARBON	470K	5%	1/4W	
R125	1-202-843-11	SOLID	270K	20%	1/2W		R184	1-247-895-91	CARBON	470K	5%	1/4W	
R126	1-202-843-11	SOLID	270K	20%	1/2W		R185	1-249-429-11	CARBON	10K	5%	1/4W	
							R186	1-249-429-11	CARBON	10K	5%	1/4W	
R127	1-202-843-11	SOLID	270K	20%	1/2W		R187	1-249-429-11	CARBON	10K	5%	1/4W	
R128	1-249-431-11	CARBON	15K	5%	1/4W								
R129	1-215-445-00	METAL	10K	1%	1/4W		R188	1-215-475-00	METAL	180K	1%	1/4W	
R130	1-249-420-11	CARBON	1.8K	5%	1/4W		R189	1-247-863-91	CARBON	22K	5%	1/4W	
R131	1-215-905-11	METAL OXIDE	10	5%	3W	F	R190	1-247-863-91	CARBON	22K	5%	1/4W	
							R191	1-247-843-11	CARBON	3.3K	5%	1/4W	
R132	1-249-429-11	CARBON	10K	5%	1/4W	F	R192	1-249-429-11	CARBON	10K	5%	1/4W	
R133	1-247-807-31	CARBON	100	5%	1/4W								
R134	1-249-429-11	CARBON	10K	5%	1/4W		R193	1-249-429-11	CARBON	10K	5%	1/4W	
R135	1-247-807-31	CARBON	100	5%	1/4W		R194	1-215-455-00	METAL	27K	1%	1/4W	
R136	1-215-895-11	METAL OXIDE	3.3K	5%	2W	F	R195	1-249-437-11	CARBON	47K	5%	1/4W	
							R196	1-247-843-11	CARBON	3.3K	5%	1/4W	

PA **PB** **QM** **YA**

The components identified by shading and marked Δ are critical for safety.
Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
R197	1-249-437-11	CARBON	47K 5% 1/4W	* A-1394-815-A	YA COMPLETE PC BOARD (Include YO Mounted PC Board) *****		
R198	1-247-843-11	CARBON	3.3K 5% 1/4W	* 1-526-660-21	SOCKET, IC (DP) 32P		
R199	1-249-437-11	CARBON	47K 5% 1/4W		< CAPACITOR >		
R200	1-247-843-11	CARBON	3.3K 5% 1/4W	C100	1-126-960-11	ELECT	1MF 20% 50V
R201	1-249-417-11	CARBON	1K 5% 1/4W	C101	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V
R202	1-249-413-11	CARBON	470 5% 1/4W	C102	1-163-037-11	CERAMIC CHIP	0.022MF 10% 50V
R1001	1-249-429-11	CARBON	10K 5% 1/4W	C103	1-163-031-11	CERAMIC CHIP	0.01MF 50V
R1002	1-247-871-11	CARBON	47K 5% 1/4W	C104	1-126-935-11	ELECT	470MF 20% 16V
R1003	1-247-871-11	CARBON	47K 5% 1/4W	C105	1-126-933-11	ELECT	100MF 20% 16V
< VARIABLE RESISTOR >				C106	1-163-031-11	CERAMIC CHIP	0.01MF 50V
\boxtimes RV1 Δ 1-238-789-11	RES, ADJ, CERMET 50K			C107	1-163-031-11	CERAMIC CHIP	0.01MF 50V
\boxtimes RV2 Δ 1-238-788-11	RES, ADJ, CERMET 20K			C108	1-163-031-11	CERAMIC CHIP	0.01MF 50V
< TRANSFORMER >				C109	1-163-231-11	CERAMIC CHIP	15PF 5% 50V
T1	1-429-275-11	TRANSFORMER, FERRITE (LOT)		C110	1-163-231-11	CERAMIC CHIP	15PF 5% 50V
T2	1-437-078-00	TRANSFORMER, HORIZONTAL DRIVE		C111	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V
T3	1-437-144-11	TRANSFORMER, FERRITE (HDT)		C112	1-126-933-11	ELECT	100MF 20% 16V
T4	1-424-290-11	TRANSFORMER, DRIVE		C113	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TEST PIN >				C114	1-126-933-11	ELECT	100MF 20% 16V
TP3	1-537-864-11	PIN, POST		C115	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP5	1-537-864-11	PIN, POST		C116	1-126-967-11	ELECT	47MF 20% 16V
TP6	1-537-864-11	PIN, POST		C117	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP7	1-537-864-11	PIN, POST		C118	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP8	1-537-864-11	PIN, POST		C119	1-126-967-11	ELECT	47MF 20% 16V
TP9	1-537-864-11	PIN, POST		C120	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP10	1-537-864-11	PIN, POST		C121	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP13	1-537-864-11	PIN, POST		C122	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP14	1-537-864-11	PIN, POST		C123	1-163-031-11	CERAMIC CHIP	0.01MF 50V
< CRYSTAL >				C124	1-163-031-11	CERAMIC CHIP	0.01MF 50V
X1	1-578-768-11	VIBLATOR, CERAMIC (495kHz)		C125	1-163-031-11	CERAMIC CHIP	0.01MF 50V
*****				C126	1-163-031-11	CERAMIC CHIP	0.01MF 50V
* A-1190-260-A PB MOUNTED PC BOARD				C127	1-126-967-11	ELECT	47MF 20% 16V
*****				C128	1-163-031-11	CERAMIC CHIP	0.01MF 50V
* 7-322-065-72 RUBBER, RTV (SE-9168) (130G)				C129	1-163-031-11	CERAMIC CHIP	0.01MF 50V
< CONNECTOR >				C130	1-163-031-11	CERAMIC CHIP	0.01MF 50V
CN241	* 1-564-506-11	PLUG, CONNECTOR 3P		C131	1-163-031-11	CERAMIC CHIP	0.01MF 50V
< TRANSFORMER >				C132	1-163-031-11	CERAMIC CHIP	0.01MF 50V
FBT10 Δ X-4034-325-1	TRANSFORMER ASSY, FLYBACK (NX3031/J1W)			C133	1-163-031-11	CERAMIC CHIP	0.01MF 50V
FBT11 Δ X-4034-326-1	TRANSFORMER ASSY, FLYBACK (NX3031/J1X)			C134	1-163-031-11	CERAMIC CHIP	0.01MF 50V
< NEON LAMP >				C135	1-163-031-11	CERAMIC CHIP	0.01MF 50V
NL10	1-519-108-XX	LAMP, NEON		C136	1-163-031-11	CERAMIC CHIP	0.01MF 50V
NL11	1-519-108-XX	LAMP, NEON		C137	1-163-031-11	CERAMIC CHIP	0.01MF 50V
*****				C138	1-163-031-11	CERAMIC CHIP	0.01MF 50V
* A-1270-375-A QM MOUNTED PC BOARD				C139	1-163-031-11	CERAMIC CHIP	0.01MF 50V
*****				C140	1-163-031-11	CERAMIC CHIP	0.01MF 50V
• The components identified by \boxtimes in this manual have				C141	1-126-960-11	ELECT	1MF 20% 50V
been carefully factory-selected for each set in order				C142	1-126-960-11	ELECT	1MF 20% 50V
to satisfy regulations regarding X-ray radiation.				C143	1-163-031-11	CERAMIC CHIP	0.01MF 50V
Should replacement be required, replace only with				C147	1-163-031-11	CERAMIC CHIP	0.01MF 50V
the value originally used.				C150	1-163-031-11	CERAMIC CHIP	0.01MF 50V
*****				C151	1-163-031-11	CERAMIC CHIP	0.01MF 50V
• The components identified by \boxtimes in this manual have				C152	1-163-031-11	CERAMIC CHIP	0.01MF 50V
been carefully factory-selected for each set in order				C153	1-163-031-11	CERAMIC CHIP	0.01MF 50V
to satisfy regulations regarding X-ray radiation.				C154	1-126-967-11	ELECT	47MF 20% 16V
Should replacement be required, replace only with				C155	1-126-935-11	ELECT	470MF 20% 16V
the value originally used.				C156	1-163-031-11	CERAMIC CHIP	0.01MF 50V

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
C157	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC124	8-759-186-39	IC TC74VHC74F	
C158	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC125	8-759-186-43	IC TC74VHC123AF	
C159	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC126	8-759-186-30	IC TC74VHC14F	
C160	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC127	8-759-185-82	IC TC74VHC153F(EL)	
C161	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	IC128	8-759-081-48	IC TC74VHC08F	
C162	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC129	8-759-186-29	IC TC74VHC11F	
C163	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC130	8-759-008-40	IC MC74HC4078F	
C164	1-126-967-11	ELECT	47MF 20% 16V	IC131	8-759-242-68	IC TC7W32F	
C165	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC132	8-759-242-68	IC TC7W32F	
C166	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC133	8-759-242-68	IC TC7W32F	
C167	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC134	8-759-031-84	IC SC7S04F	
C168	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC135	8-759-448-25	IC EPM7032QC44-12-IRE	
C169	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC136	8-759-242-76	IC TC7W08F	
C170	1-163-031-11	CERAMIC CHIP	0.01MF 50V	IC137	8-759-242-74	IC TC7W04F	
C171	1-126-967-11	ELECT	47MF 20% 16V			< JACK >	
C172	1-163-031-11	CERAMIC CHIP	0.01MF 50V	J103	1-507-562-00	JACK	
C173	1-163-031-11	CERAMIC CHIP	0.01MF 50V			< COIL >	
C174	1-163-031-11	CERAMIC CHIP	0.01MF 50V	L101	1-412-390-21	INDUCTOR CHIP	0μH
C175	1-163-031-11	CERAMIC CHIP	0.01MF 50V	L102	1-412-390-21	INDUCTOR CHIP	0μH
C176	1-126-967-11	ELECT	47MF 20% 16V	L103	1-412-533-21	INDUCTOR	47μH
C177	1-163-031-11	CERAMIC CHIP	0.01MF 50V	L104	1-412-533-21	INDUCTOR	47μH
C178	1-163-251-11	CERAMIC CHIP	100PF 5% 50V	L105	1-412-390-21	INDUCTOR CHIP	0μH
C179	1-163-121-00	CERAMIC CHIP	150PF 5% 50V	L106	1-412-390-21	INDUCTOR CHIP	0μH
C180	1-163-031-11	CERAMIC CHIP	0.01MF 50V	L107	1-412-390-21	INDUCTOR CHIP	0μH
C181	1-163-031-11	CERAMIC CHIP	0.01MF 50V			< RESISTOR >	
		< DIODE >		R101	1-216-073-00	METAL GLAZE	10K 5% 1/10W
D101	8-719-104-34	DIODE 1S2836		R102	1-216-057-00	METAL GLAZE	2.2K 5% 1/10W
D102	8-719-104-34	DIODE 1S2836		R103	1-216-295-91	CONDUCTOR, CHIP (2012)	
D103	8-719-109-54	DIODE RD2.2ESB2		R104	1-216-073-00	METAL GLAZE	10K 5% 1/10W
D104	8-719-109-93	DIODE RD6.2ESB2		R105	1-216-025-91	METAL GLAZE	100 5% 1/10W
D105	8-719-109-54	DIODE RD2.2ESB2		R106	1-216-025-91	METAL GLAZE	100 5% 1/10W
		< FILTER >		R107	1-216-025-91	METAL GLAZE	100 5% 1/10W
FL104	1-239-899-21	FILTER, CHIP EMI		R108	1-216-073-00	METAL GLAZE	10K 5% 1/10W
FL105	1-239-899-21	FILTER, CHIP EMI		R109	1-216-073-00	METAL GLAZE	10K 5% 1/10W
		< IC >		R110	1-216-045-00	METAL GLAZE	680 5% 1/10W
IC100	8-759-162-80	IC MM1170BFB		R111	1-216-073-00	METAL GLAZE	10K 5% 1/10W
IC101	8-759-421-40	IC MB90091APF-114		R112			
IC102	8-759-461-43	IC HD6433257A44F			1-216-025-91	METAL GLAZE	100 5% 1/10W
IC105	8-759-144-82	IC μPC2405HF		R113	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC106	8-759-430-28	IC HM6264BLFP-10LTZ		R116	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC108	8-759-445-10	IC CY7C136-55JC-TEL		R117	1-216-001-00	METAL GLAZE	10 5% 1/10W
IC109	8-759-430-23	IC UPD65806GD-064-LML		R118	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC110	8-759-097-52	IC SN75123NS		R119	1-216-295-91	CONDUCTOR, CHIP (2012)	
IC111	8-759-097-52	IC SN75123NS		R121	1-216-073-00	METAL GLAZE	10K 5% 1/10W
IC112	8-759-394-03	IC ICS1522MT		R122	1-216-295-91	CONDUCTOR, CHIP (2012)	
IC113	8-759-430-33	IC MC10H640FNR2		R123	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC114	8-759-994-67	IC MB86022PF		R125	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC115	8-759-387-78	IC TC551664AJ-20		R126	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC116	8-759-387-78	IC TC551664AJ-20		R127	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC117	8-759-185-78	IC TC74VHC132F(EL)		R128	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC118	8-759-240-41	IC TC74HC107AP		R129	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC120	8-759-186-30	IC TC74VHC14F		R130	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC121	8-759-186-54	IC TC74VHC164F		R131	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC122	8-759-185-82	IC TC74VHC153F(EL)		R132	1-216-025-91	METAL GLAZE	100 5% 1/10W
IC123	8-759-186-38	IC TC74VHC32F		R133	1-216-025-91	METAL GLAZE	100 5% 1/10W
				R134	1-216-025-91	METAL GLAZE	100 5% 1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R135	1-216-025-91	METAL GLAZE	100	5%	1/10W	R195	1-216-025-91	METAL GLAZE	100	5%	1/10W
R136	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R137	1-216-025-91	METAL GLAZE	100	5%	1/10W	R196	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R138	1-216-025-91	METAL GLAZE	100	5%	1/10W	R197	1-216-025-91	METAL GLAZE	100	5%	1/10W
R139	1-216-025-91	METAL GLAZE	100	5%	1/10W	R198	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R199	1-216-025-91	METAL GLAZE	100	5%	1/10W
R140	1-216-025-91	METAL GLAZE	100	5%	1/10W	R200	1-216-025-91	METAL GLAZE	100	5%	1/10W
R141	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R142	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R201	1-216-025-91	METAL GLAZE	100	5%	1/10W
R143	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R202	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R144	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R203	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R204	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R145	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R205	1-216-025-91	METAL GLAZE	100	5%	1/10W
R146	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R147	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R206	1-216-025-91	METAL GLAZE	100	5%	1/10W
R148	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R207	1-216-025-91	METAL GLAZE	100	5%	1/10W
R149	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R208	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R209	1-216-025-91	METAL GLAZE	100	5%	1/10W
R150	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R210	1-216-025-91	METAL GLAZE	100	5%	1/10W
R151	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R152	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R211	1-216-025-91	METAL GLAZE	100	5%	1/10W
R153	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R212	1-216-295-91	CONDUCTOR, CHIP (2012)			
R154	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R213	1-216-295-91	CONDUCTOR, CHIP (2012)			
						R214	1-216-295-91	CONDUCTOR, CHIP (2012)			
R155	1-216-025-91	METAL GLAZE	100	5%	1/10W	R215	1-216-025-91	METAL GLAZE	100	5%	1/10W
R156	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R157	1-216-025-91	METAL GLAZE	100	5%	1/10W	R216	1-216-025-91	METAL GLAZE	100	5%	1/10W
R158	1-216-025-91	METAL GLAZE	100	5%	1/10W	R217	1-216-025-91	METAL GLAZE	100	5%	1/10W
R159	1-216-025-91	METAL GLAZE	100	5%	1/10W	R218	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R219	1-216-025-91	METAL GLAZE	100	5%	1/10W
R160	1-216-025-91	METAL GLAZE	100	5%	1/10W	R220	1-216-025-91	METAL GLAZE	100	5%	1/10W
R161	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R162	1-216-025-91	METAL GLAZE	100	5%	1/10W	R221	1-216-025-91	METAL GLAZE	100	5%	1/10W
R163	1-216-025-91	METAL GLAZE	100	5%	1/10W	R222	1-216-025-91	METAL GLAZE	100	5%	1/10W
R164	1-216-025-91	METAL GLAZE	100	5%	1/10W	R223	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R224	1-216-025-91	METAL GLAZE	100	5%	1/10W
R165	1-216-025-91	METAL GLAZE	100	5%	1/10W	R225	1-216-295-91	CONDUCTOR, CHIP (2012)			
R166	1-216-025-91	METAL GLAZE	100	5%	1/10W						
R167	1-216-025-91	METAL GLAZE	100	5%	1/10W	R226	1-216-025-91	METAL GLAZE	100	5%	1/10W
R168	1-216-025-91	METAL GLAZE	100	5%	1/10W	R227	1-216-295-91	CONDUCTOR, CHIP (2012)			
R169	1-216-025-91	METAL GLAZE	100	5%	1/10W	R228	1-216-295-91	CONDUCTOR, CHIP (2012)			
						R229	1-216-295-91	CONDUCTOR, CHIP (2012)			
R170	1-216-025-91	METAL GLAZE	100	5%	1/10W	R230	1-216-295-91	CONDUCTOR, CHIP (2012)			
R171	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R173	1-216-295-91	CONDUCTOR, CHIP (2012)				R231	1-216-025-91	METAL GLAZE	100	5%	1/10W
R174	1-249-401-11	CARBON	47	5%	1/4W	R232	1-216-025-91	METAL GLAZE	100	5%	1/10W
R175	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R233	1-216-025-91	METAL GLAZE	100	5%	1/10W
						R234	1-216-025-91	METAL GLAZE	100	5%	1/10W
R176	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R235	1-216-025-91	METAL GLAZE	100	5%	1/10W
R177	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R178	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R236	1-216-025-91	METAL GLAZE	100	5%	1/10W
R179	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R237	1-216-025-91	METAL GLAZE	100	5%	1/10W
R180	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R238	1-216-105-91	METAL GLAZE	220K	5%	1/10W
						R239	1-216-025-91	METAL GLAZE	100	5%	1/10W
R181	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R240	1-216-025-91	METAL GLAZE	100	5%	1/10W
R182	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R183	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R241	1-216-295-91	CONDUCTOR, CHIP (2012)			
R184	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R242	1-216-001-00	METAL GLAZE	10	5%	1/10W
R185	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R243	1-216-295-91	CONDUCTOR, CHIP (2012)			
						R244	1-216-295-91	CONDUCTOR, CHIP (2012)			
R186	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R245	1-216-295-91	CONDUCTOR, CHIP (2012)			
R187	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R188	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R246	1-216-295-91	CONDUCTOR, CHIP (2012)			
R189	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R247	1-216-001-00	METAL GLAZE	10	5%	1/10W
R190	1-216-025-91	METAL GLAZE	100	5%	1/10W	R248	1-216-644-11	METAL CHIP	510	0.5%	1/10W
						R249	1-216-001-00	METAL GLAZE	10	5%	1/10W
R191	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W	R250	1-216-001-00	METAL GLAZE	10	5%	1/10W
R192	1-216-073-00	METAL GLAZE	10K	5%	1/10W						
R193	1-216-025-91	METAL GLAZE	100	5%	1/10W	R251	1-216-047-91	METAL GLAZE	820	5%	1/10W
R194	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R252	1-216-023-00	METAL GLAZE	82	5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
R253	1-216-047-91	METAL GLAZE	820 5% 1/10W	R335	1-216-025-91	METAL GLAZE	100 5% 1/10W
R254	1-216-023-00	METAL GLAZE	82 5% 1/10W	R336	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R256	1-216-295-91	CONDUCTOR, CHIP (2012)		R337	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R258	1-216-295-91	CONDUCTOR, CHIP (2012)		R338	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R259	1-216-295-91	CONDUCTOR, CHIP (2012)		R339	1-216-001-00	METAL GLAZE	10 5% 1/10W
R260	1-216-295-91	CONDUCTOR, CHIP (2012)		R340	1-216-001-00	METAL GLAZE	10 5% 1/10W
R261	1-216-295-91	CONDUCTOR, CHIP (2012)		R341	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R264	1-216-001-00	METAL GLAZE	10 5% 1/10W	R342	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R265	1-216-049-91	METAL GLAZE	1K 5% 1/10W	R343	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R266	1-216-025-91	METAL GLAZE	100 5% 1/10W	R344	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R267	1-216-295-91	CONDUCTOR, CHIP (2012)		R345	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R268	1-216-089-91	METAL GLAZE	47K 5% 1/10W	R346	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R269	1-216-073-00	METAL GLAZE	10K 5% 1/10W	R347	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R270	1-216-073-00	METAL GLAZE	10K 5% 1/10W	R348	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R272	1-216-073-00	METAL GLAZE	10K 5% 1/10W	R349	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R273	1-216-295-91	CONDUCTOR, CHIP (2012)		R358	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R275	1-216-001-00	METAL GLAZE	10 5% 1/10W	R359	1-216-001-00	METAL GLAZE	10 5% 1/10W
R276	1-216-001-00	METAL GLAZE	10 5% 1/10W	R360	1-216-025-91	METAL GLAZE	100 5% 1/10W
R280	1-216-001-00	METAL GLAZE	10 5% 1/10W	R361	1-216-001-00	METAL GLAZE	10 5% 1/10W
R281	1-216-049-91	METAL GLAZE	1K 5% 1/10W	R362	1-216-097-91	METAL GLAZE	100K 5% 1/10W
R282	1-216-047-91	METAL GLAZE	820 5% 1/10W	R364	1-216-025-91	METAL GLAZE	100 5% 1/10W
R283	1-216-025-91	METAL GLAZE	100 5% 1/10W	R365	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R284	1-216-073-00	METAL GLAZE	10K 5% 1/10W	< TERMINAL BOARD >			
R285	1-216-073-00	METAL GLAZE	10K 5% 1/10W	TB101	* 1-694-207-11	TERMINAL BOARD ASSY, I/O	
R286	1-216-073-00	METAL GLAZE	10K 5% 1/10W	< TEST PIN >			
R288	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP100	* 1-535-877-22	CHIP, CHECKER	
R289	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP101	* 1-535-877-22	CHIP, CHECKER	
R290	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP102	* 1-535-877-22	CHIP, CHECKER	
R291	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP103	* 1-535-877-22	CHIP, CHECKER	
R292	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP104	* 1-535-877-22	CHIP, CHECKER	
R293	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP105	* 1-535-877-22	CHIP, CHECKER	
R294	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP106	* 1-535-877-22	CHIP, CHECKER	
R295	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP107	* 1-535-877-22	CHIP, CHECKER	
R296	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP108	* 1-535-877-22	CHIP, CHECKER	
R303	1-216-295-91	CONDUCTOR, CHIP (2012)		TP109	* 1-535-877-22	CHIP, CHECKER	
R304	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP110	* 1-535-877-22	CHIP, CHECKER	
R305	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP111	* 1-535-877-22	CHIP, CHECKER	
R306	1-216-073-00	METAL GLAZE	10K 5% 1/10W	TP112	* 1-535-877-22	CHIP, CHECKER	
R307	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP113	* 1-535-877-22	CHIP, CHECKER	
R310	1-216-295-91	CONDUCTOR, CHIP (2012)		TP114	* 1-535-877-22	CHIP, CHECKER	
R311	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP115	* 1-535-877-22	CHIP, CHECKER	
R312	1-216-073-00	METAL GLAZE	10K 5% 1/10W	TP116	* 1-535-877-22	CHIP, CHECKER	
R313	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP117	* 1-535-877-22	CHIP, CHECKER	
R314	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP118	* 1-535-877-22	CHIP, CHECKER	
R315	1-216-073-00	METAL GLAZE	10K 5% 1/10W	TP119	* 1-535-877-22	CHIP, CHECKER	
R316	1-216-073-00	METAL GLAZE	10K 5% 1/10W	TP120	* 1-535-877-22	CHIP, CHECKER	
R317	1-216-295-91	CONDUCTOR, CHIP (2012)		TP121	* 1-535-877-22	CHIP, CHECKER	
R319	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP122	* 1-535-877-22	CHIP, CHECKER	
R325	1-216-001-00	METAL GLAZE	10 5% 1/10W	TP123	* 1-535-877-22	CHIP, CHECKER	
R326	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP124	* 1-535-877-22	CHIP, CHECKER	
R327	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP125	* 1-535-877-22	CHIP, CHECKER	
R328	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP126	* 1-535-877-22	CHIP, CHECKER	
R329	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP127	* 1-535-877-22	CHIP, CHECKER	
R330	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP128	* 1-535-877-22	CHIP, CHECKER	
R331	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP129	* 1-535-877-22	CHIP, CHECKER	
R332	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP130	* 1-535-877-22	CHIP, CHECKER	
R333	1-216-025-91	METAL GLAZE	100 5% 1/10W	TP131	* 1-535-877-22	CHIP, CHECKER	
R334	1-216-025-91	METAL GLAZE	100 5% 1/10W				

YA

YB

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
TP132	* 1-535-877-22	CHIP, CHECKER		C124	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP133	* 1-535-877-22	CHIP, CHECKER		C125	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP134	* 1-535-877-22	CHIP, CHECKER		C126	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP135	* 1-535-877-22	CHIP, CHECKER		C127	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP136	* 1-535-877-22	CHIP, CHECKER		C128	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP137	* 1-535-877-22	CHIP, CHECKER		C129	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP138	* 1-535-877-22	CHIP, CHECKER		C130	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP139	* 1-535-877-22	CHIP, CHECKER		C131	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP140	* 1-535-877-22	CHIP, CHECKER		C132	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP141	* 1-535-877-22	CHIP, CHECKER		C133	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP142	* 1-535-877-22	CHIP, CHECKER		C134	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP143	* 1-535-877-22	CHIP, CHECKER		C135	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP144	* 1-535-877-22	CHIP, CHECKER		C136	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP145	* 1-535-877-22	CHIP, CHECKER		C137	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP146	* 1-535-877-22	CHIP, CHECKER		C138	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP147	* 1-535-877-22	CHIP, CHECKER		C139	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP148	* 1-535-877-22	CHIP, CHECKER		C140	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP149	* 1-535-877-22	CHIP, CHECKER		C141	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP150	* 1-535-877-22	CHIP, CHECKER		C142	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP152	* 1-535-877-22	CHIP, CHECKER		C143	1-163-031-11	CERAMIC CHIP	0.01MF 50V
TP153	* 1-535-877-22	CHIP, CHECKER		C144	1-163-031-11	CERAMIC CHIP	0.01MF 50V
< CRYSTAL >				C145	1-163-031-11	CERAMIC CHIP	0.01MF 50V
X101	1-760-040-11	VIBRATOR, CRYSTAL		C146	1-163-031-11	CERAMIC CHIP	0.01MF 50V
*****				C147	1-136-165-00	FILM	0.1MF 5% 50V
				C148	1-163-031-11	CERAMIC CHIP	0.01MF 50V
				C149	1-163-031-11	CERAMIC CHIP	0.01MF 50V
* A-1394-816-A YB COMPLETE PC BOARD				C150	1-163-031-11	CERAMIC CHIP	0.01MF 50V
*****				C151	1-124-584-00	ELECT	100MF 20% 10V
				C152	1-124-584-00	ELECT	100MF 20% 10V
* 1-526-659-00 SOCKET, IC (DP) 28P				C153	1-163-031-11	CERAMIC CHIP	0.01MF 50V
* 1-526-660-21 SOCKET, IC (DP) 32P				C154	1-163-031-11	CERAMIC CHIP	0.01MF 50V
* 7-322-065-72 RUBBER, RTV (SE-9168) (130G)				C155	1-126-157-11	ELECT	10MF 20% 16V
7-685-646-79 SCREW +BVTP 3X8 TYPE2 N-S				C156	1-165-319-11	CERAMIC CHIP	0.1MF 50V
< CAPACITOR >				C157	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C100	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C158	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C101	1-163-231-11	CERAMIC CHIP	15PF 5% 50V	C159	1-163-239-11	CERAMIC CHIP	33PF 5% 50V
C102	1-163-231-11	CERAMIC CHIP	15PF 5% 50V	C160	1-163-239-11	CERAMIC CHIP	33PF 5% 50V
C103	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	C161	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V
C104	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C200	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C105	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V	C201	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C106	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C202	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C107	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C203	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C108	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C204	1-165-319-11	CERAMIC CHIP	0.1MF 50V
C109	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C206	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C110	1-165-319-11	CERAMIC CHIP	0.1MF 50V	C207	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C111	1-124-589-11	ELECT	47MF 20% 16V	C209	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C112	1-124-589-11	ELECT	47MF 20% 16V	C300	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C113	1-124-584-00	ELECT	100MF 20% 10V	C301	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C114	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C302	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C115	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C303	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C116	1-165-319-11	CERAMIC CHIP	0.1MF 50V	C304	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C117	1-126-157-11	ELECT	10MF 20% 16V	C305	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C118	1-126-157-11	ELECT	10MF 20% 16V	C306	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C119	1-126-160-11	ELECT	1MF 20% 50V	C307	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V
C120	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C308	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C121	1-124-589-11	ELECT	47MF 20% 16V	C309	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V
C122	1-165-319-11	CERAMIC CHIP	0.1MF 50V	C310	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C123	1-163-031-11	CERAMIC CHIP	0.01MF 50V	C311	1-163-031-11	CERAMIC CHIP	0.01MF 50V

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK
C312	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D107	8-719-801-78	DIODE 1SS184	
C313	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D108	8-719-974-51	DIODE SB20-03P	
C314	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D109	8-719-801-78	DIODE 1SS184	
C315	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D110	8-719-801-78	DIODE 1SS184	
C316	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D111	8-719-801-78	DIODE 1SS184	
C317	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D112	8-719-801-78	DIODE 1SS184	
C318	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D113	8-719-801-78	DIODE 1SS184	
C319	1-163-031-11	CERAMIC CHIP	0.01MF	50V		D114	8-719-801-78	DIODE 1SS184	
C320	1-163-231-11	CERAMIC CHIP	15PF	5%	50V	D115	8-719-801-78	DIODE 1SS184	
C321	1-163-231-11	CERAMIC CHIP	15PF	5%	50V	D116	8-719-801-78	DIODE 1SS184	
C322	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D117	8-719-801-78	DIODE 1SS184	
C323	1-163-231-11	CERAMIC CHIP	15PF	5%	50V	D118	8-719-801-78	DIODE 1SS184	
C324	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D119	8-719-801-78	DIODE 1SS184	
C325	1-163-227-11	CERAMIC CHIP	10PF	0.5PF	50V	D120	8-719-801-78	DIODE 1SS184	
C326	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D121	8-719-801-78	DIODE 1SS184	
C327	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D122	8-719-404-49	DIODE MA111	
C328	1-163-099-00	CERAMIC CHIP	18PF	5%	50V	D123	8-719-404-49	DIODE MA111	
C329	1-163-227-11	CERAMIC CHIP	10PF	0.5PF	50V	D200	8-719-109-93	DIODE RD6.2ESB2	
C330	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	D201	8-719-109-93	DIODE RD6.2ESB2	
C331	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D202	8-719-109-93	DIODE RD6.2ESB2	
C332	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D203	8-719-106-17	DIODE RD6.8M-B2	
C333	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D301	8-719-801-78	DIODE 1SS184	
C334	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V	D400	8-719-106-08	DIODE RD6.2M-B2	
C335	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D401	8-719-106-08	DIODE RD6.2M-B2	
C336	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D402	8-719-105-82	DIODE RD5.1M-B2	
C337	1-163-031-11	CERAMIC CHIP	0.01MF		50V	D403	8-719-105-82	DIODE RD5.1M-B2	
C338	1-164-232-11	CERAMIC CHIP	0.01MF	10%	50V	D404	8-719-105-82	DIODE RD5.1M-B2	
C339	1-163-121-00	CERAMIC CHIP	150PF	5%	50V			< FILTER >	
C340	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	FL102	1-239-899-21	FILTER, CHIP EMI	
C341	1-163-031-11	CERAMIC CHIP	0.01MF		50V	FL103	1-239-899-21	FILTER, CHIP EMI	
C342	1-163-251-11	CERAMIC CHIP	100PF	5%	50V			< IC >	
C343	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	IC100	8-759-421-41	IC HD6433337WA08F	
C344	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	IC101	8-759-162-80	IC MM1170BFB	
C345	1-163-031-11	CERAMIC CHIP	0.01MF		50V	IC102	8-759-460-36	IC PC74HCT08D-T	
C400	1-163-031-11	CERAMIC CHIP	0.01MF		50V	IC103	8-759-269-12	IC SN74HCT08ANS	
C401	1-163-031-11	CERAMIC CHIP	0.01MF		50V	IC104	8-759-100-93	IC μPC393G2	
C403	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	IC105	8-759-360-79	IC TC7W14F	
C404	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	IC107	8-759-430-28	IC HM6264BLFP-10I.TZ	
C405	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	IC108	8-759-430-34	IC MAX762CSA-TE2	
C406	1-126-157-11	ELECT	10MF	20%	16V	IC109	8-752-383-22	IC CXD108-146Q	
C407	1-163-031-11	CERAMIC CHIP	0.01MF		50V	IC110	8-759-259-77	IC PQ20VZ5U	
C408	1-163-031-11	CERAMIC CHIP	0.01MF		50V	IC111	8-759-237-71	IC TC74HC573AF(EL)	
C409	1-163-031-11	CERAMIC CHIP	0.01MF		50V	IC113	8-759-979-68	IC LM2931Z-5.0	
C410	1-163-031-11	CERAMIC CHIP	0.01MF		50V	IC114	8-759-100-93	IC μPC393G2	
C411	1-163-227-11	CERAMIC CHIP	10PF	0.5PF	50V	IC115	8-759-233-02	IC TC74HC273AF	
		< CONNECTOR >				IC116	8-759-461-11	IC UPD17215GT-723	
CN454	* 1-564-507-11	PLUG, CONNECTOR 4P				IC200	8-759-184-64	IC TC4W66FU	
CN455	* 1-564-516-11	PLUG, CONNECTOR 13P				IC201	8-759-443-08	IC TC7W241FU-TE12R	
		< DIODE >				IC300	8-759-235-31	IC TC74HC14AF(EL)	
D100	8-719-801-78	DIODE 1SS184				IC301	8-759-925-85	IC SN74HC32ANS	
D101	8-719-801-78	DIODE 1SS184				IC302	8-759-435-39	IC HN58C1001P-15	
D102	8-719-801-78	DIODE 1SS184				IC303	8-759-925-90	IC SN74HC74ANS	
D103	8-719-510-02	DIODE D1NS4				IC305	8-759-445-10	IC CY7C136-55JC-TEL	
D104	8-719-106-17	DIODE RD6.8M-B2				IC306	8-759-035-93	IC SC7S32F	
D105	8-719-801-78	DIODE 1SS184				IC307	8-759-035-93	IC SC7S32F	
D106	8-719-801-78	DIODE 1SS184				IC308	8-759-446-72	IC M48Z128Y-120PM1	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
IC309	8-759-430-28	IC HM6264BLFP-10LTZ		R128	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC310	8-759-926-12	IC SN74HC139ANS		R129	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC311	8-752-383-22	IC CXD108-146Q		R130	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC312	8-759-443-08	IC TC7W241FU-TE12R		R131	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC313	8-759-421-41	IC HD6433337WA08F		R132	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC314	8-759-984-58	IC MB671469PF		R133	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC315	8-759-984-59	IC MB654842UPF		R134	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC316	8-759-162-80	IC MM1170BFB		R135	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC317	8-752-072-94	IC CXA1875AM-T4		R136	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC318	8-759-239-55	IC TC74HC123AF		R137	1-215-863-11	METAL OXIDE 100 5%	1W F
IC319	8-759-926-18	IC SN74HC157ANS		R138	1-216-699-11	METAL CHIP 100K 0.5%	1/10W
IC320	8-759-239-55	IC TC74HC123AF		R139	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC321	8-759-242-76	IC TC7W08F		R140	1-216-073-00	METAL GLAZE 10K 5%	1/10W
IC322	8-759-062-66	IC TC7S66F		R141	1-216-687-11	METAL CHIP 33K 0.5%	1/10W
IC400	8-759-011-65	IC MC74HC4053F		R142	1-216-603-11	METAL CHIP 10 0.5%	1/10W
< COIL >				R144	1-216-073-00	METAL GLAZE 10K 5%	1/10W
L100	1-412-533-21	INDUCTOR 47μH		R145	1-216-073-00	METAL GLAZE 10K 5%	1/10W
L101	1-412-533-21	INDUCTOR 47μH		R146	1-216-295-91	CONDUCTOR, CHIP (2012)	
L102	1-412-533-21	INDUCTOR 47μH		R147	1-216-073-00	METAL GLAZE 10K 5%	1/10W
< TRANSISTOR >				R148	1-216-049-91	METAL GLAZE 1K 5%	1/10W
Q100	8-729-027-59	TRANSISTOR DTC144EKA-T146		R149	1-216-089-91	METAL GLAZE 47K 5%	1/10W
Q101	8-729-027-59	TRANSISTOR DTC144EKA-T146		R150	1-216-667-11	METAL CHIP 4.7K 0.5%	1/10W
Q102	8-729-027-59	TRANSISTOR DTC144EKA-T146		R152	1-216-655-11	METAL CHIP 1.5K 0.5%	1/10W
Q103	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R154	1-216-073-00	METAL GLAZE 10K 5%	1/10W
Q104	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R155	1-216-073-00	METAL GLAZE 10K 5%	1/10W
Q105	8-729-027-59	TRANSISTOR DTC144EKA-T146		R156	1-216-073-00	METAL GLAZE 10K 5%	1/10W
Q202	8-729-216-22	TRANSISTOR 2SA1162-G		R157	1-216-073-00	METAL GLAZE 10K 5%	1/10W
Q300	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R158	1-216-073-00	METAL GLAZE 10K 5%	1/10W
Q301	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R159	1-216-073-00	METAL GLAZE 10K 5%	1/10W
Q400	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L		R160	1-216-073-00	METAL GLAZE 10K 5%	1/10W
< RESISTOR >				R161	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R101	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R162	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R102	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R163	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R103	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R164	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R104	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R165	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R105	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R166	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R107	1-216-057-00	METAL GLAZE 2.2K 5%	1/10W	R167	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R108	1-216-057-00	METAL GLAZE 2.2K 5%	1/10W	R168	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R109	1-216-057-00	METAL GLAZE 2.2K 5%	1/10W	R169	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R110	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R170	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R111	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R171	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R112	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R172	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R113	1-216-025-91	METAL GLAZE 100 5%	1/10W	R173	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R114	1-216-025-91	METAL GLAZE 100 5%	1/10W	R174	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R115	1-216-295-91	CONDUCTOR, CHIP (2012)		R175	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R117	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R176	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R118	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R177	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R119	1-216-037-00	METAL GLAZE 330 5%	1/10W	R178	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R120	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R179	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R121	1-216-025-91	METAL GLAZE 100 5%	1/10W	R180	1-216-295-91	CONDUCTOR, CHIP (2012)	
R122	1-216-049-91	METAL GLAZE 1K 5%	1/10W	R181	1-247-855-31	CARBON 10K 5%	1/4W
R123	1-216-081-00	METAL GLAZE 22K 5%	1/10W	R182	1-249-432-11	CARBON 18K 5%	1/4W
R124	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R183	1-249-441-11	CARBON 100K 5%	1/4W
R125	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R184	1-249-441-11	CARBON 100K 5%	1/4W
R126	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R191	1-216-073-00	METAL GLAZE 10K 5%	1/10W
R127	1-216-073-00	METAL GLAZE 10K 5%	1/10W	R192	1-216-073-00	METAL GLAZE 10K 5%	1/10W
				R193	1-216-295-91	CONDUCTOR, CHIP (2012)	
				R194	1-216-295-91	CONDUCTOR, CHIP (2012)	
				R195	1-216-025-91	METAL GLAZE 100 5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
R196	1-216-025-91	METAL GLAZE	100	5%	1/10W	R257	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R197	1-216-025-91	METAL GLAZE	100	5%	1/10W	R258	1-216-049-91	METAL GLAZE	1K	5%	1/10W
R198	1-216-025-91	METAL GLAZE	100	5%	1/10W	R259	1-216-025-91	METAL GLAZE	100	5%	1/10W
R199	1-216-025-91	METAL GLAZE	100	5%	1/10W	R301	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R201	1-216-025-91	METAL GLAZE	100	5%	1/10W	R302	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R202	1-216-025-91	METAL GLAZE	100	5%	1/10W	R303	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R203	1-216-025-91	METAL GLAZE	100	5%	1/10W	R304	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R204	1-216-025-91	METAL GLAZE	100	5%	1/10W	R305	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R205	1-216-025-91	METAL GLAZE	100	5%	1/10W	R306	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R206	1-216-025-91	METAL GLAZE	100	5%	1/10W	R307	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R207	1-216-025-91	METAL GLAZE	100	5%	1/10W	R308	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R208	1-216-025-91	METAL GLAZE	100	5%	1/10W	R309	1-216-025-91	METAL GLAZE	100	5%	1/10W
R209	1-216-025-91	METAL GLAZE	100	5%	1/10W	R310	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R210	1-216-025-91	METAL GLAZE	100	5%	1/10W	R311	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R211	1-216-025-91	METAL GLAZE	100	5%	1/10W	R312	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R212	1-216-025-91	METAL GLAZE	100	5%	1/10W	R313	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R213	1-216-025-91	METAL GLAZE	100	5%	1/10W	R314	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R214	1-216-025-91	METAL GLAZE	100	5%	1/10W	R316	1-216-055-00	METAL GLAZE	1.8K	5%	1/10W
R215	1-216-025-91	METAL GLAZE	100	5%	1/10W	R318	1-216-025-91	METAL GLAZE	100	5%	1/10W
R216	1-216-025-91	METAL GLAZE	100	5%	1/10W	R319	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W
R217	1-216-025-91	METAL GLAZE	100	5%	1/10W	R320	1-216-121-91	METAL GLAZE	1M	5%	1/10W
R218	1-216-025-91	METAL GLAZE	100	5%	1/10W	R321	1-216-121-91	METAL GLAZE	1M	5%	1/10W
R219	1-216-025-91	METAL GLAZE	100	5%	1/10W	R322	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R220	1-216-025-91	METAL GLAZE	100	5%	1/10W	R323	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R221	1-216-025-91	METAL GLAZE	100	5%	1/10W	R324	1-216-047-91	METAL GLAZE	820	5%	1/10W
R222	1-216-025-91	METAL GLAZE	100	5%	1/10W	R325	1-216-047-91	METAL GLAZE	820	5%	1/10W
R223	1-216-025-91	METAL GLAZE	100	5%	1/10W	R326	1-216-047-91	METAL GLAZE	820	5%	1/10W
R224	1-216-025-91	METAL GLAZE	100	5%	1/10W	R327	1-216-047-91	METAL GLAZE	820	5%	1/10W
R225	1-216-025-91	METAL GLAZE	100	5%	1/10W	R328	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R226	1-216-025-91	METAL GLAZE	100	5%	1/10W	R329	1-216-073-00	METAL GLAZE	10K	5%	1/10W
R227	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R330	1-216-047-91	METAL GLAZE	820	5%	1/10W
R228	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R331	1-216-105-91	METAL GLAZE	220K	5%	1/10W
R229	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R332	1-216-675-11	METAL CHIP	10K	0.5%	1/10W
R230	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R333	1-216-047-91	METAL GLAZE	820	5%	1/10W
R231	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R334	1-216-047-91	METAL GLAZE	820	5%	1/10W
R232	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R335	1-216-047-91	METAL GLAZE	820	5%	1/10W
R233	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R336	1-216-113-00	METAL GLAZE	470K	5%	1/10W
R234	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R337	1-216-047-91	METAL GLAZE	820	5%	1/10W
R235	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R338	1-216-025-91	METAL GLAZE	100	5%	1/10W
R236	1-216-075-00	METAL GLAZE	12K	5%	1/10W	R339	1-216-025-91	METAL GLAZE	100	5%	1/10W
R237	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R340	1-216-025-91	METAL GLAZE	100	5%	1/10W
R239	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R341	1-216-025-91	METAL GLAZE	100	5%	1/10W
R240	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R342	1-216-025-91	METAL GLAZE	100	5%	1/10W
R241	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R343	1-216-025-91	METAL GLAZE	100	5%	1/10W
R242	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R344	1-216-025-91	METAL GLAZE	100	5%	1/10W
R243	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R345	1-216-025-91	METAL GLAZE	100	5%	1/10W
R244	1-216-081-00	METAL GLAZE	22K	5%	1/10W	R346	1-216-025-91	METAL GLAZE	100	5%	1/10W
R245	1-216-085-00	METAL GLAZE	33K	5%	1/10W	R348	1-216-025-91	METAL GLAZE	100	5%	1/10W
R246	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R349	1-216-025-91	METAL GLAZE	100	5%	1/10W
R247	1-216-073-00	METAL GLAZE	10K	5%	1/10W	R350	1-216-025-91	METAL GLAZE	100	5%	1/10W
R248	1-216-089-91	METAL GLAZE	47K	5%	1/10W	R351	1-216-025-91	METAL GLAZE	100	5%	1/10W
R250	1-216-295-91	CONDUCTOR, CHIP (2012)				R352	1-216-025-91	METAL GLAZE	100	5%	1/10W
R251	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R353	1-216-025-91	METAL GLAZE	100	5%	1/10W
R252	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R354	1-216-025-91	METAL GLAZE	100	5%	1/10W
R253	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R355	1-216-025-91	METAL GLAZE	100	5%	1/10W
R254	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R356	1-216-025-91	METAL GLAZE	100	5%	1/10W
R255	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R357	1-216-025-91	METAL GLAZE	100	5%	1/10W
R256	1-216-049-91	METAL GLAZE	1K	5%	1/10W	R358	1-216-025-91	METAL GLAZE	100	5%	1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK
R359	1-216-025-91	METAL GLAZE	100 5% 1/10W
R360	1-216-025-91	METAL GLAZE	100 5% 1/10W
R361	1-216-025-91	METAL GLAZE	100 5% 1/10W
R362	1-216-025-91	METAL GLAZE	100 5% 1/10W
R363	1-216-025-91	METAL GLAZE	100 5% 1/10W
R364	1-216-025-91	METAL GLAZE	100 5% 1/10W
R365	1-216-025-91	METAL GLAZE	100 5% 1/10W
R366	1-216-025-91	METAL GLAZE	100 5% 1/10W
R367	1-216-037-00	METAL GLAZE	330 5% 1/10W
R370	1-216-037-00	METAL GLAZE	330 5% 1/10W
R373	1-216-037-00	METAL GLAZE	330 5% 1/10W
R374	1-216-025-91	METAL GLAZE	100 5% 1/10W
R375	1-216-025-91	METAL GLAZE	100 5% 1/10W
R376	1-216-025-91	METAL GLAZE	100 5% 1/10W
R377	1-216-025-91	METAL GLAZE	100 5% 1/10W
R378	1-216-025-91	METAL GLAZE	100 5% 1/10W
R379	1-216-025-91	METAL GLAZE	100 5% 1/10W
R380	1-216-025-91	METAL GLAZE	100 5% 1/10W
R381	1-216-025-91	METAL GLAZE	100 5% 1/10W
R382	1-216-025-91	METAL GLAZE	100 5% 1/10W
R383	1-216-025-91	METAL GLAZE	100 5% 1/10W
R384	1-216-025-91	METAL GLAZE	100 5% 1/10W
R385	1-216-025-91	METAL GLAZE	100 5% 1/10W
R386	1-216-025-91	METAL GLAZE	100 5% 1/10W
R387	1-216-025-91	METAL GLAZE	100 5% 1/10W
R388	1-216-025-91	METAL GLAZE	100 5% 1/10W
R389	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R390	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R391	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R392	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R393	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R394	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R395	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R398	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R399	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R400	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R401	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R402	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R403	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R404	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R405	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R406	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R407	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R408	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R409	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R410	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R411	1-216-049-91	METAL GLAZE	1K 5% 1/10W
R412	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R413	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R414	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R415	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R416	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R417	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R418	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R419	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R420	1-216-047-91	METAL GLAZE	820 5% 1/10W
R421	1-216-025-91	METAL GLAZE	100 5% 1/10W
R422	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R423	1-216-017-91	METAL GLAZE	47 5% 1/10W

REF NO.	PART NO.	DESCRIPTION	REMARK
R424	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R425	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R426	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R428	1-216-295-91	CONDUCTOR, CHIP (2012)	
R429	1-216-073-00	METAL GLAZE	10K 5% 1/10W
R432	1-216-295-91	CONDUCTOR, CHIP (2012)	
R434	1-216-025-91	METAL GLAZE	100 5% 1/10W
< SWITCH >			
S100	1-570-598-11	SWITCH, DIP	
S101	1-571-674-11	SWITCH, SLIDE	
S102	1-570-204-21	SWITCH, KEY BOARD	
S400	1-571-674-11	SWITCH, SLIDE	
< TERMINAL BOARD >			
TB101	* 1-694-209-11	TERMINAL BOARD ASSY, I/O	
• TEST PIN •			
TP100	* 1-535-877-22	CHIP, CHECKER	
TP101	* 1-535-877-22	CHIP, CHECKER	
TP102	* 1-535-877-22	CHIP, CHECKER	
TP103	* 1-535-877-22	CHIP, CHECKER	
TP104	* 1-535-877-22	CHIP, CHECKER	
TP105	* 1-535-877-22	CHIP, CHECKER	
TP106	* 1-535-877-22	CHIP, CHECKER	
TP107	* 1-535-877-22	CHIP, CHECKER	
TP108	* 1-535-877-22	CHIP, CHECKER	
TP109	* 1-535-877-22	CHIP, CHECKER	
TP110	* 1-535-877-22	CHIP, CHECKER	
TP111	* 1-535-877-22	CHIP, CHECKER	
TP112	* 1-535-877-22	CHIP, CHECKER	
TP113	* 1-535-877-22	CHIP, CHECKER	
TP114	* 1-535-877-22	CHIP, CHECKER	
TP115	* 1-535-877-22	CHIP, CHECKER	
TP116	* 1-535-877-22	CHIP, CHECKER	
TP117	1-537-864-11	PIN, POST	
TP118	* 1-535-877-22	CHIP, CHECKER	
TP119	* 1-535-877-22	CHIP, CHECKER	
TP120	* 1-535-877-22	CHIP, CHECKER	
TP121	* 1-535-877-22	CHIP, CHECKER	
TP122	* 1-535-877-22	CHIP, CHECKER	
TP123	* 1-535-877-22	CHIP, CHECKER	
TP124	* 1-535-877-22	CHIP, CHECKER	
TP125	* 1-535-877-22	CHIP, CHECKER	
TP126	* 1-535-877-22	CHIP, CHECKER	
TP127	* 1-535-877-22	CHIP, CHECKER	
TP128	* 1-535-877-22	CHIP, CHECKER	
TP129	* 1-535-877-22	CHIP, CHECKER	
TP130	* 1-535-877-22	CHIP, CHECKER	
TP300	* 1-535-877-22	CHIP, CHECKER	
TP301	* 1-535-877-22	CHIP, CHECKER	
TP302	* 1-535-877-22	CHIP, CHECKER	
TP303	* 1-535-877-22	CHIP, CHECKER	
TP304	* 1-535-877-22	CHIP, CHECKER	
TP305	* 1-535-877-22	CHIP, CHECKER	
TP306	* 1-535-877-22	CHIP, CHECKER	
TP307	* 1-535-877-22	CHIP, CHECKER	
TP308	* 1-535-877-22	CHIP, CHECKER	

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
TP309	* 1-535-877-22	CHIP, CHECKER				< DIODE >	
TP310	* 1-535-877-22	CHIP, CHECKER		D1007	8-719-109-93	DIODE RD6.2ESB2	
TP311	* 1-535-877-22	CHIP, CHECKER		D1008	8-719-109-93	DIODE RD6.2ESB2	
TP312	* 1-535-877-22	CHIP, CHECKER		D1009	8-719-109-93	DIODE RD6.2ESB2	
TP313	* 1-535-877-22	CHIP, CHECKER		D1010	8-719-109-93	DIODE RD6.2ESB2	
				D1011	8-719-109-93	DIODE RD6.2ESB2	
TP314	* 1-535-877-22	CHIP, CHECKER		D1012	8-719-109-93	DIODE RD6.2ESB2	
TP315	* 1-535-877-22	CHIP, CHECKER		D1013	8-719-109-93	DIODE RD6.2ESB2	
TP316	* 1-535-877-22	CHIP, CHECKER		D1014	8-719-109-93	DIODE RD6.2ESB2	
TP317	* 1-535-877-22	CHIP, CHECKER		D1024	8-719-801-78	DIODE 1SS184	
TP318	* 1-535-877-22	CHIP, CHECKER				< IC >	
TP319	* 1-535-877-22	CHIP, CHECKER		IC1000	8-759-360-79	IC TC7W14F	
TP320	* 1-535-877-22	CHIP, CHECKER		IC1001	8-759-397-00	IC MAX489ECSO-TE2	
TP321	* 1-535-877-22	CHIP, CHECKER		IC1002	8-759-162-80	IC MM1170BFB	
TP322	* 1-535-877-22	CHIP, CHECKER		IC1008	8-759-421-41	IC HD6433337WA08F	
TP323	* 1-535-877-22	CHIP, CHECKER		IC1009	8-759-445-10	IC CY7C136-55JC-TEL	
TP325	* 1-535-877-22	CHIP, CHECKER		IC1010	8-759-925-90	IC SN74HC74ANS	
TP326	* 1-535-877-22	CHIP, CHECKER		IC1011	8-759-430-28	IC HM6264BLFP-10LTZ	
		< CRYSTAL >		IC1013	8-759-926-11	IC SN74HC138ANS	
X100	1-577-116-21	VIBRATOR, CRYSTAL (16MHz)		IC1014	8-759-925-79	IC SN74HC11ANS	
X101	1-567-781-41	VIBRATOR, CRYSTAL (4MHz)		IC1015	8-759-979-68	IC LM2931Z-5.0	
X300	1-577-116-21	VIBRATOR, CRYSTAL (16MHz)				< COIL >	
X301	1-578-687-11	VIBRATOR, CRYSTAL (12.288MHz)		L1000	1-412-533-21	INDUCTOR 47μH	
X302	1-577-116-21	VIBRATOR, CRYSTAL (16MHz)				< TRANSISTOR >	
*****				Q1003	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
				Q1004	8-729-230-49	TRANSISTOR 2SC2712-YG-TE85L	
* A-1394-818-A	YC COMPLETE PC BOARD					< RESISTOR >	
	*****			R1001	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
* 1-526-659-00	SOCKET, IC (DP) 28P			R1002	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
		< CAPACITOR >		R1003	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
C1000	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1004	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
C1001	1-164-004-11	CERAMIC CHIP 0.1MF 10% 25V		R1005	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
C1003	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1006	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
C1004	1-163-009-11	CERAMIC CHIP 0.001MF 10% 50V		R1007	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
C1012	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1008	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
C1013	1-163-231-11	CERAMIC CHIP 15PF 5% 50V		R1009	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1014	1-163-231-11	CERAMIC CHIP 15PF 5% 50V		R1011	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1017	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1012	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1018	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1013	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1019	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1014	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1020	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1015	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1021	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1016	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1022	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1017	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1023	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1018	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1024	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1019	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1025	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1020	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1026	1-124-584-00	ELECT 100MF 20% 10V		R1021	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1027	1-124-584-00	ELECT 100MF 20% 10V		R1022	1-216-295-91	CONDUCTOR, CHIP (2012)	
C1028	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1023	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1029	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1024	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1030	1-126-157-11	ELECT 10MF 20% 16V		R1025	1-216-025-91	METAL GLAZE 100 5% 1/10W	
C1203	1-163-031-11	CERAMIC CHIP 0.01MF 50V		R1026	1-216-073-00	METAL GLAZE 10K 5% 1/10W	
		< CONNECTOR >		R1027	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	
CN463	* 1-564-512-11	PLUG, CONNECTOR 9P		R1028	1-216-065-00	METAL GLAZE 4.7K 5% 1/10W	

YO

REF NO.	PART NO.	DESCRIPTION				REMARK	REF NO.	PART NO.	DESCRIPTION				REMARK
R1029	1-216-073-00	METAL GLAZE	10K	5%	1/10W		R1202	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1030	1-216-073-00	METAL GLAZE	10K	5%	1/10W		R1203	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1037	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W		R1204	1-216-295-91	CONDUCTOR, CHIP (2012)				
							R1205	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1038	1-216-065-00	METAL GLAZE	4.7K	5%	1/10W		R1206	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1040	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1041	1-216-025-91	METAL GLAZE	100	5%	1/10W		R1207	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1049	1-216-073-00	METAL GLAZE	10K	5%	1/10W		R1208	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1050	1-216-073-00	METAL GLAZE	10K	5%	1/10W		R1209	1-216-049-91	METAL GLAZE	1K	5%	1/10W	
							R1211	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1053	1-216-073-00	METAL GLAZE	10K	5%	1/10W		R1212	1-216-295-91	CONDUCTOR, CHIP (2012)				
R1054	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1057	1-216-073-00	METAL GLAZE	10K	5%	1/10W				< SWITCH >				
R1058	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1059	1-216-073-00	METAL GLAZE	10K	5%	1/10W		S1000	1-571-674-11	SWITCH, SLIDE				
							S1001	1-692-270-21	SWITCH, SLIDE				
R1060	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1061	1-216-073-00	METAL GLAZE	10K	5%	1/10W				< TERMINAL BOARD >				
R1063	1-216-295-91	CONDUCTOR, CHIP (2012)											
R1064	1-216-295-91	CONDUCTOR, CHIP (2012)					TB1001	* 1-694-208-11	TERMINAL BOARD ASSY, I/O				
R1065	1-216-025-91	METAL GLAZE	100	5%	1/10W								
									< TEST PIN >				
R1066	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1067	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1000	* 1-535-877-22	CHIP, CHECKER				
R1068	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1001	* 1-535-877-22	CHIP, CHECKER				
R1069	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1002	* 1-535-877-22	CHIP, CHECKER				
R1070	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1004	* 1-535-877-22	CHIP, CHECKER				
							TP1005	* 1-535-877-22	CHIP, CHECKER				
R1071	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1072	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1006	* 1-535-877-22	CHIP, CHECKER				
R1073	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1007	* 1-535-877-22	CHIP, CHECKER				
R1074	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1008	* 1-535-877-22	CHIP, CHECKER				
R1075	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1009	* 1-535-877-22	CHIP, CHECKER				
							TP1011	* 1-535-877-22	CHIP, CHECKER				
R1076	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1077	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1012	* 1-535-877-22	CHIP, CHECKER				
R1078	1-216-025-91	METAL GLAZE	100	5%	1/10W		TP1013	* 1-535-877-22	CHIP, CHECKER				
R1079	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1080	1-216-025-91	METAL GLAZE	100	5%	1/10W				< CRYSTAL >				
R1081	1-216-025-91	METAL GLAZE	100	5%	1/10W		X1000	1-577-116-21	VIBRATOR, CRYSTAL (16MHz)				
R1082	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1083	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1084	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1085	1-216-025-91	METAL GLAZE	100	5%	1/10W				* A-1373-586-A	YF MOUNTED PC BOARD			
R1086	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1087	1-216-025-91	METAL GLAZE	100	5%	1/10W				1-526-652-21	SOCKET, IC (DP) 8P			
R1088	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1089	1-216-025-91	METAL GLAZE	100	5%	1/10W				< CONNECTOR >				
R1090	1-216-025-91	METAL GLAZE	100	5%	1/10W								
							CN465	* 1-564-524-11	PLUG, CONNECTOR 9P				
R1100	1-216-025-91	METAL GLAZE	100	5%	1/10W								
R1101	1-216-025-91	METAL GLAZE	100	5%	1/10W				< SWITCH >				
R1102	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1103	1-216-073-00	METAL GLAZE	10K	5%	1/10W		S1501	1-572-853-11	SWITCH, ROTARY				
R1104	1-216-073-00	METAL GLAZE	10K	5%	1/10W		S1502	1-572-853-11	SWITCH, ROTARY				
R1105	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1106	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1107	1-216-073-00	METAL GLAZE	10K	5%	1/10W				* A-1390-732-A	YO MOUNTED PC BOARD			
R1108	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1109	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1110	1-216-073-00	METAL GLAZE	10K	5%	1/10W				1-526-660-21	SOCKET, IC (DP) 32P			
R1111	1-216-073-00	METAL GLAZE	10K	5%	1/10W				* 7-322-065-72	RUBBER, RTV (SE-9168) (130G)			
R1112	1-216-073-00	METAL GLAZE	10K	5%	1/10W								
R1113	1-216-073-00	METAL GLAZE	10K	5%	1/10W				< CAPACITOR >				
R1201	1-216-295-91	CONDUCTOR, CHIP (2012)											
							C1	1-163-031-11	CDRAMIC CHIP	0.01uF	50V		
							C2	1-163-031-11	CDRAMIC CHIP	0.01uF	50V		

REF NO.	PART NO.	DESCRIPTION	REMARK				REF NO.	PART NO.	DESCRIPTION	REMARK			
< IC >						C53	1-163-104-00	CERAMIC CHIP	30PF		50V		
IC2	8-759-925-76	IC SN74HC08ANS					C54	1-163-104-00	CERAMIC CHIP	30PF		50V	
							C55	1-163-104-00	CERAMIC CHIP	30PF		50V	
*****						C56	1-163-104-00	CERAMIC CHIP	30PF		50V		
* 9-939-547-01 IFB-40 MOUNTED PC BOARD						C57	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
*****						C58	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
< CAPACITOR >						C59	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C1	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C60	1-126-967-11	ELECT	47MF		16V		
C2	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C61	1-124-779-00	ELECT	10MF		16V		
C3	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C62	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C4	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C63	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C5	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C64	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C6	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C65	1-135-159-00	TANTAL CHIP	10MF		16V		
C7	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C66	1-163-231-91	CERAMIC CHIP	15PF		50V		
C8	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C67	1-126-923-91	ELECT	2200MF		10V		
C9	1-164-232-11	CERAMIC	1000PF		50V	C68	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C10	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	C69	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C11	1-164-232-11	CERAMIC	1000PF		50V	C71	1-124-779-00	ELECT	10MF		16V		
C12	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	C72	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C13	1-164-232-11	CERAMIC	1000PF		50V	C73	1-163-104-00	CERAMIC CHIP	30PF		50V		
C14	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	C74	1-163-104-00	CERAMIC CHIP	30PF		50V		
C15	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C75	1-163-104-00	CERAMIC CHIP	30PF		50V		
C16	1-135-159-00	TANTAL CHIP	10MF		16V	C76	1-163-104-00	CERAMIC CHIP	30PF		50V		
C17	1-135-159-00	TANTAL CHIP	10MF		16V	C77	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C18	1-135-159-00	TANTAL CHIP	10MF		16V	C78	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C19	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C79	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C20	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C80	1-126-967-11	ELECT	47MF		16V		
C21	1-135-159-00	TANTAL CHIP	10MF		16V	C81	1-124-779-00	ELECT	10MF		16V		
C22	1-135-159-00	TANTAL CHIP	10MF		16V	C82	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C23	1-135-159-00	TANTAL CHIP	10MF		16V	C83	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C24	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C84	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C25	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C85	1-135-159-00	TANTAL CHIP	10MF		16V		
C26	1-135-159-00	TANTAL CHIP	10MF		16V	C86	1-163-231-11	CERAMIC CHIP	15PF		50V		
C27	1-126-933-91	ELECT	100MF		16V	C87	1-126-923-91	ELECT 2200MF			10V		
C29	1-135-159-00	TANTAL CHIP	10MF		16V	C91	1-124-779-00	ELECT	10MF		16V		
C30	1-135-159-00	TANTAL CHIP	10MF		16V	C92	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C31	1-135-159-00	TANTAL CHIP	10MF		16V	C93	1-163-104-00	CERAMIC CHIP	30PF		50V		
C32	1-135-159-00	TANTAL CHIP	10MF		16V	C94	1-163-104-00	CERAMIC CHIP	30PF		50V		
C33	1-163-082-00	CERAMIC CHIP	0.5PF		50V	C95	1-163-104-00	CERAMIC CHIP	30PF		50V		
C34	1-124-779-00	ELECT	10MF		16V	C96	1-163-104-00	CERAMIC CHIP	30PF		50V		
C35	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C97	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C36	1-126-923-11	ELECT	2200MF		10V	C98	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C37	1-135-159-00	TANTAL CHIP	10MF		16V	C99	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C38	1-163-082-00	CERAMIC CHIP	0.5PF		50V	C100	1-126-967-11	ELECT	47MF		16V		
C39	1-124-779-00	ELECT	10MF		16V	C101	1-124-779-00	ELECT	10MF		16V		
C40	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C102	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C41	1-126-923-91	ELECT	2200MF		10V	C103	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C42	1-135-159-00	TANTAL CHIP	10MF		16V	C104	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C43	1-163-082-00	CERAMIC CHIP	0.5PF		50V	C105	1-135-159-00	TANTAL CHIP	10MF		16V		
C44	1-124-779-00	ELECT	10MF		16V	C106	1-163-231-91	CERAMIC CHIP	15PF		50V		
C45	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C107	1-126-923-91	ELECT	2200MF		10V		
C46	1-126-923-91	ELECT	2200MF		10V	C110	1-126-933-91	ELECT	100MF		16V		
C47	1-135-159-00	TANTAL CHIP	10MF		16V	C111	1-126-967-11	ELECT	47MF		16V		
C48	1-135-159-00	TANTAL CHIP	10MF		16V	C112	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C51	1-124-779-00	ELECT	10MF		16V	C113	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
C52	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V	C114	1-126-925-91	ELECT	470MF		10V		
						C115	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
						C116	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		
						C117	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V		

REF NO.	PART NO.	DESCRIPTION	REMARK			REF NO.	PART NO.	DESCRIPTION	REMARK		
C118	1-124-779-00	ELECT	10MF	16V		IC24	8-759-708-05	IC NJM78L05A			
C119	1-124-779-00	ELECT	10MF	16V		IC25	8-759-231-57	IC TA7810S			
C120	1-124-779-00	ELECT	10MF	16V							
C121	1-124-779-00	ELECT	10MF	16V		IC26	8-759-708-05	IC NJM78L05A			
C122	1-164-004-11	CERAMIC CHIP	0.1MF	25V	10%	IC27	8-759-710-78	IC NJM082BM			
C123	1-135-159-00	TANTAL CHIP	10MF	16V		IC27	8-759-338-94	IC NJM2903M			
								< JACK >			
C124	1-135-159-00	TANTAL CHIP	10MF	16V							
		< CONNECTOR >				J1	9-939-564-01	CONNECTOR (MALE)(DIN)(96P)			
CN1	9-939-543-01	CONNECTOR (MALE)(14P)				J2	1-564-512-11	CONNECTOR (9P)			
CN2	9-939-544-01	CONNECTOR (FEMALE)(14P)				J3	1-564-505-11	CONNECTOR (2P)			
CN3	9-939-546-01	MINI JACK				J4	1-564-505-11	CONNECTOR (2P)			
		< VIBRATOR >				J5	1-564-505-11	CONNECTOR (2P)			
CR1	9-939-555-01	CR MODULE				J6	1-564-512-11	CONNECTOR (9P)			
CR2	9-939-555-01	CR MODULE				J7	1-564-509-11	CONNECTOR (6P)			
CR3	9-939-555-01	CR MODULE						< LED >			
		< DIODE >				LD1	9-939-552-01	LED VR3668S			
								< TRANSISTOR >			
D1	8-719-800-76	DIODE 1SS226				Q1	8-729-421-26	TRANSISTOR RN1310			
D2	8-719-800-76	DIODE 1SS226				Q2	9-939-536-01	TRANSISTOR RN1423			
D3	8-719-157-88	DIODE RD2.7SB				Q3	9-939-536-01	TRANSISTOR RN1423			
D5	8-719-800-76	DIODE 1SS226				Q4	9-939-536-01	TRANSISTOR RN1423			
D6	8-719-800-76	DIODE 1SS226				Q5	9-939-536-01	TRANSISTOR RN1423			
D7	8-719-800-76	DIODE 1SS226				Q6	9-939-536-01	TRANSISTOR RN1423			
D8	8-719-800-76	DIODE 1SS226				Q7	8-729-421-26	TRANSISTOR RN1310			
D9	8-719-800-76	DIODE 1SS226				Q8	9-939-537-01	TRANSISTOR HN1B01F			
D10	8-719-800-76	DIODE 1SS226				Q9	9-939-537-01	TRANSISTOR HN1B01F			
D11	8-719-800-76	DIODE 1SS226				Q10	8-729-421-26	TRANSISTOR RN1310			
D12	8-719-800-76	DIODE 1SS226				Q11	8-729-421-26	TRANSISTOR RN1310			
D13	8-719-800-76	DIODE 1SS226				Q12	9-939-537-01	TRANSISTOR HN1B01F			
D14	8-719-159-06	DIODE RD4.7SB				Q13	9-939-537-01	TRANSISTOR HN1B01F			
D15	8-719-157-88	DIODE RD2.7SB				Q14	8-729-421-26	TRANSISTOR RN1310			
		< IC >				Q15	9-939-539-01	TRANSISTOR HN1A01F			
IC1	8-759-981-61	IC LM2901M				Q16	9-939-539-01	TRANSISTOR HN1A01F			
IC2	8-759-925-80	IC SN74HC14ANS				Q17	9-939-539-01	TRANSISTOR HN1A01F			
IC3	8-759-925-72	IC SN74HC02ANS				Q18	9-939-537-01	TRANSISTOR HN1B01F			
IC4	8-759-925-85	IC SN74HC32ANS				Q19	8-729-421-26	TRANSISTOR RN1310			
IC5	8-759-710-78	IC NJM082BM				Q20	9-939-536-01	TRANSISTOR RN1423			
IC6	8-759-092-80	IC SN75157PS				Q21	8-729-216-22	TRANSISTOR 2SA1162-G			
IC7	8-759-239-25	IC TC74HC4066AF				Q22	9-939-551-01	TRANSISTOR 2SA1388			
IC8	9-939-532-01	IC OPA658U				Q23	8-729-421-26	TRANSISTOR RN1310			
IC9	9-939-532-01	IC OPA658U				Q24	8-729-421-26	TRANSISTOR RN1310			
IC10	9-939-532-01	IC OPA658U				Q25	9-939-538-01	TRANSISTOR HN1C01F			
IC11	9-939-532-01	IC OPA658U				Q26	8-729-421-26	TRANSISTOR RN1310			
IC12	9-939-532-01	IC OPA658U				Q27	8-729-421-26	TRANSISTOR RN1310			
IC13	9-939-532-01	IC OPA658U				Q28	8-729-421-26	TRANSISTOR RN1310			
IC14	9-939-534-01	IC MPC100AU				Q29	8-729-421-26	TRANSISTOR RN1310			
IC15	9-939-534-01	IC MPC100AU				Q30	8-729-421-26	TRANSISTOR RN1310			
IC16	9-939-534-01	IC MPC100AU				Q32	9-939-536-01	TRANSISTOR RN1423			
IC17	9-939-532-01	IC OPA658U						< RESISTOR >			
IC18	9-939-532-01	IC OPA658U				R1	1-216-025-91	METAL, CHIP	100	5%	
IC19	9-939-532-01	IC OPA658U				R2	1-216-057-00	METAL, CHIP	2.2K	5%	
IC20	8-759-710-78	IC NJM082BM				R3	1-216-081-00	METAL, CHIP	22K	5%	
						R4	1-216-049-91	METAL, CHIP	1K	5%	
IC21	8-759-011-65	IC MC74HC4053F				R5	1-216-081-00	METAL, CHIP	22K	5%	
IC22	8-759-011-65	IC MC74HC4053F									
IC23	9-939-533-01	IC SN75453BPS									

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
R6	1-216-049-91	METAL, CHIP	1K 5% 1/10W	R66	1-216-642-11	METAL, CHIP	430 1% 1/10W
R7	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R67	1-216-624-11	METAL, CHIP	75 1% 1/10W
R8	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R68	1-216-624-11	METAL, CHIP	75 5% 1/10W
R9	1-216-009-91	METAL, CHIP	22 5% 1/10W	R69	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R10	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R70	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R11	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R71	1-216-624-11	METAL, CHIP	75 1% 1/10W
R12	1-216-073-00	METAL, CHIP	10K 5% 1/10W	R72	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R13	1-216-009-91	METAL, CHIP	22 5% 1/10W	R73	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R14	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R74	1-216-649-91	METAL, CHIP	820 1% 1/10W
R15	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R75	1-216-649-91	METAL, CHIP	820 1% 1/10W
R16	1-216-073-00	METAL, CHIP	10K 5% 1/10W	R76	1-216-009-91	METAL, CHIP	22 5% 1/10W
R17	1-216-009-91	METAL, CHIP	22 5% 1/10W	R77	1-216-642-11	METAL, CHIP	430 1% 1/10W
R18	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R78	1-216-624-11	METAL, CHIP	75 1% 1/10W
R19	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R79	1-216-624-11	METAL, CHIP	75 1% 1/10W
R20	1-216-073-00	METAL, CHIP	10K 5% 1/10W	R80	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R21	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R81	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R22	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W	R82	1-216-624-11	METAL, CHIP	75 1% 1/10W
R23	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W	R83	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R24	1-216-041-00	METAL, CHIP	470 5% 1/10W	R84	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R25	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R85	1-216-649-91	METAL, CHIP	820 1% 1/10W
R26	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R86	1-216-649-91	METAL, CHIP	820 1% 1/10W
R27	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W	R87	1-216-009-91	METAL, CHIP	22 5% 1/10W
R28	1-216-073-00	METAL, CHIP	10K 5% 1/10W	R88	1-216-642-11	METAL, CHIP	430 1% 1/10W
R29	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R89	1-216-624-11	METAL, CHIP	75 1% 1/10W
R30	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R90	1-216-624-11	METAL, CHIP	75 1% 1/10W
R31	1-216-073-00	METAL, CHIP	10K 5% 1/10W	R91	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R32	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R92	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R33	1-216-053-91	METAL, CHIP	1.5K 5% 1/10W	R110	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R34	1-216-089-91	METAL, CHIP	47K 5% 1/10W	R111	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R35	1-216-624-11	METAL, CHIP	75 1% 1/10W	R112	1-216-009-91	METAL, CHIP	22 5% 1/10W
R36	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R113	1-216-642-11	METAL, CHIP	430 1% 1/10W
R37	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R114	1-216-633-11	METAL, CHIP	180 1% 1/10W
R38	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R115	1-216-628-91	METAL, CHIP	110 1% 1/10W
R39	1-216-097-91	METAL, CHIP	100K 5% 1/10W	R116	1-216-624-11	METAL, CHIP	75 1% 1/10W
R40	1-216-089-91	METAL, CHIP	47K 5% 1/10W	R117	1-216-308-00	METAL, CHIP	4.7 5% 1/10W
R41	1-216-089-91	METAL, CHIP	47K 5% 1/10W	R118	1-216-625-11	METAL, CHIP	82 1% 1/10W
R42	1-216-097-91	METAL, CHIP	100K 5% 1/10W	R119	1-216-631-91	METAL, CHIP	150 1% 1/10W
R43	1-216-624-11	METAL, CHIP	75 1% 1/10W	R120	1-216-633-11	METAL, CHIP	180 1% 1/10W
R44	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R121	1-208-767-11	METAL, CHIP	240 1% 1/10W
R45	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R122	1-216-624-11	METAL, CHIP	75 1% 1/10W
R46	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W	R123	1-216-624-11	METAL, CHIP	75 1% 1/10W
R47	1-216-097-91	METAL, CHIP	100K 5% 1/10W	R124	1-216-624-11	METAL, CHIP	75 1% 1/10W
R48	1-216-089-91	METAL, CHIP	47K 5% 1/10W	R125	1-216-624-11	METAL, CHIP	75 1% 1/10W
R49	1-216-089-91	METAL, CHIP	47K 5% 1/10W	R126	1-216-009-91	METAL, CHIP	22 5% 1/10W
R50	1-216-097-91	METAL, CHIP	100K 5% 1/10W	R127	1-216-009-91	METAL, CHIP	22 5% 1/10W
R51	1-216-121-91	METAL, CHIP	1M 5% 1/10W	R128	1-216-009-91	METAL, CHIP	22 5% 1/10W
R52	1-216-097-91	METAL, CHIP	100K 5% 1/10W	R129	1-216-009-91	METAL, CHIP	22 5% 1/10W
R53	1-216-089-91	METAL, CHIP	47K 5% 1/10W	R130	1-216-009-91	METAL, CHIP	22 5% 1/10W
R54	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W	R131	1-216-621-91	METAL, CHIP	56 1% 1/10W
R55	1-216-121-91	METAL, CHIP	1M 5% 1/10W	R132	1-216-049-91	METAL, CHIP	1K 5% 1/10W
R56	1-216-121-91	METAL, CHIP	1M 5% 1/10W	R133	1-216-641-11	METAL, CHIP	390 1% 1/10W
R57	1-216-121-91	METAL, CHIP	1M 5% 1/10W	R134	1-216-121-91	METAL, CHIP	1M 5% 1/10W
R58	1-216-121-91	METAL, CHIP	1M 5% 1/10W	R135	1-216-121-91	METAL, CHIP	1M 5% 1/10W
R60	1-216-624-11	METAL, CHIP	75 1% 1/10W	R136	1-216-097-91	METAL, CHIP	100K 5% 1/10W
R61	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R137	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R62	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R138	1-216-049-91	METAL, CHIP	1K 5% 1/10W
R63	1-216-649-91	METAL, CHIP	820 1% 1/10W	R139	1-216-624-11	METAL, CHIP	75 1% 1/10W
R64	1-216-649-91	METAL, CHIP	820 1% 1/10W	R140	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R65	1-216-009-91	METAL, CHIP	22 5% 1/10W				

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
R141	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R199	1-216-624-11	METAL, CHIP	75 1% 1/10W
R142	1-216-009-91	METAL, CHIP	22 5% 1/10W	R200	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R143	1-216-642-11	METAL, CHIP	430 1% 1/10W	R201	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R144	1-216-633-11	METAL, CHIP	180 1% 1/10W	R202	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R145	1-216-628-91	METAL, CHIP	110 1% 1/10W	R203	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R146	1-216-624-11	METAL, CHIP	75 1% 1/10W	R204	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R147	1-216-308-00	METAL, CHIP	4.7 5% 1/10W	R205	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R148	1-216-625-11	METAL, CHIP	82 1% 1/10W	R206	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R149	1-216-631-91	METAL, CHIP	150 1% 1/10W	R207	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R150	1-216-633-11	METAL, CHIP	180 1% 1/10W	R208	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R151	1-208-767-11	METAL, CHIP	240 1% 1/10W	R209	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R152	1-216-624-11	METAL, CHIP	75 1% 1/10W	R210	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R153	1-216-624-11	METAL, CHIP	75 1% 1/10W	R211	9-939-554-01	CARBON	33 1W F
R154	1-216-624-11	METAL, CHIP	75 1% 1/10W	R212	9-939-553-01	METAL, CHIP	150 5% 1/4W
R155	1-216-624-11	METAL, CHIP	75 1% 1/10W	R213	9-939-553-01	METAL, CHIP	150 5% 1/4W
R156	1-216-009-91	METAL, CHIP	22 5% 1/10W	R214	1-216-017-91	METAL, CHIP	47 5% 1/10W
R157	1-216-009-91	METAL, CHIP	22 5% 1/10W	R215	1-216-017-91	METAL, CHIP	47 5% 1/10W
R158	1-216-009-91	METAL, CHIP	22 5% 1/10W	R216	1-216-041-00	METAL, CHIP	470 5% 1/10W
R159	1-216-009-91	METAL, CHIP	22 5% 1/10W	R217	1-216-633-11	METAL, CHIP	180 1% 1/10W
R160	1-216-009-91	METAL, CHIP	22 5% 1/10W	R218	1-216-049-91	METAL, CHIP	1K 5% 1/10W
R161	1-216-621-91	METAL, CHIP	56 1% 1/10W	R219	1-216-049-91	METAL, CHIP	1K 5% 1/10W
R162	1-216-049-91	METAL, CHIP	1K 5% 1/10W	R220	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W
R163	1-216-641-11	METAL, CHIP	390 1% 1/10W	R221	1-216-041-00	METAL, CHIP	470 5% 1/10W
R164	1-216-121-91	METAL, CHIP	1M 5% 1/10W	R222	1-216-041-00	METAL, CHIP	470 5% 1/10W
R165	1-216-121-91	METAL, CHIP	1M 5% 1/10W	R223	1-249-470-11	CARBON	0.47 1/2W F
R166	1-216-097-91	METAL, CHIP	100K 5% 1/10W	R224	1-216-049-91	METAL, CHIP	1K 5% 1/10W
R167	1-216-073-00	METAL, CHIP	10K 5% 1/10W	R225	1-216-049-91	METAL, CHIP	1K 5% 1/10W
R168	1-216-049-91	METAL, CHIP	1K 5% 1/10W	R226	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W
R169	1-216-624-11	METAL, CHIP	75 1% 1/10W	R227	1-216-041-00	METAL, CHIP	470 5% 1/10W
R170	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R228	1-216-071-91	METAL, CHIP	8.2K 5% 1/10W
R171	1-216-081-00	METAL, CHIP	22K 5% 1/10W	R229	1-216-066-91	METAL, CHIP	5.1K 5% 1/10W
R172	1-216-009-91	METAL, CHIP	22 5% 1/10W	R230	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W
R173	1-216-642-11	METAL, CHIP	430 1% 1/10W	R231	1-216-073-00	METAL, CHIP	10K 5% 1/10W
R174	1-216-633-11	METAL, CHIP	180 1% 1/10W	R232	1-216-049-91	METAL, CHIP	1K 5% 1/10W
R175	1-216-628-91	METAL, CHIP	110 1% 1/10W	R233	1-216-065-00	METAL, CHIP	4.7K 5% 1/10W
R176	1-216-624-11	METAL, CHIP	75 1% 1/10W	R234	1-216-097-91	METAL, CHIP	100K 5% 1/10W
R177	1-216-308-00	METAL, CHIP	4.7 5% 1/10W	R235	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R178	1-216-625-11	METAL, CHIP	82 1% 1/10W	R236	1-216-089-91	METAL, CHIP	47K 5% 1/10W
R179	1-216-631-91	METAL, CHIP	150 1% 1/10W	R237	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W
R180	1-216-633-11	METAL, CHIP	180 1% 1/10W	R238	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W
R181	1-208-767-11	METAL, CHIP	240 1% 1/10W	R239	1-216-097-91	METAL, CHIP	100K 5% 1/10W
R182	1-216-624-11	METAL, CHIP	75 1% 1/10W	R240	1-216-081-00	METAL, CHIP	22K 5% 1/10W
R183	1-216-624-11	METAL, CHIP	75 1% 1/10W	R241	1-216-089-91	METAL, CHIP	47K 5% 1/10W
R184	1-216-624-11	METAL, CHIP	75 1% 1/10W	R242	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W
R185	1-216-624-11	METAL, CHIP	75 1% 1/10W	R243	1-216-057-00	METAL, CHIP	2.2K 5% 1/10W
R186	1-216-009-91	METAL, CHIP	22 5% 1/10W	< RELAY >			
R187	1-216-009-91	METAL, CHIP	22 5% 1/10W	RY1	9-901-739-01	RELAY	
R188	1-216-009-91	METAL, CHIP	22 5% 1/10W	RY2	9-901-739-01	RELAY	
R189	1-216-009-91	METAL, CHIP	22 5% 1/10W	RY3	9-901-739-01	RELAY	
R190	1-216-009-91	METAL, CHIP	22 5% 1/10W	< SWITCH >			
R191	1-216-621-91	METAL, CHIP	56 1% 1/10W	SW1	9-939-540-01	SWITCH, ROTARY	
R192	1-216-049-91	METAL, CHIP	1K 5% 1/10W	SW2	9-939-541-01	SWITCH, SLIDE	
R193	1-216-641-11	METAL, CHIP	390 1% 1/10W	*****			
R194	1-216-121-91	METAL, CHIP	1M 5% 1/10W				
R195	1-216-121-91	METAL, CHIP	1M 5% 1/10W				
R196	1-216-097-91	METAL, CHIP	100K 5% 1/10W				
R197	1-216-073-00	METAL, CHIP	10K 5% 1/10W				
R198	1-216-049-91	METAL, CHIP	1K 5% 1/10W				

The components identified by shading and marked Δ are critical for safety.

Replace only with the part number specified.

Les composants identifiés par une trame et une marque Δ sont critiques pour la sécurité.

Ne les remplacer que par une pièce portant le numéro spécifié.

REF NO.	PART NO.	DESCRIPTION	REMARK	REF NO.	PART NO.	DESCRIPTION	REMARK
		MISCELLANEOUS *****					
	Δ 1-251-263-11	INLET, AC			* 4-055-850-01	CUSHION (UPPER) (ASSY)	
	Δ 1-451-449-11	DEFLECTION YOKE			* 4-055-860-01	INDIVIDUAL CARTON (G70QM)	
	Δ 1-452-880-11	NECK ASSEMBLY (NA-2911)			* 4-057-520-01	INDIVIDUAL CARTON (G70Q)	
	Δ 1-452-881-11	NECK ASSEMBLY (NA-2912)			* 4-057-521-01	INDIVIDUAL CARTON (G70QMG)	
	Δ 1-453-108-11	DC BLOCK, HIGH-VOLTAGE			4-057-924-11	CAP (A), LENS	
	Δ 1-453-108-31	DC BLOCK, HIGH-VOLTAGE			4-396-077-01	JOINT	
	1-473-900-11	REMOTE COMMANDER (RM-PJ1000)			A-1500-012-A	BATTERY ASSY	
	1-533-702-11	HOLDER, FUSE			* X-4033-984-1	TRAY ASSY, BASE	
	1-900-228-18	CONNECTOR (C-G) ASSY, RELAY					
	1-900-228-19	CONNECTOR (C-B) ASSY, RELAY					
	1-900-229-29	CONNECTOR ASSY, MICRO 3P					
	1-900-229-30	TERMINAL ASSY, FASTON					
	1-900-229-32	CONNECTOR ASSY, H-V (S)					
	1-900-229-35	CONNECTOR ASSY, RELAY					
	1-900-229-36	CONNECTOR ASSY, MICRO 9P					
	1-900-229-37	CONNECTOR ASSY, MICRO 13P					
	1-900-229-40	CONNECTOR (L) ASSY, VH 3P					
	1-900-229-44	TERMINAL (L) ASSY, FASTON					
	1-900-229-53	CONNECTOR (DY-R) ASSY, RELA					
	1-900-229-54	CONNECTOR (DY-G) ASSY, RELAY					
	1-900-229-55	CONNECTOR (DY-B) ASSY, RELAY					
	1-900-229-60	CONNECTOR ASSY (S), VH 3P					
	1-900-229-85	TERMINAL (L) ASSY, FASTON					
	1-900-229-86	TERMINAL (N) ASSY, FASTON					
	A-1501-056-A	FAN ASSY					
	* X-4034-374-2	CASE ASSY, REAR					
F1	Δ 1-533-576-11	FUSE, TIME-LAG ((UL)ET) (G70QM/G70QMG)					
F1	Δ 1-533-694-11	FUSE GLASS ((UL)ET)(10A 250V)(G70Q)					
S901	Δ 1-762-870-11	SWITCH, AC POWER SEESAW					
V901	Δ A-1501-115-A	COUPLING (R) ASSY, CRT					
V902	Δ A-1501-116-A	COUPLING (G) ASSY, CRT					
V903	Δ A-1501-117-A	COUPLING (B) ASSY, CRT					

		ACCESSORIES AND PACKING MATERIAL *****					
	1-473-899-11	REMOTE COMMANDER (RM-PJ1000)					
	Δ 1-500-037-11	CORE, FERRITE (WITH CASE) (AC CORD) (G70Q)					
	Δ 1-575-175-11	CORD SET, POWER (G70QM/G70QMG)					
	1-696-607-11	CORD, CONNECTION (WITH PLUG)					
	1-782-021-11	CORD, CONNECTION					
	1-900-229-31	CONNECTOR ASSY, H-V (M)					
	3-701-616-01	BAG, POLYETHYLENE					
	* 3-704-356-01	SHEET (STANDARD), PROTECTION					
	3-858-606-11	MANUAL, INSTRUCTION (ENGLISH/FRENCH/SPANISH) (G70QMG)					
	3-858-606-21	MANUAL, INSTRUCTION (GERMAN/ITALIAN) (G70QMG)					
	3-858-607-11	MANUAL, INSTALLATION (ENGLISH/FRENCH/SPANISH) (G70QMG)					
	3-858-607-21	MANUAL, INSTALLATION (GERMAN/ITALIAN) (G70QMG)					
	3-858-608-11	MANUAL, INSTRUCTION (ENGLISH/FRENCH/SPANISH) (G70Q/70QMG)					
	3-858-608-21	MANUAL, INSTRUCTION (CHINESE) (G70QM)					
	3-858-609-11	MANUAL, INSTALLATION (ENGLISH/FRENCH/SPANISH) (G70Q/70QMG)					
	3-858-609-21	MANUAL, INSTALLATION (CHINESE) (G70QM)					

